

PART 1 - GENERAL

- | | |
|-----------------------|---|
| <u>1.1 References</u> | .1 CSA C22.1, Canadian Electrical Code, Part 1. |
|-----------------------|---|

PART 2 - PRODUCTS

- | | |
|---|--|
| <u>2.1 Outlet and
Conduit Boxes
General</u> | .1 Size boxes in accordance with CSA C22.1. |
| | .2 102 mm square or larger outlet boxes as required for special devices. |
| | .3 Gang boxes where wiring devices are grouped. |
| | .4 Blank cover plates for boxes without wiring devices. |
| | .5 347 V outlet boxes for 347 V switching devices. |
| | .6 Combination boxes with barriers where outlets for more than one system are grouped. |
| <u>2.2 Sheet Steel
Outlet Boxes</u> | .1 Electro-galvanized steel single and multi gang flush device boxes for flush installation, minimum size 76 x 50 x 38 mm or as indicated. 102 mm square outlet boxes when more than one conduit enters one side with extension and plaster rings as required. |
| | .2 Electro-galvanized steel utility boxes for outlets connected to surface-mounted EMT |

conduit, minimum size 102 x 54 x 48 mm.

- .3 102 mm square or octagonal outlet boxes for lighting fixture outlets.
- .4 102 mm square outlet boxes with extension and plaster rings for flush mounting devices in finished plaster walls.

2.3 Masonry Boxes

- .1 Electro-galvanized steel masonry single and multi gang boxes for devices flush mounted in exposed block walls.

2.4 Concrete Boxes

- .1 Electro-glavanized sheet steel concrete type boxes for flush mount in concrete with matching extension and plaster rings as required.

2.5 Floor Boxes

- .1 Concrete tight electro-galvanized sheet steel floor boxes with adjustable finishing rings to suit floor finish with brass faceplate. Device mounting plate to accommodate short or long ear duplex receptacles. Minimum depth: 28 mm for receptacles; 73 mm for communication equipment.
- .2 Adjustable, watertight, concrete tight, cast floor boxes with openings drilled and tapped for 12 mm and 19 mm conduit. Minimum size: 73 mm deep.

2.6 Conduit Boxes

- .1 Cast FS or FD aluminum boxes with factory-threaded hubs and mounting feet for surface wiring of switches and receptacle.

2.7 Fittings -
General

- .1 Bushing and connectors with nylon insulated throats.
- .2 Knock-out fillers to prevent entry of debris.
- .3 Conduit outlet bodies for conduit up to 32 mm and pull boxes for larger conduits.
- .4 Double locknuts and insulated bushings on sheet metal boxes.

2.8 Service
Fittings

- .1 'High tension' receptacle fitting made of 2 piece die-cast aluminum with brushed aluminum housing finish for 1 duplex receptacles. Bottom plate with two knockouts for centered or offset installation. 12 x 102 mm extension piece as indicated.
- .2 Pedestal type 'low tension' fitting made of 2 piece die cast aluminum with brushed aluminum housing finish to accommodate two amphenol jack connectors.

PART 3 - EXECUTION

3.1 Installation

- .1 Support boxes independently of connecting conduits.
- .2 Fill boxes with paper, sponges or foam or similar approved material to prevent entry of debris during construction. Remove upon completion of work.
- .3 For flush installations mount outlets flush with finished wall using plaster rings to permit

wall finish to come within 6 mm of opening.

- .4 Provide correct size of openings in boxes for conduit, mineral insulated and armoured cable connections. Reducing washers are not allowed.