
PART 1 **GENERAL**

1.1 **SECTION INCLUDES**

- .1 Materials and installation for standard breaker type panelboards.

1.2 **RELATED SECTIONS**

- .1 Section 01 33 00 - Submittal Procedures.
- .2 Section 01 74 21 – Construction/Demolition Waste Management and Disposal.
- .3 Section 26 05 00 - Common Work Results – Electrical.
- .4 Section 26 28 16.02 - Moulded Case Circuit Breakers.

1.3 **REFERENCES**

- .1 Canadian Standards Association (CSA International)
 - .1 CSA C22.2 No.29-M1989, Panelboards and enclosed Panelboards.

1.4 **SHOP DRAWINGS**

- .1 Submit shop drawings in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Drawings to include electrical detail of panel, branch breaker type, quantity, ampacity and enclosure dimension.

1.5 **WASTE MANAGEMENT AND DISPOSAL**

- .1 Separate and recycle waste materials in accordance with Section 01 74 21 - Construction/Demolition Waste Management And Disposal.
- .2 Remove from site and dispose of packaging materials at appropriate recycling facilities.
- .3 Collect and separate for disposal paper, plastic, polystyrene, corrugated cardboard packaging material in appropriate on-site bins for recycling in accordance with Waste Management Plan.
- .4 Divert unused metal and wiring materials from landfill to metal recycling facility approved by Departmental Representative.

PART 2 **PRODUCTS**

2.1 **PANELBOARDS**

- .1 Panelboards: to CSA C22.2 No.29 and product of one manufacturer.
 - .1 Install circuit breakers in panelboards before shipment.
 - .2 In addition to CSA requirements manufacturer's nameplate must show fault current that panel including breakers has been built to withstand.
- .2 250 and 600 V panelboards: bus and breakers rated for 10 KA and 22 KA, respectively (symmetrical) interrupting capacity if not indicated otherwise.
- .3 Sequence phase bussing with odd numbered breakers on left and even on right, with each breaker identified by permanent number identification as to circuit number and phase.
- .4 Panelboards: mains, number of circuits, and number and size of branch circuit breakers as indicated.
- .5 Locking cover latch with two keys for each panelboard and key all panelboards alike.
- .6 Copper bus including neutral of same ampere rating as mains.
- .7 Mains: suitable for bolt-on breakers.
- .8 Trim with concealed front bolts and hinges.
- .9 Trim and door finish: baked grey enamel air dried grey enamel as per colour schedule.
- .10 Refer to Section 26 05 00 for equipment colours.
- .11 All panelboards shall be equipped with required provisions to provide a sprinklerproof rating as per CSA C22.1 – Canadian Electrical Code.

2.2 **BREAKERS**

- .1 Breakers: to Section 26 28 16.02 - Moulded Case Circuit Breakers.
- .2 Breakers with thermal and magnetic tripping in panelboards except as indicated otherwise.
- .3 Main breaker: separately mounted on top or bottom of panel to suit cable entry. When mounted vertically, down position should open breaker.
- .4 Lock-on devices for 10% of 15 to 30 A breakers installed as indicated. Turn over unused lock-on devices to Departmental Representative.

2.3 EQUIPMENT IDENTIFICATION

- .1 Provide equipment identification in accordance with Section 26 05 00 - Common Work Results – Electrical.
- .2 Nameplate for each panelboard size 4 engraved as indicated.
- .3 Nameplate for each circuit in distribution panelboards size 2 engraved as indicated.
- .4 Complete circuit directory with typewritten legend showing location and load of each circuit.

PART 3 EXECUTION

3.1 INSTALLATION

- .1 Locate panelboards as indicated and mount securely, plumb, true and square, to adjoining surfaces.
- .2 Install surface mounted panelboards on plywood backboards in accordance with Section 06 10 00 - Rough Carpentry. Where practical, group panelboards on common backboard.
- .3 Mount panelboards to height specified in Section 26 05 00 - Common Work Results - Electrical or as indicated.
- .4 Connect loads to circuits.
- .5 Connect neutral conductors to common neutral bus with respective neutral identified.

END OF SECTION