

Part 1 General

1.1 RELATED SECTIONS

- .1 Section 26 05 01 - Common Work Results - Electrical.

1.2 REFERENCES

- .1 Canadian Standards Association (CSA International)
 - .1 CAN/CSA-C22.2 No.18-98(R2003), Outlet Boxes, Conduit Boxes and Fittings.
 - .2 CAN/CSA-C22.2 No.65-03(R2008), Wire Connectors (Tri-National Standard with UL 486A-486B and NMJ-J-543-ANCE-03).
- .2 Electrical and Electronic Manufacturers' Association of Canada (EEMAC)
 - .1 EEMAC 1Y-2, 1961 Bushing Stud Connectors and Aluminum Adapters (1200 Ampere Maximum Rating).
- .3 National Electrical Manufacturers Association (NEMA).

1.3 WASTE MANAGEMENT AND DISPOSAL

- .1 Remove from site and dispose of all packaging materials at appropriate recycling facilities.
- .2 Collect and separate for disposal packaging material for recycling in accordance with Waste Management Plan.
- .3 Divert unused wiring materials from landfill to metal recycling facility as approved by Departmental Representative.

Part 2 Products

2.1 MATERIALS

- .1 For branch circuit wiring #10 AWG and smaller, use spring type pressure wire connectors with current carrying parts of copper, or copper alloy, and insulating cap, all to fit copper conductors as required. Standard of acceptable quality: Ideal "wing nuts".
- .2 Joints for all other wiring shall be made using T & B colour keyed compression type connectors, 54000 series, and T & B series compression tools. Insulation shall consist of a first layer of compound type tape followed by a layer of Scotch #33 vinyl tape

Part 3 Execution

3.1 INSTALLATION

- .1 Remove insulation carefully from ends of conductors and:
 - .1 Install spring type wire connectors for branch circuit and control wiring #10 AWG and smaller. Plier tighten all wire nut joints and connections.
 - .2 Install pressure type wire connectors for branch circuit wiring larger than #10 AWG. Insulating tapes to overlap successive wraps by a minimum of 50%.
 - .3 The splicing of feeders conductors is not acceptable.
- .2 All connections shall be made electrically and mechanically secure. The sizes of connectors shall be according to manufacturer's recommendations for each wire size and combination of wires.

END OF SECTION