

**PART 1**      **GENERAL**

**1.1**            **SECTION INCLUDES**

- .1      Materials and installation for wire and box connectors.

**1.2**            **RELATED SECTIONS**

- .1      Section 26 05 00 – Common Work Requirements - Electrical.

**1.3**            **REFERENCES**

- .1      Canadian Standards Association (CSA)
  - .1      CAN/CSA-C22.2 No.18, Outlet Boxes, Conduit Boxes, Fittings and Associated Hardware.
  - .2      CSA C22.2 No.65, Wire Connectors.
- .2      Electrical and Electronic Manufacturers' Association of Canada (EEMAC)
  - .1      EEMAC 1Y-2, Bushing Stud Connectors and Aluminum Adapters (1200 Ampere Maximum Rating).
- .3      National Electrical Manufacturers Association (NEMA)

**PART 2**      **PRODUCTS**

**2.1**            **MATERIALS**

- .1      Pressure type wire connectors to: CSA C22.2 No.65, with current carrying parts of copper sized to fit copper conductors as required.
- .2      Fixture type splicing connectors to: CSA C22.2 No.65, with current carrying parts of copper sized to fit copper conductors 10 AWG or less.
- .3      Bushing stud connectors: to EEMAC 1Y-2 to consist of:
  - .1      Connector body and stud clamp for stranded copper conductors.
  - .2      Clamp for copper bar.
  - .3      Stud clamp bolts.
  - .4      Bolts for copper bar.
  - .5      Sized for conductors and bars as indicated.
- .4      Clamps or connectors for armoured cable, aluminum sheathed cable, mineral insulated cable, flexible conduit, non-metallic sheathed cable as required to: CAN/CSA-C22.2 No.18.

- .5 Terminal blocks to be used inside pedestal junction boxes. Terminal blocks to be sized to accommodate wire as shown on drawings. Mount terminal blocks on DIN rail, and use appropriate end stops to hold terminal blocks in place.

**PART 3      EXECUTION**

**3.1            INSTALLATION**

- .1 Remove insulation carefully from ends of conductors and:
  - .1 Install mechanical pressure type connectors and tighten screws with appropriate compression tool recommended by manufacturer. Installation shall meet secureness tests in accordance with CSA C22.2 No.65.
  - .2 Install fixture type connectors and tighten. Replace insulating cap.
  - .3 Install bushing stud connectors in accordance with EEMAC 1Y-2.

**END OF SECTION**