

PART 1 GENERAL

1.1 SECTION INCLUDES

- .1 Materials and installation for standard and custom breaker type panelboards.

1.2 RELATED SECTIONS

- .1 Section 01 33 00 - Submittal Procedures.
- .2 Section 13 00 01 - Building Construction.
- .3 Section 26 05 00 – Common Work Results - Electrical.
- .4 Section 26 28 16.02 - Moulded Case Circuit Breakers.

1.3 REFERENCES

- .1 Canadian Standards Association (CSA)
 - .1 CSA C22.2 No.29, Panelboards and enclosed Panelboards.

1.4 SUBMITTALS

- .1 Drawings to include electrical detail of panel, branch breaker type, quantity, ampacity and enclosure dimension.

PART 2 PRODUCTS

2.1 PANELBOARDS

- .1 Panelboards: to CSA C22.2 No.29 and product of one manufacturer.
 - .1 Install circuit breakers in panelboards before shipment.
 - .2 In addition to CSA requirements manufacturer's nameplate must show fault current that panel including breakers has been built to withstand.
- .2 250 and 600 V panelboards: bus and breakers rated for 10,000 and 18,000 A (symmetrical) minimum interrupting capacity respectively or as indicated on electrical drawings.
- .3 Sequence phase bussing with odd numbered breakers on left and even on right, with each breaker identified by permanent number identification as to circuit number and phase.
- .4 Panelboards: mains, number of circuits, and number and size of branch circuit breakers as indicated.

- .5 Two keys for each panelboard and key panelboards alike.
- .6 Tin plated aluminum bus with neutral of same ampere rating as mains.
- .7 Mains: suitable for bolt-on breakers.
- .8 Trim with concealed front bolts and hinges.
- .9 Trim and door finish: baked grey enamel.

2.2 CUSTOM BUILT PANELBOARD ASSEMBLIES

- .1 125 mm relay section on one or both sides of panels as indicated for installation of low voltage remote control switching components.
- .2 Double stack panels as indicated.
- .3 Contactors in mains as indicated.
- .4 Feed through lugs as indicated.

2.3 BREAKERS

- .1 Breakers: to Section 26 28 16.02 - Moulded Case Circuit Breakers.
- .2 Breakers with thermal and magnetic tripping in panelboards except as indicated otherwise.
- .3 Main breaker: separately mounted on top or bottom of panel to suit cable entry. When mounted vertically, down position should open breaker.
- .4 Lock-on devices for 10% of 15 to 30 A breakers installed as indicated. Turn over unused lock-on devices to Departmental Representative.
- .5 Lock-on devices for receptacles, fire alarm clock outlet, emergency, door supervisory, intercom, stairway, exit and night light circuits as indicated.

2.4 EQUIPMENT IDENTIFICATION

- .1 Provide equipment identification in accordance with Section 26 05 00 – Common Work Results - Electrical.
- .2 Nameplate for each panelboard size 4 engraved as indicated.
- .3 Nameplate for each circuit in distribution panelboards size 2 engraved as indicated.
- .4 Complete circuit directory with typewritten legend showing location and load of each circuit.

PART 3 EXECUTION

3.1 INSTALLATION

- .1 Locate panelboards as indicated and mount securely, plumb, true and square, to adjoining surfaces.
- .2 Install surface mounted panelboards on plywood backboards in accordance with Section 13 00 01- Building Construction. Where practical, group panelboards on common backboard.
- .3 Mount panelboards to height specified in Section 26 05 00 – Common Work Results - Electrical or as indicated.
- .4 Connect loads to circuits.
- .5 Connect neutral conductors to common neutral bus with respective neutral identified.

END OF SECTION