

PART 1 - GENERAL

1.1 References

- .1 CSA C22.2No.65 Wire Connectors.
- .2 EEMAC 1Y-2, 1961 Bushing Stud Connectors and Aluminum Adapters (1200 Ampere Maximum Rating).
- .3 CAN/CSA-C22.2 No.18, Outlet Boxes, Conduit Boxes, Fittings and Associated Hardware.

PART 2 - PRODUCTS

2.1 Materials

- .1 Pressure type wire connectors: with current carrying parts of copper sized to fit copper conductors as required.
- .2 Fixture type splicing connectors: with current carrying parts of copper sized to fit copper conductors 10 AWG or less.
- .3 Bushing stud connectors: to EEMAC 1Y-2 to consist of:
 - .1 Connector body and stud clamp for stranded copper conductors.
 - .2 Clamp for copper bar.
 - .3 Stud clamp bolts.
 - .4 Bolts for copper bar.
 - .5 Sized for conductors and bars as indicated.
- .4 Clamps or connectors for armoured cable, aluminum sheathed cable, mineral insulated cable, flexible conduit, non-metallic sheathed cable as required.

PART 3 - EXECUTION

3.1 Installation

- .1 Remove insulation carefully from ends of conductors and:
 - .1 Install mechanical pressure type connectors and tighten screws with appropriate compression tool recommended by manufacturer. Installation shall meet secureness tests in accordance with CSA C22.2 No.65.
 - .2 Install fixture type connectors and tighten. Replace insulating cap.
 - .3 Install bushing stud connectors in accordance with EEMAC 1Y-2.