
Part 1 General

1.1 RELATED SECTIONS

- .1 Section 26 05 00 - Common Work Results for Electrical.

1.2 REFERENCES

- .1 CSA International.
 - .1 CAN/CSA-C22.2 No.18-98(R2003), Outlet Boxes, Conduit Boxes and Fittings.
 - .2 CAN/CSA-C22.2 No.65-03(R2008), Wire Connectors (Tri-National Standard with UL 486A-486B and NMX-J-543-ANCE-03).
- .2 Electrical and Electronic Manufacturers' Association of Canada (EEMAC).
 - .1 EEMAC 1Y-2-1961, Bushing Stud Connectors and Aluminum Adapters (1200 Ampere Maximum Rating).
- .3 National Electrical Manufacturers Association (NEMA).

1.3 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
 - .1 Submit manufacturer's instructions, printed product literature and data sheets for wire and box connectors and include product characteristics, performance criteria, physical size, finish, and limitations.

1.4 CLOSEOUT SUBMITTALS

- .1 Submit in accordance with Section 01 78 00 - Closeout Submittals.
- .2 Operation and Maintenance Data: submit operation and maintenance data for wire and box connectors for incorporation into manual.

1.5 DELIVERY, STORAGE, AND HANDLING

- .1 Deliver, store, and handle materials in accordance with manufacturer's written instructions.
- .2 Delivery and Acceptance Requirements: Deliver materials to site in original factory packaging, labelled with manufacturer's name and address.
- .3 Storage and Handling Requirements:
 - .1 Store materials off ground, indoors, and in accordance with manufacturer's recommendations in clean, dry, and well-ventilated area.
 - .2 Store and protect wire and box connectors from nicks, scratches, and blemishes.
 - .3 Replace defective or damaged materials with new.

Part 2 Products

2.1 MATERIALS

- .1 Pressure type wire connectors to: CAN/CSA-C22.2 No. 65, with current carrying parts of copper sized to fit copper conductors as required.
- .2 Fixture type splicing connectors to: CAN/CSA-C22.2 No. 65, with current carrying parts of copper sized to fit copper conductors 10 AWG or less.
- .3 Bushing stud connectors: to NEMA to consist of:
 - .1 Connector body and stud clamp for round copper conductors.
 - .2 Clamp for stranded copper conductors.
 - .3 Stud clamp bolts.
 - .4 Bolts for copper conductors.
 - .5 Sized for conductors as indicated.
- .4 Clamps or connectors for armoured cable, TECK cable, mineral insulated cable, flexible conduit, as required to: CAN/CSA-C22.2 No. 18.

Part 3 Execution

3.1 EXAMINATION

- .1 Verification of Conditions: Verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for wire and box connectors installation in accordance with manufacturer's written instructions.
 - .1 Visually inspect substrate.
 - .2 Inform Departmental Representative of unacceptable conditions immediately upon discovery.
 - .3 Proceed with installation only after unacceptable conditions have been remedied.

3.2 INSTALLATION

- .1 Remove insulation carefully from ends of conductors and cables, and:
 - .1 Install mechanical pressure type connectors and tighten screws with appropriate compression tool recommended by manufacturer. Installation shall meet secureness tests in accordance with CAN/CSA-C22.2 No. 65.
 - .2 Install fixture type connectors and tighten to CAN/CSA-C22.2 No. 65. Replace insulating cap.
 - .3 Install bushing stud connectors in accordance with NEMA.

3.3 CLEANING

- .1 Progress Cleaning: Clean in accordance with Section 01 74 11 - Cleaning.
 - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 11 - Cleaning.

END OF SECTION