

PART 1 - GENERAL

1.1 RELATED SECTIONS

- .1 Section 26 05 00 - Common Work Results - Electrical.

1.2 REFERENCES

- .1 CSA C22.2 No.18, Outlet Boxes, Conduit Boxes, Fittings, and Associated Hardware.

PART 2 - PRODUCTS

2.1 OUTLET AND CONDUIT BOXES GENERAL

- .1 Size boxes in accordance with CSA C22.1.
- .2 102 mm square or larger outlet boxes as required.
- .3 Gang boxes where wiring devices are grouped.
- .4 Blank cover plates for boxes without wiring devices.
- .5 347 V outlet boxes for 347 V switching devices.
- .6 Combination boxes with barriers where outlets for more than one system are grouped.

2.2 OUTLET BOXES STEEL PLATE

- .1 Boxes, electro-galvanized steel, for single and multi-gang flush device boxes for flush installation, minimum size 102 mm x 102 mm x 65 mm or as indicated. 102 mm square outlet boxes when more than one conduit enters one side with extension and plaster rings as required.
 - .2 Utility boxes for outlets connected to surface-mounted EMT conduit, minimum size 102 x 54 x 48 mm.
 - .3 102 mm square or octagonal outlet boxes for lighting fixture outlets.
 - .4 Square outlet boxes of 102 mm side with extension and plaster rings for flush mounting devices in finished plaster or ceramic tile.
-

2.3 MASONRY BOXES

- .1 Electro-galvanized steel masonry single and multi-gang boxes for devices flush mounted in exposed block walls.

2.4 CONDUIT BOXES

- .1 Cast FS or FD aluminum boxes with factory-threaded hubs and mounting feet for surface mounting of switches and receptacles, when installed in locations that are not protected from weather.

2.5 FITTINGS - GENERAL

- .1 Sleeves and collar connectors with nylon insulation.
- .2 Knock-out fillers to prevent entry of debris.
- .3 Conduit outlet bodies for conduit up to 32 mm and pull boxes for larger conduits.
- .4 Double locknuts and insulated bushings on sheet metal boxes.

PART 3 - EXECUTION

3.1 INSTALLATION

- .1 Support boxes independently of connecting conduits.
- .2 Fill boxes with paper, sponges or foam or similar approved material to prevent entry of debris during construction. Remove upon completion of Work.
- .3 For flush installations mount outlets flush with finished wall using plaster rings to permit wall finish to come within 6 mm of opening.
- .4 Provide correct size of openings in boxes for conduit, mineral insulated and armored cable connections. Do not install reducing washers.

END OF SECTION
