

PART 1 **GENERAL**

1.1 **RELATED SECTIONS**

- .1 Section 26 05 00 – Common Work Results – Electrical.
- .2 Section 26 05 29 – Hangers and Supports for Electrical Systems.
- .3 Section 26 05 34 – Conduits, Conduit Fastenings and Fittings.

1.2 **REFERENCES**

- .1 Canadian Standards Association (CSA)
 - .1 CSA C22.1, Canadian Electrical Code, Part 1.

PART 2 **PRODUCTS**

2.1 **OUTLET AND CONDUIT BOXES GENERAL**

- .1 Size boxes in accordance with CSA C22.1.
- .2 102 mm square or larger outlet boxes as required for special devices.
- .3 Gang boxes where wiring devices are grouped.
- .4 Blank cover plates for boxes without wiring devices.
- .5 347 V outlet boxes for 347 V switching devices.
- .6 Combination boxes with barriers where outlets for more than one system are grouped.

2.2 **GALVANIZED STEEL OUTLET BOXES**

- .1 Electro-galvanized steel single and multi gang flush device boxes for flush installation, minimum size 76 x 50 x 38 mm or as indicated. 102 mm square outlet boxes when more than one conduit enters one side with extension and plaster rings as required.
- .2 Electro-galvanized steel utility boxes for outlets connected to surface-mounted EMT conduit, minimum size 102 x 54 x 48 mm.
- .3 102 mm square or octagonal outlet boxes for lighting fixture outlets.
- .4 102 mm square outlet boxes with extension and plaster rings for flush mounting devices in finished plaster walls.

2.3 CONDUIT BOXES

- .1 Cast FS or FD aluminum boxes with factory-threaded hubs and mounting feet for surface wiring of switches and receptacle.

2.4 OUTLET BOXES FOR NON-METALLIC SHEATHED CABLE

- .1 Electro-galvanized, sectional, screw ganging steel boxes, minimum size 76 x 50 x 63 mm with two double clamps to take non-metallic sheathed cables. For use in wood stud construction only.

2.5 FITTINGS - GENERAL

- .1 Bushing and connectors with nylon insulated throats.
- .2 Knock-out fillers to prevent entry of debris.
- .3 Conduit outlet bodies for conduit up to 32 mm and pull boxes for larger conduits.
- .4 Double locknuts and insulated bushings on sheet metal boxes.
- .5 Double split rings for AC-90 terminations.

2.6 SERVICE FITTINGS

- .1 'High tension' receptacle fitting made of 2 piece die-cast aluminum with brushed aluminum housing finish for 1 duplex receptacles. Bottom plate with two knockouts for centered or offset installation.
- .2 Pedestal type 'low tension' fitting made of 2 piece die cast aluminum with brushed aluminum housing finish to accommodate two amphenol jack connectors.

PART 3 EXECUTION

3.1 INSTALLATION

- .1 Support boxes independently of connecting conduits.
- .2 Fill boxes with paper, sponges or foam or similar approved material to prevent entry of debris during construction. Remove upon completion of work.
- .3 For flush installations mount outlets flush with finished wall using plaster rings to permit wall finish to come within 6 mm of opening.
- .4 Provide correct size of openings in boxes for conduit, mineral insulated and armoured cable connections. Reducing washers are not allowed.
- .5 Vacuum clean interior of outlet boxes before installation of wiring devices.

.6 Identify systems for outlet boxes as required.

END OF SECTION