

---

**Washroom Buildings Recapitalization  
Buildings 32, 34 & 38  
Newman Sound Campground  
Terra Nova National Park, NL  
Proj. No.: R.079272.001**

Section 26 05 32 – Outlet Boxes, Conduit Boxes and Fittings

Page 1 of 2

---

**PART 1      GENERAL**

**1.1            RELATED SECTIONS**

- .1      Section 26 05 00 – Common Work Results – Electrical.
- .2      Section 26 05 29 – Hangers and Supports for Electrical Systems.
- .3      Section 26 05 34 – Conduits, Conduit Fastenings and Fittings.

**1.2            REFERENCES**

- .1      Canadian Standards Association (CSA)
  - .1      CSA C22.1, Canadian Electrical Code, Part 1.

**PART 2      PRODUCTS**

**2.1            OUTLET AND CONDUIT BOXES GENERAL**

- .1      Size boxes in accordance with CSA C22.1.
- .2      102 mm square or larger outlet boxes as required for special devices.
- .3      Gang boxes where wiring devices are grouped.
- .4      Blank cover plates for boxes without wiring devices.
- .5      Combination boxes with barriers where outlets for more than one system are grouped.

**2.2            GALVANIZED STEEL OUTLET BOXES**

- .1      Electro-galvanized steel single and multi gang flush device boxes for flush installation, minimum size 76 x 50 x 38 mm or as indicated. 102 mm square outlet boxes when more than one conduit enters one side with extension and plaster rings as required.
- .2      Electro-galvanized steel utility boxes for outlets connected to surface-mounted EMT conduit, minimum size 102 x 54 x 48 mm.
- .3      102 mm square or octagonal outlet boxes for lighting fixture outlets.
- .4      102 mm square outlet boxes with extension and plaster rings for flush mounting devices in finished plaster walls.

---

**Washroom Buildings Recapitalization  
Buildings 32, 34 & 38  
Newman Sound Campground  
Terra Nova National Park, NL  
Proj. No.: R.079272.001**

Section 26 05 32 – Outlet Boxes, Conduit Boxes and Fittings

Page 2 of 2

---

**2.3 CONDUIT BOXES**

- .1 Cast FS or FD aluminum boxes with factory-threaded hubs and mounting feet for surface wiring of switches and receptacle.

**2.4 FITTINGS - GENERAL**

- .1 Bushing and connectors with nylon insulated throats.
- .2 Knock-out fillers to prevent entry of debris.
- .3 Conduit outlet bodies for conduit up to 32 mm and pull boxes for larger conduits.
- .4 Double locknuts and insulated bushings on sheet metal boxes.
- .5 Double split rings for AC-90 terminations.

**PART 3 EXECUTION**

**3.1 INSTALLATION**

- .1 Support boxes independently of connecting conduits.
- .2 Fill boxes with paper, sponges or foam or similar approved material to prevent entry of debris during construction. Remove upon completion of work.
- .3 For flush installations mount outlets flush with finished wall using plaster rings to permit wall finish to come within 6 mm of opening.
- .4 Provide correct size of openings in boxes for conduit, and armoured cable connections. Reducing washers are not allowed.
- .5 Vacuum clean interior of outlet boxes before installation of wiring devices.
- .6 Identify systems for outlet boxes as required.

**END OF SECTION**