
Washroom Buildings Recapitalization
Buildings 32, 34 & 38
Newman Sound Campground
Terra Nova National Park, NL
Proj. No.: R.079272.001
Section 26 27 26 – Wiring Devices

Page 1 of 3

PART 1 **GENERAL**

1.1 **SECTION INCLUDES**

- .1 Switches, receptacles, wiring devices, cover plates and their installation.

1.2 **RELATED SECTIONS**

- .1 Section 01 33 00 - Submittal Procedures.
- .2 Section 26 05 00 – Common Work Results - Electrical.

1.3 **REFERENCES**

- .1 Canadian Standards Association (CSA)
 - .1 CSA-C22.2 No.42, General Use Receptacles, Attachment Plugs and Similar Devices.
 - .2 CSA-C22.2 No.42.1, Cover Plates for Flush-Mounted Wiring Devices (Bi-national standard, with UL 514D).
 - .3 CSA-C22.2 No.55, Special Use Switches.
 - .4 CSA-C22.2 No.111, General-Use Snap Switches (Bi-national standard, with UL 20, twelfth edition).

PART 2 **PRODUCTS**

2.1 **SWITCHES**

- .1 15 A, 120 V, single pole, double pole, three-way, four-way switches as indicated to: CSA-C22.2 No.55 and CSA-C22.2 No.111.
- .2 Manually-operated general purpose ac switches with following features:
 - .1 Terminal holes approved for No. 10 AWG wire.
 - .2 Silver alloy contacts.
 - .3 Urea or melamine moulding for parts subject to carbon tracking.
 - .4 Suitable for back and side wiring.
 - .5 White toggle.
 - .6 Specification grade.
- .3 Toggle operated fully rated for tungsten filament and fluorescent lamps, and up to 80% of rated capacity of motor loads.

Washroom Buildings Recapitalization
Buildings 32, 34 & 38
Newman Sound Campground
Terra Nova National Park, NL
Proj. No.: R.079272.001
Section 26 27 26 – Wiring Devices

Page 2 of 3

.4 Switches of one manufacturer throughout project.

.5 Acceptable products:

- .1 Hubbel HBL 1201 W,
- .2 Leviton 1201-2W,
- .3 Pass and Seymour.

2.2 RECEPTACLES

.1 Duplex receptacles, CSA type 5-15 R, 125 V, 15 A, U ground, to: CSA-C22.2 No.42 with following features:

- .1 White thermoplastic moulded housing.
- .2 Suitable for No. 10 AWG for back and side wiring.
- .3 Break-off links for use as split receptacles.
- .4 Eight back wired entrances, four side wiring screws.
- .5 Triple wipe contacts and rivetted grounding contacts.
- .6 Specification grade.

.2 Single receptacles CSA type 5-15 R, 125 V, 15 A, U ground with following features:

- .1 White thermoplastic moulded housing.
- .2 Suitable for No. 10 AWG for back and side wiring.
- .3 Four back wired entrances, 2 side wiring screws.

.3 Other receptacles with ampacity and voltage as indicated.

.4 Receptacles of one manufacturer throughout project.

.5 Acceptable products:

- .1 Hubbel 5262-W,
- .2 Leviton 5262-W,
- .3 Pass and Seymour 5262-W.

2.3 COVER PLATES

.1 Cover plates for wiring devices to: CSA-C22.2 No.42.1.

.2 Cover plates from one manufacturer throughout project.

.3 Sheet steel utility box cover for wiring devices installed in surface-mounted utility boxes.

.4 Stainless steel cover plates as indicated, thickness 2.5 mm for wiring devices mounted in flush-mounted outlet box.

Washroom Buildings Recapitalization
Buildings 32, 34 & 38
Newman Sound Campground
Terra Nova National Park, NL
Proj. No.: R.079272.001
Section 26 27 26 – Wiring Devices

Page 3 of 3

- .5 Sheet metal cover plates for wiring devices mounted in surface-mounted FS or FD type conduit boxes.
- .6 Weatherproof double lift spring-loaded cast aluminum cover plates, complete with gaskets for duplex receptacles as indicated.
- .7 Weatherproof spring-loaded cast aluminum cover plates complete with gaskets for single receptacles or switches.
- .8 All wiring device cover plates to be labeled using clear adhesive strips with black type identifying panel and circuit number for each device.

PART 3 **EXECUTION**

3.1 **INSTALLATION**

- .1 Switches:
 - .1 Install single throw switches with handle in "UP" position when switch closed.
 - .2 Install switches in gang type outlet box when more than one switch is required in one location.
 - .3 Mount toggle switches at height in accordance with Section 26 05 00 – Common Work Results - Electrical.
- .2 Receptacles:
 - .1 Install receptacles in gang type outlet box when more than one receptacle is required in one location.
 - .2 Mount receptacles at height in accordance with Section 26 05 00 – Common Work Results - Electrical.
 - .3 Where split receptacle has one portion switched, mount vertically and switch upper portion.
- .3 Cover plates:
 - .1 Protect cover plate finish with paper or plastic film until painting and other work is finished.
 - .2 Install suitable common cover plates where wiring devices are grouped.
 - .3 Do not use cover plates meant for flush outlet boxes on surface-mounted boxes.