

Part 1 General

1.1 REFERENCES

- .1 Definitions:
 - .1 Electrical and electronic terms: unless otherwise specified or indicated, terms used in these specifications, and on drawings, are those defined by IEEE SP1122.
- .2 Reference Standards:
 - .1 CSA Group
 - .1 CSA C22.1-12, Canadian Electrical Code, Part 1 (22nd Edition), Safety Standard for Electrical Installations.
 - .2 Institute of Electrical and Electronics (IEEE)/National Electrical Safety Code Product Line (NESC)
 - .1 IEEE SP1122-2000, The Authoritative Dictionary of IEEE Standards Terms, 7th Edition.

1.2 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
 - .1 Submit manufacturer's instructions, printed product literature and data sheets and include product characteristics, performance criteria, physical size, finish and limitations.
- .3 Submit for review fire alarm riser diagram, plan and zoning of building at fire alarm control panel and annunciator.
- .4 Shop drawings:
 - .1 Submit wiring diagrams and installation details of equipment indicating proposed location, layout and arrangement, control panels, accessories, piping, ductwork, and other items that must be shown to ensure co-ordinated installation.
 - .2 Identify on wiring diagrams circuit terminals and indicate internal wiring for each item of equipment and interconnection between each item of equipment.
 - .3 Indicate of drawings clearances for operation, maintenance, and replacement of operating equipment devices.
 - .4 If changes are required, notify Departmental Representative of these changes before they are made.
- .5 Certificates:
 - .1 Provide CSA certified equipment and material.
 - .2 Permits and fees: in accordance with General Conditions of contract.
 - .3 Submit certificate of acceptance from authority having jurisdiction upon completion of Work to Departmental Representative.

- .6 Hazardous Materials:
 - .1 Coordinate with Hazardous Materials contractor for removal of Ballasts which may contain PLB's.

Part 2 Products

2.1 DESIGN REQUIREMENTS

- .1 Operating voltages: to CAN3-C235.
- .2 Motors, electric heating, control and distribution devices and equipment to operate satisfactorily at 60 Hz within normal operating limits established by above standard.
 - .1 Equipment to operate in extreme operating conditions established in above standard without damage to equipment.
- .3 Language operating requirements: provide identification nameplates for control items in English.
- .4 Use one[nameplate for each language.

2.2 MATERIALS AND EQUIPMENT

- .1 Provide material and equipment] in accordance with Section 01 61 00 - Common Product Requirements.

2.3 ELECTRIC MOTORS, EQUIPMENT AND CONTROLS

- .1 Verify installation and co-ordination responsibilities related to motors, equipment and controls, as indicated.

2.4 WIRING TERMINATIONS

- .1 Ensure lugs, terminals, screws used for termination of wiring are suitable for either copper or aluminum conductors.

2.5 EQUIPMENT IDENTIFICATION

- .1 Identify electrical equipment with nameplates labels as follows:
 - .1 Nameplates: lamicoid 3 mm thick plastic engraving sheet, black face, white core, lettering accurately aligned and engraved into core mechanically attached with self tapping screws.
 - .2 Sizes as follows:

NAMEPLATE SIZES			
Size 1	10 x 50 mm	1 line	3 mm high letters
Size 2	12 x 70 mm	1 line	5 mm high letters
Size 3	12 x 70 mm	2 lines	3 mm high letters
Size 4	20 x 90 mm	1 line	8 mm high letters
Size 5	20 x 90 mm	2 lines	5 mm high letters
Size 6	25 x 100 mm	1 line	12 mm high letters
Size 7	25 x 100 mm	2 lines	6 mm high letters

- .2 Wording on nameplates to be approved by Departmental Representative prior to manufacture.
- .3 Allow for minimum of twenty-five (25) letters per nameplate.
- .4 Nameplates for terminal cabinets and junction boxes to indicate system and/or voltage characteristics.
- .5 Disconnects, starters and contactors: indicate equipment being controlled and voltage.
- .6 Terminal cabinets and pull boxes: indicate system and voltage.
- .7 Transformers: indicate capacity, primary and secondary voltages.

2.6 WIRING IDENTIFICATION

- .1 Identify wiring with permanent indelible identifying markings, [numbered] [coloured plastic tapes], on both ends of phase conductors of feeders and branch circuit wiring.
- .2 Maintain phase sequence and colour coding throughout.
- .3 Colour coding: to CSA C22.1.
- .4 Use colour coded wires in communication cables, matched throughout system.

2.7 CONDUIT AND CABLE IDENTIFICATION

- .1 Colour code conduits, boxes and metallic sheathed cables.
- .2 Code with plastic tape or paint at points where conduit or cable enters wall, ceiling, or floor, and at 15 m intervals.
- .3 Colours: 25 mm wide prime colour and 20 mm wide auxiliary colour.

Prime	Auxiliary	
up to 250 V	Yellow	
up to 600 V	Yellow	Green
up to 5 kV	Yellow	Blue
up to 15 kV	Yellow	Red
Telephone	Green	
Other Communication Systems	Green	Blue
Fire Alarm	Red	
Emergency Voice	Red	Blue
Other Security Systems	Red	Yellow

Part 3 Execution

3.1 INSTALLATION

- .1 Do complete installation in accordance with CSA C22.1 except where specified otherwise.
- .2 Do overhead and underground systems in accordance with CAN/CSA-C22.3 No.1 except where specified otherwise.

3.2 NAMEPLATES AND LABELS

- .1 Ensure manufacturer's nameplates, CSA labels and identification nameplates are visible and legible after equipment is installed.

3.3 CONDUIT AND CABLE INSTALLATION

- .1 Install cables, conduits and fittings embedded or plastered over, close to building structure so furring can be kept to minimum.

3.4 LOCATION OF OUTLETS

- .1 Locate outlets in accordance with Section 26 05 34 – Conduits, conduit fastenings and conduit fittings.
- .2 Do not install outlets back-to-back in wall; allow minimum 150 mm horizontal clearance between boxes.
- .3 Change location of outlets at no extra cost or credit, providing distance does not exceed 3000 mm, and information is given before installation.
- .4 Locate light switches on latch side of doors.
 - .1 Locate disconnect devices in mechanical and elevator machine rooms on latch side of floor.

3.5 MOUNTING HEIGHTS

- .1 Mounting height of equipment is from finished floor to centreline of equipment unless specified or indicated otherwise.
- .2 If mounting height of equipment is not specified or indicated, verify before proceeding with installation.
- .3 Install electrical equipment at following heights unless indicated otherwise.
 - .1 Local switches: 1400 mm.
 - .2 Wall receptacles:
 - .1 General: 300 mm.
 - .2 Above top of continuous baseboard heater: 200 mm.
 - .3 Above top of counters or counter splash backs: 175 mm.
 - .4 In mechanical rooms: 1400 mm.
 - .3 Panelboards: as required by Code or as indicated.
 - .4 Telephone and interphone outlets: 300 mm.
 - .5 Wall mounted telephone and interphone outlets: 1500 mm.
 - .6 Fire alarm stations: 1500 mm.
 - .7 Fire alarm bells: 2100 mm.
 - .8 Television outlets: 300 mm.
 - .9 Wall mounted speakers: 2100 mm.
 - .10 Clocks: 2100 mm.
 - .11 Door bell pushbuttons: 1500 mm.

3.6 CO-ORDINATION OF PROTECTIVE DEVICES

- .1 Ensure circuit protective devices such as overcurrent trips, relays and fuses are installed to required values and settings.

3.7 FIELD QUALITY CONTROL

- .1 Load Balance:
 - .1 Measure phase current to panelboards with normal loads (lighting) operating at time of acceptance; adjust branch circuit connections as required to obtain best balance of current between phases and record changes.
 - .2 Measure phase voltages at loads and adjust transformer taps to within 2% of rated voltage of equipment.
 - .3 Provide upon completion of work, load balance report as directed in PART 1 - ACTION AND INFORMATIONAL SUBMITTALS, phase and neutral currents on panelboards, dry-core transformers and motor control centres, operating under normal load, as well as hour and date on which each load was measured, and voltage at time of test.
- .2 Conduct following tests in accordance with Section 01 45 00 - Quality Control.
 - .1 Power distribution system including phasing, voltage, grounding and load balancing.
 - .2 Circuits originating from branch distribution panels.
 - .3 Lighting and its control.
 - .4 Motors, heaters and associated control equipment including sequenced operation of systems where applicable.
 - .5 Systems: fire alarm.
 - .6 Insulation resistance testing:
 - .1 Megger circuits, feeders and equipment up to 350 V with a 500 V instrument.
 - .2 Megger 350-600 V circuits, feeders and equipment with a 1000 V instrument.
 - .3 Check resistance to ground before energizing.
- .3 Carry out tests in presence of Departmental Representative.
- .4 Provide instruments, meters, equipment and personnel required to conduct tests during and at conclusion of project.
- .5 Manufacturer's Field Services:
 - .1 Obtain written report from manufacturer verifying compliance of Work, in handling, installing, applying, protecting and cleaning of product and submit Manufacturer's Field Reports as described in PART 1 - ACTION AND INFORMATIONAL SUBMITTALS.
 - .2 Provide manufacturer's field services consisting of product use recommendations and periodic site visits for inspection of product installation in accordance with manufacturer's instructions.

3.8 SYSTEM STARTUP

- .1 Instruct Departmental Representative operating personnel in operation, care and maintenance of systems, system equipment and components.
- .2 Arrange and pay for services of manufacturer's factory service engineer to supervise start-up of installation, check, adjust, balance and calibrate components and instruct operating personnel.
- .3 Provide these services for such period, and for as many visits as necessary to put equipment in operation, and ensure that operating personnel are conversant with aspects of its care and operation.

3.9 CLEANING

- .1 Progress Cleaning: clean in accordance with Section 01 74 11 - Cleaning.
 - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 11 - Cleaning.

END OF SECTION

Part 1 General

1.1 PRODUCT DATA

- .1 Provide product data in accordance with Section 01 33 00 - Submittal Procedures.

Part 2 Products

2.1 BUILDING WIRES

- .1 Conductors: stranded for 10 AWG and larger. Minimum size: 12 AWG.
- .2 Copper conductors: size as indicated, with 600 V insulation of cross-linked thermosetting polyethylene material rated RW90 XLPE Non Jacketted.
- .3 Copper conductors: size as indicated, with thermoplastic insulation type T90 Nylon rated at 600 V.

2.2 TECK 90 CABLE

- .1 Cable: in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Conductors:
 - .1 Grounding conductor: copper as indicated.
 - .2 Circuit conductors: copper as indicated, size as indicated.
- .3 Insulation:
 - .1 Ethylene propylene rubber EP.
 - .2 Cross-linked polyethylene XLPE.
 - .3 Rating: 600 V.
- .4 Inner jacket: polyvinyl chloride material.
- .5 Armour: interlocking aluminum.
- .6 Overall covering: thermoplastic polyvinyl chloride, compliant to applicable Building Code classification for this project.
- .7 Fastenings:
 - .1 One hole steel straps to secure surface cables 50 mm and smaller. Two hole steel straps for cables larger than 50 mm.
 - .2 Channel type supports for two or more cables at 1500 mm centers.
 - .3 Threaded rods: 6 mm diameter to support suspended channels.
- .8 Connectors:
 - .1 Watertight or explosion-proof based on hazardous area ratings approved for TECK cable.

2.3 ARMOURED CABLES

- .1 Conductors: insulated, copper, size as indicated.

- .2 Type: AC90.
- .3 Armour: interlocking type fabricated from aluminum strip.
- .4 Connectors: anti short connectors.

2.4 CONTROL CABLES

- .1 Type: LVT: 2 soft annealed copper conductors, sized as indicated:
 - .1 Insulation: thermoplastic.
 - .2 Sheath: thermoplastic jacket.
- .2 Type: low energy 300 V control cable: stranded annealed copper conductors sized as indicated LVT: 2 soft annealed copper conductors, sized as indicated:
 - .1 Insulation: PVC.
 - .2 Overall covering: PVC.

Part 3 Execution

3.1 FIELD QUALITY CONTROL

- .1 Perform tests in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Perform tests before energizing electrical system.

3.2 GENERAL CABLE INSTALLATION

- .1 Cable Colour Coding: to Section 26 05 00 - Common Work Results for Electrical.
- .2 Lace or clip groups of feeder cables at distribution centres, pull boxes, and termination points.
- .3 Provide numbered wire collars for control wiring. Numbers to correspond to control shop drawing legend. Obtain wiring diagram for control wiring.

3.3 INSTALLATION OF BUILDING WIRES

- .1 Install wiring as follows:
 - .1 In conduit systems in accordance with Section 26 05 34 - Conduits, Conduit Fastenings and Conduit Fittings.

3.4 INSTALLATION OF TECK90 CABLE (0 -1000 V)

- .1 Group cables wherever possible on channels.
- .2 Install cable exposed, securely supported by hangers.

3.5 INSTALLATION OF ARMOURED CABLES

- .1 Group cables wherever possible on channels.

3.6 INSTALLATION OF CONTROL CABLES

- .1 Install control cables in conduit.
- .2 Ground control cable shield.

END OF SECTION

Approved: 2011-12-31

Part 1 General

Not Used

Part 2 Products

2.1 EQUIPMENT

- .1 Clamps for grounding of conductor: size as required to electrically conductive underground water pipe.
- .2 Rod electrodes: copper clad steel 19 mm diameter by minimum 3 m long.
- .3 Grounding conductors: bare stranded copper, soft annealed, size No. 2.
- .4 Insulated grounding conductors: green, copper conductors, size as indicated.
- .5 Non-corroding accessories necessary for grounding system, type, size, material as indicated, including but not necessarily limited to:
 - .1 Grounding and bonding bushings.
 - .2 Protective type clamps.
 - .3 Bolted type conductor connectors.
 - .4 Thermit welded type conductor connectors.
 - .5 Bonding jumpers, straps.
 - .6 Pressure wire connectors.

Part 3 Execution

3.1 INSTALLATION GENERAL

- .1 Install complete permanent, continuous grounding system including, electrodes, conductors, connectors, accessories.
- .2 Install connectors in accordance with manufacturer's instructions.
- .3 Protect exposed grounding conductors from mechanical injury.
- .4 Make buried connections, and connections to conductive water main, electrodes, using permanent mechanical connectors or inspectable wrought copper compression connectors to ANSI/IEEE 837.
- .5 Use mechanical connectors for grounding connections to equipment provided with lugs.
- .6 Soldered joints not permitted.
- .7 Install bonding wire for flexible conduit, connected at both ends to grounding bushing, solderless lug, clamp or cup washer and screw. Neatly cleat bonding wire to exterior of flexible conduit.

- .8 Install flexible ground straps for bus duct enclosure joints, where such bonding is not inherently provided with equipment.
- .9 Connect building structural steel and metal siding to ground by welding copper to steel.
- .10 Make grounding connections in radial configuration only, with connections terminating at ground grid and street side of water pipe. Avoid loop connections.

3.2 EQUIPMENT GROUNDING

- .1 Install grounding connections to typical equipment included in, but not necessarily limited to following list. Service equipment, transformers, switchgear, duct systems, frames of motors, motor control centres, starters, control panels, building steel work, generators, elevators and escalators, distribution panels, outdoor lighting, cable trays.

3.3 FIELD QUALITY CONTROL

- .1 Perform tests in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Perform ground continuity and resistance tests using method appropriate to site conditions and to approval of Departmental Representative and local authority having jurisdiction over installation.
- .3 Perform tests before energizing electrical system.
- .4 Disconnect ground fault indicator during tests.

END OF SECTION

Part 1 General

Not Used

Part 2 Products

2.1 SUPPORT CHANNELS

- .1 U shape, size 41 x 41 mm, 2.5 mm thick, surface mounted.

Part 3 Execution

3.1 INSTALLATION

- .1 Secure equipment to solid masonry, tile and plaster surfaces with lead anchors.
- .2 Secure equipment to poured concrete with expandable inserts.
- .3 Secure equipment to hollow masonry walls or suspended ceilings with toggle bolts.
- .4 Secure surface mounted equipment with twist clip fasteners to inverted T bar ceilings. Ensure that T bars are adequately supported to carry weight of equipment specified before installation.
- .5 Support equipment, conduit or cables using clips, spring loaded bolts, cable clamps designed as accessories to basic channel members.
- .6 Fasten exposed conduit or cables to building construction or support system using straps.
 - .1 One-hole steel straps to secure surface conduits and cables 50 mm and smaller.
 - .2 Two-hole steel straps for conduits and cables larger than 50 mm.
 - .3 Beam clamps to secure conduit to exposed steel work.
- .7 Suspended support systems.
 - .1 Support individual cable or conduit runs with 6 mm diameter threaded rods and spring clips.
 - .2 Support 2 or more cables or conduits on channels supported by 6 mm diameter threaded rod hangers where direct fastening to building construction is impractical.
- .8 For surface mounting of two or more conduits use channels at 1.5 m on centre spacing.
- .9 Provide metal brackets, frames, hangers, clamps and related types of support structures where indicated or as required to support conduit and cable runs.
- .10 Ensure adequate support for raceways and cables dropped vertically to equipment where there is no wall support.
- .11 Do not use wire lashing or perforated strap to support or secure raceways or cables.

- .12 Do not use supports or equipment installed for other trades for conduit or cable support except with permission of other trade and approval of Departmental Representative
- .13 Install fastenings and supports as required for each type of equipment cables and conduits, and in accordance with manufacturer's installation recommendations.

END OF SECTION

Part 1 General

1.1 REFERENCES

- .1 Canadian Standards Association (CSA International)
 - .1 CAN/CSA C22.2 No. 18-98 (R2003), Outlet Boxes, Conduit Boxes, Fittings and Associated Hardware, A National Standard of Canada.
 - .2 CSA C22.2 No. 45-M1981(R2003), Rigid Metal Conduit.
 - .3 CSA C22.2 No. 56-04, Flexible Metal Conduit and Liquid-Tight Flexible Metal Conduit.
 - .4 CSA C22.2 No. 83-M1985(R2003), Electrical Metallic Tubing.
 - .5 CSA C22.2 No. 211.2-M1984(R2003), Rigid PVC (Unplasticized) Conduit.
 - .6 CAN/CSA C22.2 No. 227.3-05, Nonmetallic Mechanical Protection Tubing (NMPT), A National Standard of Canada (February 2006).

Part 2 Products

2.1 CABLES AND REELS

- .1 Provide cables on reels or coils.
 - .1 Mark or tag each cable and outside of each reel or coil, to indicate cable length, voltage rating, conductor size, and manufacturer's lot number and reel number.
- .2 Each coil or reel of cable to contain only one continuous cable without splices.
- .3 Identify cables for exclusively dc applications.
- .4 Reel and mark shielded cables rated 2,001 volts and above.

2.2 CONDUITS

- .1 Rigid metal conduit: to CSA C22.2 No. 45, hot dipped galvanized steel threaded.
- .2 Epoxy coated conduit: to CSA C22.2 No. 45, with zinc coating and corrosion resistant epoxy finish inside and outside.
- .3 Electrical metallic tubing (EMT): to CSA C22.2 No. 83, with couplings.
- .4 Rigid pvc conduit: to CSA C22.2 No. 211.2.
- .5 Flexible metal conduit: to CSA C22.2 No. 56, liquid-tight flexible metal.
- .6 Flexible pvc conduit: to CAN/CSA-C22.2 No. 227.3.

2.3 CONDUIT FASTENINGS

- .1 One hole steel straps to secure surface conduits 50 mm and smaller.
 - .1 Two hole steel straps for conduits larger than 50 mm.
- .2 Beam clamps to secure conduits to exposed steel work.

- .3 Channel type supports for two or more conduits at 1.5 m on centre.
- .4 Threaded rods, 6 mm diameter, to support suspended channels.

2.4 CONDUIT FITTINGS

- .1 Fittings: to CAN/CSA C22.2 No. 18, manufactured for use with conduit specified.
Coating: same as conduit.
- .2 Ensure factory "ells" where 90 degrees bends for 25 mm and larger conduits.
- .3 Watertight connectors and couplings for EMT.
 - .1 Set-screws are not acceptable.

2.5 OUTLET AND CONDUIT BOXES GENERAL

- .1 Size boxes in accordance with CSA C22.1.
- .2 [102] mm square or larger outlet boxes as required.
- .3 Gang boxes where wiring devices are grouped.
- .4 Blank cover plates for boxes without wiring devices.
- .5 347 V outlet boxes for 347 V switching devices.
- .6 Combination boxes with barriers where outlets for more than one system are grouped.

Part 3 Execution

3.1 MANUFACTURER'S INSTRUCTIONS

- .1 Compliance: comply with manufacturer's written recommendations or specifications, including product technical bulletins, handling, storage and installation instructions, and datasheets.

3.2 INSTALLATION

- .1 Install conduits to conserve headroom in exposed locations and cause minimum interference in spaces through which they pass.
- .2 Surface mount conduits.
- .3 Use rigid hot dipped galvanized steel threaded conduit except where specified otherwise.
- .4 Use rigid pvc conduit in corrosive areas.
- .5 Use liquid tight flexible metal conduit for connection to motors or vibrating equipment in damp, wet or corrosive locations.
- .6 Use explosion proof flexible connection for connection to explosion proof motors.
- .7 Install conduit sealing fittings in hazardous areas.
 - .1 Fill with compound.
- .8 Minimum conduit size for lighting and power circuits: 19 mm.

- .9 Bend conduit cold:
 - .1 Replace conduit if kinked or flattened more than 1/10th of its original diameter.
- .10 Field threads on rigid conduit must be of sufficient length to draw conduits up tight.
- .11 Remove and replace blocked conduit sections.
 - .1 Do not use liquids to clean out conduits.
- .12 Dry conduits out before installing wire.

3.3 SURFACE CONDUITS

- .1 Run parallel or perpendicular to building lines.
- .2 Locate conduits behind infrared or gas fired heaters with 1.5 m clearance.
- .3 Run conduits in flanged portion of structural steel.
- .4 Group conduits wherever possible on suspended surface channels.
- .5 Do not pass conduits through structural members except as indicated.
- .6 Do not locate conduits less than 75 mm parallel to steam or hot water lines with minimum of 25 mm at crossovers.

3.4 CLEANING

- .1 Proceed in accordance with Section 01 74 11 - Cleaning.
- .2 On completion and verification of performance of installation, remove surplus materials, excess materials, rubbish, tools and equipment.

END OF SECTION

Part 1 General

1.1 REFERENCES

- .1 CSA International
 - .1 CSA C22.2 No.31-10, Switchgear Assemblies.
- .2 Electrical and Electronic Manufacturers' Association of Canada (EEMAC)
 - .1 EEMAC G8-3.3-89, Metal Enclosed Interrupter Switchgear Assemblies.

1.2 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
 - .1 Submit manufacturer's instructions, printed product literature and data sheets for low voltage switchgear and include product characteristics, performance criteria, physical size, finish and limitations.
- .3 Shop Drawings:
 - .1 Indicate on drawings:
 - .1 Floor anchoring method and foundation template.
 - .2 Dimensioned [cable] entry and exit locations.
 - .3 Dimensioned position and size of bus.
 - .4 Overall length, height and depth of complete switchgear.
 - .5 Dimensioned layout of internal and front panel mounted components.

1.3 CLOSEOUT SUBMITTALS

- .1 Submit in accordance with Section 01 78 00 - Closeout Submittals.
- .2 Operation and Maintenance Data: submit operation and maintenance data for low voltage switchgear and components for incorporation into manual.

Part 2 Products

2.1 MATERIALS

- .1 Switchgear assembly: to CSA C22.2 No.31 EEMAC G8-3.3.

2.2 RATING

- .1 Secondary switchgear: outdoor, 120/208 V, 400 A, 3 phase, 4 wire, 60 Hz, minimum short circuit capacity 18 kA (rms symmetrical).
- .2 Enclosure to be rated NEMA 4x

2.3 SPLITTERS

- .1 Three phase and 100% rated bare busbars, continuous current rating 400 A self-cooled, extending full width of suitably supported on insulators.
- .2 Busbars and main connections: 99.30% minimum conductivity copper.
- .3 Tin plated joints, secured with non-corrosive bolts and Belleville washers.
- .4 Identify phases of busbars by suitable marking.
- .5 Busbar connectors, when switchboard shipped in more than one section.

2.4 EQUIPMENT IDENTIFICATION

- .1 Identify equipment in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Nameplates:
 - .1 White plate, black letters, size 7.
 - .2 Complete switchgear labelled: voltage, system configuration and main bus ampacity.

Part 3 Execution

3.1 INSTALLATION

- .1 Connect load side of breakers in distribution cubicles to distribution feeders.
- .2 Check factory made connections for mechanical security and electrical continuity.
- .3 Run one grounding conductor #2 AWG bare copper in conduit from ground bus to ground.
- .4 Check trip unit settings against co-ordination study to ensure proper working and protection of components.

END OF SECTION

Part 1 General

1.1 REFERENCES

- .1 CSA International
 - .1 CSA C22.2 No.42-10, General Use Receptacles, Attachment Plugs and Similar Devices.
 - .2 CAN/CSA C22.2 No.42.1-00(R2009), Cover Plates for Flush-Mounted Wiring Devices (Bi-national standard, with UL 514D).
 - .3 CSA C22.2 No.55-M1986(R2008), Special Use Switches.
 - .4 CSA C22.2 No.111-10, General-Use Snap Switches (Bi-national standard, with UL 20).

Part 2 Products

2.1 SWITCHES

- .1 20 A, 120 V single pole, switches to: CSA C22.2 No.55 CSA C22.2 No.111.
- .2 Manually-operated general purpose AC switches with following features:
 - .1 Terminal holes approved for No. 10 AWG wire.
 - .2 Silver alloy contacts.
 - .3 Urea or melamine moulding for parts subject to carbon tracking.
 - .4 Suitable for back and side wiring.
 - .5 Ivory toggle.
- .3 Toggle operated locking fully rated for tungsten filament and fluorescent lamps, and up to 80% of rated capacity of motor loads heating loads.
- .4 Switches of one manufacturer throughout project.

2.2 RECEPTACLES

- .1 Duplex receptacles, CSA type 5-15 R, 125 V, 15 A, U ground, to: CSA C22.2 No.42 with following features:
 - .1 Ivory urea moulded housing.
 - .2 Suitable for No. 10 AWG for back and side wiring.
 - .3 Break-off links for use as split receptacles.
 - .4 Eight back wired entrances, four side wiring screws.
 - .5 Triple wipe contacts and rivetted grounding contacts.
- .2 Single receptacles CSA type 5-15 R, 125 V, 15 A, U ground with following features:
 - .1 Ivory urea moulded housing.
 - .2 Suitable for No. 10 AWG for back and side wiring.
 - .3 Four back wired entrances, 2 side wiring screws.

- .3 Other receptacles with ampacity and voltage as indicated.
- .4 Receptacles of one manufacturer throughout project.

2.3 COVER PLATES

- .1 Cover plates for wiring devices to: CSA C22.2 No.42.1.
- .2 Weatherproof double lift spring-loaded cast aluminum cover plates, complete with gaskets for duplex receptacles as indicated.
- .3 Weatherproof spring-loaded cast aluminum cover plates complete with gaskets for single receptacles or switches.

2.4 SOURCE QUALITY CONTROL

- .1 Cover plates from one manufacturer throughout project.

Part 3 Execution

3.1 INSTALLATION

- .1 Switches:
 - .1 Install single throw switches with handle in "UP" position when switch closed.
 - .2 Install switches in gang type outlet box when more than one switch is required in one location.
 - .3 Mount toggle switches at height as indicated in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Receptacles:
 - .1 Install receptacles in gang type outlet box when more than one receptacle is required in one location.
 - .2 Mount receptacles at height as indicated in accordance with Section 26 05 00 - Common Work Results for Electrical.
 - .3 Where split receptacle has one portion switched, mount vertically and switch upper portion.
 - .4 Install GFI type receptacles as indicated.
- .3 Cover plates:
 - .1 Install suitable common cover plates where wiring devices are grouped.
 - .2 Do not use cover plates meant for flush outlet boxes on surface-mounted boxes.

END OF SECTION

Part 1 General

1.1 REFERENCES

- .1 International Electrotechnical Commission (IEC)
 - .1 IEC 947-4-1-2002, Part 4: Electromechanical contactors and motor-starters.

1.2 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Provide submittals in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
 - .1 Provide manufacturer's printed product literature, specifications and datasheet and include product characteristics, performance criteria, physical size, finish and limitations.
- .3 Shop Drawings:
 - .1 Provide shop drawings: in accordance with Section 01 33 00 - Submittal Procedures.
 - .1 Provide shop drawings for each type of starter to indicate:
 - .1 Mounting method and dimensions.
 - .2 Starter size and type.
 - .3 Layout and components.
 - .4 Enclosure types.
 - .5 Wiring diagram.
 - .6 Interconnection diagrams.

Part 2 Products

2.1 MATERIALS

- .1 Starters: to IEC 947-4 with AC4 utilization category.

2.2 MANUAL MOTOR STARTERS

- .1 Three phase manual motor starters of size, type, rating, and enclosure type as indicated, with components as follows:
 - .1 Switching mechanism, quick make and break.
 - One Three overload heaters, manual reset, trip indicating handle.
- .2 Accessories:
 - .1 pushbutton Toggle Key switch: standard heavy duty oil tight labelled as indicated.
 - .2 Indicating light: standard heavy duty oil tight type and colour as indicated.
 - .3 Locking tab to permit padlocking in "ON" or "OFF" position.

2.3 FULL VOLTAGE MAGNETIC STARTERS

- .1 Combination magnetic starters of size, type, rating and enclosure type NEMA 4x with components as follows:
 - .1 Contactor solenoid operated, rapid action type.
 - .2 Motor overload protective device in each phase, manually reset from outside enclosure.
 - .3 Wiring and schematic diagram inside starter enclosure in visible location.
 - .4 Identify each wire and terminal for external connections, within starter, with permanent number marking identical to diagram.
- .2 Combination type starters to include fused disconnect switch with operating lever on outside of enclosure to control disconnect and provision for:
 - .1 Locking in "OFF" position with up to 3 padlocks.
 - .2 Independent locking of enclosure door.
 - .3 Provision for preventing switching to "ON" position while enclosure door open.
- .3 Accessories:
 - .1 Pushbuttons AWD Selector switches: oil tight labelled as indicated.
 - .2 Indicating lights: oil tight type and color as indicated.
 - .3 1-N/O and 1-N/C spare auxiliary contacts unless otherwise indicated.

2.4 CONTROL TRANSFORMER

- .1 Single phase, dry type, control transformer with primary voltage as indicated and 120 V secondary, complete with secondary fuse, installed in with starter as indicated.
- .2 Size control transformer for control circuit load plus 20% spare capacity.

2.5 ACCESSORIES

- .1 Pushbutton: heavy duty, oil tight as required.
- .2 Selector switches: heavy duty, oil tight as required.
- .3 Indicating lights: heavy duty, oil tight, type and colour as indicated.

2.6 FINISHES

- .1 Finish to enclosure to be suitable for exterior mounting and in accordance with Section 26 05 00 - Common Work Results for Electrical.

2.7 EQUIPMENT IDENTIFICATION

- .1 Provide equipment identification in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Manual starter designation label, white plate, black letters, size 1, engraved as indicated.
- .3 Magnetic starter designation label, white plate, black letters, size 6 engraved as indicated.

Part 3 Execution

3.1 INSTALLATION

- .1 Install starters and control devices in accordance with manufacturer's instructions.
- .2 Install and wire starters and controls as indicated.
- .3 Ensure correct fuses installed.
- .4 Confirm motor nameplate and adjust overload device to suit.

3.2 FIELD QUALITY CONTROL

- .1 Perform tests in accordance with Section 26 05 00 - Common Work Results for Electrical and manufacturer's instructions.
- .2 Operate switches and contactors to verify correct functioning.
- .3 Perform starting and stopping sequences of contactors and relays.
- .4 Check that sequence controls, interlocking with other separate related starters, equipment, control devices, operate as indicated.

END OF SECTION

Part 1 General

1.1 REFERENCES

- .1 American National Standards Institute (ANSI)
 - .1 ANSI C82.1-04, Lamp Ballasts-Line Frequency Fluorescent Lamp Ballast.
 - .2 ANSI C82.4-02(R2007), Ballasts for High-Intensity-Discharge and Low-Pressure Sodium Lamps Multi Supply Type.
- .2 American National Standards Institute/Institute of Electrical and Electronics Engineers (ANSI/IEEE)
 - .1 ANSI/IEEE C62.41-1991, Recommended Practice for Surge Voltages in Low-Voltage AC Power Circuits.
- .3 ASTM International Inc.
 - .1 ASTM F1137-00(2006), Standard Specification for Phosphate/Oil and Phosphate/Organic Corrosion Protective Coatings for Fasteners.
- .4 Canadian Standards Association (CSA International)
- .5 ICES-005-07, Radio Frequency Lighting Devices.
- .6 Underwriters' Laboratories of Canada (ULC)

1.2 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Provide submittals in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
 - .1 Provide manufacturer's printed product literature, specifications and datasheet and include product characteristics, performance criteria, physical size, finish and limitations.
 - .2 Provide complete photometric data prepared by independent testing laboratory for luminaires where specified, for approval review by Departmental Representative.
 - .3 Photometric data to include: VCP Table where applicable spacing criterion.

1.3 DELIVERY, STORAGE AND HANDLING

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements.
- .2 Deliver materials to site in original factory packaging, labelled with manufacturer's name, address.
- .3 Divert unused metal materials from landfill to metal recycling facility.
- .4 Disposal and recycling of fluorescent lamps as per local regulations.
- .5 Coordinate with Hazard Material Abatement Contractor for Disposal of old PCB filled ballasts.

Part 2 Products

2.1 LAMPS

- .1 LED Lamps, CRI 80, 50,000 hour lamp life LM 70 Rated, Colour temperature as noted on fixture schedule.

2.2 BALLASTS

- .1 Fluorescent ballast: CBM and CSA certified, energy efficient type, IC electronic IC electronic dimmable.
 - .1 Rating: voltage as indicated 120 V, 60 Hz, for use with 2-32W, rapid start lamps.
 - .2 Totally encased and designed for 40 degrees Celsius ambient temperature.
 - .3 Power factor: minimum 95 % with 95% of rated lamp lumens.
 - .4 Current crest factor: 1.7 maximum.
 - .5 Harmonics: 10 % maximum THD.
 - .6 Operating frequency of electronic ballast: 20 kHz minimum.
 - .7 Total circuit power: 62 Watts.
 - .8 Ballast factor: greater than 0.90.
 - .9 Sound rated: Class A.
 - .10 Mounting: integral with luminaire.
- .2 LED ballast:
 - .1 Rating: voltage as indicated 120 V, 60 Hz, matched to LED Lamp wattage.
 - .2 Totally encased and designed for 40 degrees Celsius ambient temperature.
 - .3 Power factor: minimum 95 % with 95% of rated lamp lumens.
 - .4 Harmonics, 10% maximum PHD.
 - .5 Input voltage range: plus or minus 10% of nominal.
 - .6 Minimum starting temperature: minus 30 degrees Celsius at 90% line voltage.
 - .7 Mounting: integral with luminaire.
 - .8 Current crest factor: 1.7 maximum current.

2.3 FINISHES

- .1 Light fixture finish and construction to meet ULC listings and CSA certifications related to intended installation.

2.4 OPTICAL CONTROL DEVICES

- .1 As indicated in luminaire schedule.

2.5 LUMINAIRES

- .1 As indicated in luminaire schedule.

Part 3 Execution

3.1 INSTALLATION

- .1 Locate and install luminaires as indicated.
- .2 Provide adequate support to suit ceiling system.

3.2 WIRING

- .1 Connect luminaires to lighting circuits:
 - .1 Install flexible or rigid conduit for luminaires as indicated.

3.3 LUMINAIRE SUPPORTS

- .1 For suspended ceiling installations support luminaires independently of ceiling support luminaires from ceiling grid in accordance with local inspection requirements.

3.4 LUMINAIRE ALIGNMENT

- .1 Align luminaires mounted in continuous rows to form straight uninterrupted line.
- .2 Align luminaires mounted individually parallel or perpendicular to building grid lines.

3.5 COMMISSIONING

- .1 For Retrofitted Fixtures, provide CSA Certification of new lighting components in existing fixtures.

END OF SECTION