

**Part 1 GENERAL**

**1.1 REFERENCES**

- .1 Canadian Standards Association (CSA International)
  - .1 CSA C22.1-15, Canadian Electrical Code, Part 1, 23rd Edition.

**1.2 ACTION AND INFORMATIONAL SUBMITTALS**

- .1 Provide submittals in accordance with Section 01 33 00 - Submittal Procedures.

**1.3 DELIVERY, STORAGE AND HANDLING**

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements.
- .2 Waste Management and Disposal:
  - .1 Separate waste materials for reuse and recycling in accordance with Section 01 74 21 - Construction/Demolition Waste Management and Disposal.

**Part 2 PRODUCTS**

**2.1 OUTLET AND CONDUIT BOXES GENERAL**

- .1 Size boxes in accordance with CSA C22.1.
- .2 102 mm square or larger outlet boxes as required.
- .3 Gang boxes where wiring devices are grouped.
- .4 Blank cover plates for boxes without wiring devices.
- .5 347 V outlet boxes for 347 V switching devices.
- .6 Combination boxes with barriers where outlets for more than one system are grouped.

**2.2 GALVANIZED STEEL OUTLET BOXES**

- .1 One-piece electro-galvanized construction.
- .2 Single and multi gang flush device boxes for flush installation, minimum size 76 x 50 x 38 mm or as indicated. 102 mm square outlet boxes when more than one conduit enters one side with extension and plaster rings as required.
- .3 Utility boxes for outlets connected to surface-mounted EMT conduit, minimum size 102 x 54 x 48 mm.
- .4 102 mm square or octagonal outlet boxes for lighting fixture outlets.

- .5 Extension and plaster rings for flush mounting devices in finished plaster and tile walls.

## **2.3 MASONRY BOXES**

- .1 Electro-galvanized steel masonry single and multi gang boxes for devices flush mounted in exposed block walls.

## **2.4 FITTINGS - GENERAL**

- .1 Bushing and connectors with nylon insulated throats.
- .2 Knock-out fillers to prevent entry of debris.
- .3 Conduit outlet bodies for conduit up to 35mm and pull boxes for larger conduits.
- .4 Double locknuts and insulated bushings on sheet metal boxes.

## **Part 3 EXECUTION**

### **3.1 INSTALLATION**

- .1 Support boxes independently of connecting conduits.
- .2 Fill boxes with paper, sponges or foam or similar approved material to prevent entry of debris during construction. Remove upon completion of work.
- .3 For flush installations mount outlets flush with finished wall using plaster rings to permit wall finish to come within 6 mm of opening.
- .4 Provide correct size of openings in boxes for conduit, mineral insulated and armoured cable connections. Do not install reducing washers.
- .5 Vacuum clean interior of outlet boxes before installation of wiring devices.
- .6 Identify systems for outlet boxes as required.

**END OF SECTION**