

PART 1 - GENERAL

- 1.1 REFERENCES
- .1 Canada Green Building Council (CaGBC)
 - .1 LEED Canada-NC-2009, LEED (Leadership in Energy and Environmental Design): Green Building Rating System Reference Package For New Construction and Major Renovations.
 - .2 CSA International
 - .1 CSA C22.2 No.141-10, Emergency Lighting Equipment.
- 1.2 ACTION AND INFORMATIONAL SUBMITTALS
- .1 Submit in accordance with Section 01 33 00 - Submittal Procedures.
 - .2 Product Data:
 - .1 Submit manufacturer's instructions, printed product literature and data sheets for emergency lighting and include product characteristics, performance criteria, physical size, finish and limitations.
 - .3 Sustainable Design Submittals:
 - .1 LEED Canada submittals: in accordance with Section 01 35 21 - LEED Requirements.
 - .2 Construction Waste Management:
 - .1 Submit project Waste Management Plan highlighting recycling and salvage requirements.
 - .2 Submit calculations on end-of-project recycling rates, salvage rates, and landfill rates demonstrating that 75% of construction wastes were recycled or salvaged.
- 1.3 CLOSEOUT SUBMITTALS
- .1 Submit in accordance with Section 01 78 00 - Closeout Submittals.
 - .2 Operation and Maintenance Data: submit operation and maintenance data for emergency lighting for incorporation into manual.
-

- 1.4 DELIVERY,
STORAGE AND
HANDLING
- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements and with manufacturer's written instructions.
 - .2 Develop Construction Waste Management Plan related to Work of this Section and in accordance with Section 01 35 21 - LEED Requirements.
 - .3 Packaging Waste Management: remove for reuse or return of pallets, crates, padding, banding, and packaging materials as specified in Construction Waste Management Plan in accordance with Section 01 74 21 - Construction/Demolition Waste Management and Disposal and Section 01 35 21 - LEED Requirements.
- 1.5 WARRANTY
- .1 For batteries in this Section 26 52 00 - Emergency Lighting, 12 months warranty period is extended to 120 months.

PART 2 - PRODUCTS

- 2.1 EQUIPMENT
- .1 Emergency lighting equipment: to CSA C22.2 No.141.
 - .2 Supply voltage: 120 V, AC.
 - .3 Output voltage: 12 V DC.
 - .4 Operating time: 90 minutes, 72 W capacity.
 - .5 Battery: sealed, maintenance free.
 - .6 Charger: solid state, multi-rate, voltage/current regulated, inverse temperature compensated, short circuit protected with regulated output of plus or minus 0.01 V for plus or minus 10% input variations.
 - .7 Solid state transfer circuit.
-

2.1 EQUIPMENT
(Cont'd)

- .8 Low voltage disconnect: solid state, modular, operates at 80% battery output voltage.
- .9 Signal lights: solid state, for 'AC Power ON'.
- .10 Lamp heads: integral on unit or remote, 345 degrees horizontal and 180 degrees vertical adjustment. Lamp type: LED, 5 W minimum.
- .11 Cabinet: compact size; approximately 300 mm x 90 mm x 150 mm high suitable for direct or shelf mounting to wall and complete with knockouts for conduit. Removable or hinged front panel for easy access to batteries.
- .12 Finish: standard.
- .13 Auxiliary equipment:
 - .1 Ammeter.
 - .2 Voltmeter.
 - .3 Test switch.
 - .4 Battery disconnect device.
 - .5 AC input and DC output terminal blocks inside cabinet.
 - .6 Bracket.
- .14 Standard of Acceptance:
 - .1 Emergi-Lite JMLG Series.
 - .2 Lumacell RGC Series.
 - .3 AimLite EBST Series.

2.2 WIRING OF
REMOTE HEADS

- .1 Conduit: in accordance with Section 26 05 34 - Conduits, Conduit Fastenings and Conduit Fittings.
- .2 Conductors: RW90 type in accordance with Section 26 05 21 - Wires and Cables (0-1000 V), sized as indicated in accordance with manufacturer's recommendations.

PART 3 - EXECUTION

- 3.1 INSTALLATION .1 Install unit equipment and remote mounted fixtures.
- .2 Direct heads.
- 3.2 CLEANING .1 Progress Cleaning: clean in accordance with Section 01 74 11 - Cleaning.
- .2 Waste Management: separate waste materials for reuse and recycling in accordance with Section 01 74 21 - Construction/Demolition Waste Management and Disposal and Section 01 35 21 - LEED Requirements.
- .1 Remove recycling containers and bins from site and dispose of materials at appropriate facility.
- 3.3 PROTECTION .1 Protect installed products and components from damage during construction.
- .2 Repair damage to adjacent materials caused by emergency lighting installation.