

**Part 1 General**

**1.1 Related Requirements**

- .1 This Section covers items common to Sections of Divisions 26 and 28. These Sections supplement requirements of Division 1.

**1.2 References**

- .1 Definitions:
  - .1 Electrical and electronic terms: unless otherwise specified or indicated, terms used in these specifications, and on drawings, are those defined by IEEE SP1122.
- .2 Reference Standards:
  - .1 CSA Group
    - .1 CSA C22.1-15, Canadian Electrical Code, Part 1 (23rd Edition), Safety Standard for Electrical Installations.
    - .2 CAN3-C235 latest enforceable edition, Preferred Voltage Levels for AC Systems, 0 to 50,000 V.
  - .2 Institute of Electrical and Electronics (IEEE)/National Electrical Safety Code Product Line (NESC)
    - .1 IEEE SP1122, The Authoritative Dictionary of IEEE Standards Terms, Latest enforceable Edition.

**1.3 Action And Informational Submittals**

- .1 Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
  - .1 Submit manufacturer's instructions, printed product literature and data sheets and include product characteristics, performance criteria, physical size, finish and limitations.
- .3 Submit for review fire alarm riser diagram, plan and zoning of building under plexiglass at fire alarm control panel and annunciator.
- .4 Shop drawings:
  - .1 Submit wiring diagrams and installation details of equipment indicating proposed location, layout and arrangement, control panels, accessories, piping, ductwork, and other items that must be shown to ensure co-ordinated installation.
  - .2 Identify on wiring diagrams circuit terminals and indicate internal wiring for each item of equipment and interconnection between each item of equipment.
  - .3 Indicate on drawings clearances for operation, maintenance, and replacement of operating equipment devices.
  - .4 If changes are required, notify Departmental Representative of these changes before they are made.

- .5 Certificates:
  - .1 Provide CSA certified equipment and material.
  - .2 Where CSA certified equipment and material is not available, submit such equipment and material to authority having jurisdiction for approval before delivery to site.
  - .3 Submit test results of installed electrical systems and instrumentation.
  - .4 Permits and fees: in accordance with General Conditions of contract.
  - .5 Submit, upon completion of Work, load balance report as described in PART 3 - LOAD BALANCE.
  - .6 Submit certificate of acceptance from authority having jurisdiction upon completion of Work to Departmental Representative.
- .6 Manufacturer's Field Reports: submit to Departmental Representative manufacturer's written report, within 3 days of review, verifying compliance of Work and electrical system and instrumentation testing, as described in PART 3 - FIELD QUALITY CONTROL.
- .7 Sustainable Design Submittals:

#### **1.4 Closeout Submittals**

- .1 Submit in accordance with Section 01 78 00 - Closeout Submittals.
- .2 Operation and Maintenance Data: submit operation and maintenance data for incorporation into manual.
  - .1 Provide for each system and principal item of equipment as specified in technical sections for use by operation and maintenance personnel.
  - .2 Operating instructions to include following:
    - .1 Wiring diagrams, control diagrams, and control sequence for each principal system and item of equipment.
    - .2 Start up, proper adjustment, operating, lubrication, and shutdown procedures.
    - .3 Safety precautions.
    - .4 Procedures to be followed in event of equipment failure.
    - .5 Other items of instruction as recommended by manufacturer of each system or item of equipment.
  - .3 Print or engrave operating instructions and frame under glass or in approved laminated plastic.
  - .4 Post instructions where directed.
  - .5 For operating instructions exposed to weather, provide weather-resistant materials or weatherproof enclosures.
  - .6 Ensure operating instructions will not fade when exposed to sunlight and are secured to prevent easy removal or peeling.

#### **1.5 Delivery, Storage And Handling**

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements and with manufacturer's written instructions.

- .2 Delivery and Acceptance Requirements: deliver materials to site in original factory packaging, labelled with manufacturer's name and address.
- .3 Storage and Handling Requirements:
  - .1 Store materials off ground, indoors, in dry location and in accordance with manufacturer's recommendations in clean, dry, well-ventilated area.
  - .2 Store and protect all materials and equipment from nicks, scratches, and blemishes.
  - .3 Replace defective or damaged materials with new.

## **Part 2 Products**

### **2.1 Design Requirements**

- .1 Operating voltages: to CAN3-C235.
- .2 Motors, electric heating, control and distribution devices and equipment to operate satisfactorily at 60 Hz within normal operating limits established by above standard.
  - .1 Equipment to operate in extreme operating conditions established in above standard without damage to equipment.
- .3 Language operating requirements: provide identification nameplates for control items in English.
- .4 Use one nameplate for each language.

### **2.2 Materials And Equipment**

- .1 Provide material and equipment in accordance with Section 01 61 00 - Common Product Requirements.
- .2 Material and equipment to be CSA certified. Where CSA certified material and equipment are not available, obtain special approval from authority having jurisdiction before delivery to site and submit such approval as described in PART 1 - ACTION AND INFORMATIONAL SUBMITTALS.
- .3 Factory assemble control panels and component assemblies.

### **2.3 Electric Motors, Equipment And Controls**

- .1 Verify installation and co-ordination responsibilities related to motors, equipment and controls, as indicated.

### **2.4 Warning Signs**

- .1 Warning Signs: in accordance with requirements of authority having jurisdiction and Departmental Representative.
- .2 Decal signs, minimum size 175 x 250 mm.

### **2.5 Wiring Terminations**

- .1 Ensure lugs, terminals, screws used for termination of wiring are suitable for either copper or aluminum conductors.

## 2.6 Equipment Identification

- .1 Identify electrical equipment with nameplates as follows:

- .1 Nameplates: lamicoid 3 mm thick plastic engraving sheet, black face, white core, lettering accurately aligned and engraved into core and mechanically attached with self tapping screws.

- .2 Sizes as follows:

NAMEPLATE SIZES			
Size 1	10 x 50 mm	1 line	3 mm high letters
Size 2	12 x 70 mm	1 line	5 mm high letters
Size 3	12 x 70 mm	2 lines	3 mm high letters
Size 4	20 x 90 mm	1 line	8 mm high letters
Size 5	20 x 90 mm	2 lines	5 mm high letters
Size 6	25 x 100 mm	1 line	12 mm high letters
Size 7	25 x 100 mm	2 lines	6 mm high letters

- .2 Labels: embossed plastic labels with 6 mm high letters unless specified otherwise.
- .3 Wording on nameplates to be approved by Departmental Representative prior to manufacture.
- .4 Allow for minimum of twenty-five (25) letters per nameplate.
- .5 Nameplates for terminal cabinets and junction boxes to indicate system and/or voltage characteristics.
- .6 Identify equipment with Size 3 labels engraved "ASSET INVENTORY NO. \_\_\_\_" as directed by Departmental Representative.
- .7 Disconnects, starters and contactors: indicate equipment being controlled and voltage.
- .8 Terminal cabinets and pull boxes: indicate system and voltage.
- .9 Transformers: indicate capacity, primary and secondary voltages.

## 2.7 Wiring Identification

- .1 Identify wiring with permanent indelible identifying markings, coloured plastic tapes, on both ends of phase conductors of feeders and branch circuit wiring.
- .2 Maintain phase sequence and colour coding throughout.
- .3 Colour coding: to CSA C22.1.
- .4 Use colour coded wires in communication cables, matched throughout system.

## 2.8 Conduit And Cable Identification

- .1 Colour code conduits, boxes and metallic sheathed cables.
- .2 Code with plastic tape or paint at points where conduit or cable enters wall, ceiling, or floor, and at 15 m intervals.
- .3 Colours: 25 mm wide prime colour and 20 mm wide auxiliary colour.

	Prime	Auxiliary
up to 250 V	Yellow	
up to 600 V	Yellow	Green
Other Communication Systems	Green	Blue
Fire Alarm	Red	
Emergency Voice	Red	Blue
Other Security Systems	Red	Yellow

## 2.9 **Finishes**

- .1 Shop finish metal enclosure surfaces by application of rust resistant primer inside and outside, and at least two coats of finish enamel.

## Part 3 **Execution**

### 3.1 **Examination**

- .1 Verification of Conditions: verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for installation in accordance with manufacturer's written instructions.
  - .1 Visually inspect substrate in presence of Departmental Representative.
  - .2 Inform Departmental Representative of unacceptable conditions immediately upon discovery.
  - .3 Proceed with installation only after unacceptable conditions have been remedied and after receipt of written approval to proceed from Departmental Representative.

### 3.2 **Installation**

- .1 Do complete installation in accordance with CSA C22.1 except where specified otherwise.
- .2 Do overhead and underground systems in accordance with CAN/CSA-C22.3 No.1 except where specified otherwise.

### 3.3 **Nameplates And Labels**

- .1 Ensure manufacturer's nameplates, CSA labels and identification nameplates are visible and legible after equipment is installed.

### 3.4 **Conduit And Cable Installation**

- .1 Install conduit and sleeves prior to pouring of concrete.
  - .1 Sleeves through concrete: plastic, sized for free passage of conduit, and protruding 50 mm.
- .2 If plastic sleeves are used in fire rated walls or floors, remove before conduit installation.
- .3 Install cables, conduits and fittings embedded or plastered over, close to building structure so furring can be kept to minimum.

### **3.5 Location Of Outlets**

- .1 Locate outlets in accordance with Section 26 05 32 - Outlet Boxes, Conduit Boxes and Fittings.
- .2 Do not install outlets back-to-back in wall; allow minimum 150 mm horizontal clearance between boxes.
- .3 Change location of outlets at no extra cost or credit, providing distance does not exceed 3000 mm, and information is given before installation.
- .4 Locate light switches on latch side of doors.
  - .1 Locate disconnect devices in mechanical and elevator machine rooms on latch side of floor.

### **3.6 Mounting Heights**

- .1 Mounting height of equipment is from finished floor to centreline of equipment unless specified or indicated otherwise.
- .2 If mounting height of equipment is not specified or indicated, verify before proceeding with installation.
- .3 Install electrical equipment at following heights unless indicated otherwise.
  - .1 Local switches: 1200 mm to top of device.
  - .2 Wall receptacles:
    - .1 General: 400 mm.
    - .2 Above top of continuous baseboard heater: 200 mm.
    - .3 Above top of counters or counter splash backs: 175 mm.
    - .4 In mechanical rooms: 1400 mm.
  - .3 Panelboards: as required by Code or as indicated.
  - .4 Fire alarm stations: 1150 mm.
  - .5 Fire alarm bells: 2100 mm.

### **3.7 Co-Ordination Of Protective Devices**

- .1 Ensure circuit protective devices such as overcurrent trips, relays and fuses are installed to required values and settings.

### **3.8 Field Quality Control**

- .1 Load Balance:
  - .1 Measure phase current to panelboards with normal loads (lighting) operating at time of acceptance; adjust branch circuit connections as required to obtain best balance of current between phases and record changes.
  - .2 Measure phase voltages at loads and adjust transformer taps to within 2% of rated voltage of equipment.
  - .3 Provide upon completion of work, load balance report as directed in PART 1 - ACTION AND INFORMATIONAL SUBMITTALS, phase and neutral currents on panelboards, dry-core transformers and motor control centres, operating under normal load, as well as hour and date on which each load was measured, and voltage at time of test.

- .2 Conduct following tests in accordance with Section 01 45 00 - Quality Control.
  - .1 Circuits originating from branch distribution panels.
  - .2 Lighting and its control.
  - .3 Motors, heaters and associated control equipment including sequenced operation of systems where applicable.
  - .4 Systems: fire alarm.
  - .5 Insulation resistance testing:
    - .1 Megger circuits, feeders and equipment up to 350 V with a 500 V instrument.
    - .2 Megger 350-600 V circuits, feeders and equipment with a 1000 V instrument.
    - .3 Check resistance to ground before energizing.
- .3 Carry out tests in presence of Departmental Representative.
- .4 Provide instruments, meters, equipment and personnel required to conduct tests during and at conclusion of project.
- .5 Manufacturer's Field Services:
  - .1 Obtain written report from manufacturer verifying compliance of Work, in handling, installing, applying, protecting and cleaning of product and submit Manufacturer's Field Reports as described in PART 1 - ACTION AND INFORMATIONAL SUBMITTALS.
  - .2 Provide manufacturer's field services consisting of product use recommendations and periodic site visits for inspection of product installation in accordance with manufacturer's instructions.

### **3.9 System Startup**

- .1 Instruct Departmental Representative and operating personnel in operation, care and maintenance of systems, system equipment and components.
- .2 Arrange and pay for services of manufacturer's factory service engineer to supervise start-up of installation, check, adjust, balance and calibrate components and instruct operating personnel.
- .3 Provide these services for such period, and for as many visits as necessary to put equipment in operation, and ensure that operating personnel are conversant with aspects of its care and operation.

### **3.10 Cleaning**

- .1 Progress Cleaning: clean in accordance with Section 01 74 11 - Cleaning.
  - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 11 - Cleaning.

**END OF SECTION**

**PART 1      General**

**1.1          Related Work**

- .1      Refer to all sections of the specification for related work.

**1.2          Coordination**

- .1      The existing building shall remain open and remain in normal operation during the construction period.
- .2      Contractor shall allow for off-hours work as required.
- .3      Where existing services or systems, such as electrical power, telephone system, data systems, fire alarm system, etc. are required to be disrupted and/or shut-down, coordinate the shut-downs with the Departmental Representative and carry out the work at a time and in a manner acceptable to them. Carefully schedule all disruptions and/or shutdowns and ensure the duration of same is kept to the absolute minimum. Submit for review, a written concise schedule of each disruption at least 120 hours in advance of performing work and obtain written consent prior to implementing.
- .4      Should any temporary connections be required to maintain services or systems during work in the existing building, supply and install all necessary material and equipment and provide all labour at no extra cost. Should any existing equipment or system be damaged, make full repairs without extra cost, and to the satisfaction of the Departmental Representative.
- .5      Comply with instructions regarding working hours necessary to maintain the building in operation.

**1.3          Existing Devices In New Construction**

- .1      Disconnect and remove existing electrical equipment made obsolete due to the renovations. Remove associated wiring and conduits back to source panel.
- .2      Where existing devices (receptacles, switches, etc.) are presently mounted on a wall which will be covered with a new finish, provide an extension ring, coverplate, etc., as required, to mount the device to the new wall finish.
- .3      Identify all existing electrical equipment to remain, which is located in or on portions of existing walls being modified and/or demolished, devices shall be relocated to the nearest wall. This equipment shall include cabinets, panels, switches, receptacles, etc.
- .4      Where existing conduits, which are in use, pass vertically through a wall being demolished, relocate those conduits and conceal in a new wall or surface mount in a service area. Extend conduit, wiring, etc. as required.

- .5 Identify work or equipment installation/removal located in plaster walls and inform Departmental Representative for directions before commencing work.
- .6 Where new ceilings are to be installed, relocate all existing ceiling mounted devices down or to suit new ceiling. This equipment shall include but not be limited to smoke detectors, heat detectors, speakers, luminaires, etc. Extend existing conduit and wiring as required.
- .7 All existing junction boxes in walls and ceiling spaces required to maintain existing circuits shall remain accessible.
- .8 Include all costs to x-ray existing floors to be drilled or sleeved to ensure no existing services are severed or damaged. Damages could be very serious. Any damages resulting from failure to x-ray (or scan) is the Contractor's responsibility.
- .9 Panelboards and devices included or related to renovation may be located in plaster walls. Where electrical equipment or devices are found located in plaster walls, review work and options with DCC Representative before proceeding.

#### **1.4 Schedule Of Work**

- .1 Confirm Schedule of work and include all requirements to conform to it.

### **PART 2 Products**

#### **2.1 Materials**

- .1 Provide all materials required for the complete interface and reconnection installation as herein described and as indicated on the drawings.
- .2 New wiring required to interconnect new devices to existing systems shall be provided to suit the manufacturer's requirements and instructions.
- .3 Add modules, switches, etc., in existing control panels as required, Electrical Contractor to allow for modifications and extend existing systems to the new or renovated areas.

### **PART 3 Execution**

#### **3.1 Installation**

- .1 Install boxes, conduit and wiring through existing areas as required for the new installation.
- .2 Patch and repair walls and ceilings in existing building that have been damaged or cut open due to the new electrical installation.

- .3 Patch and make good existing walls which are to remain where existing electrical devices have been removed.
- .4 Where new cables or conduits have been installed through existing fire rated walls, seal opening around cables and conduit to maintain fire rating.

**END OF SECTION**

**Part 1            General**

**1.1            Related Requirements**

- .1        This Section covers items common to Sections of Divisions 26 and 28. These Sections supplement requirements of Division 1.

**1.2            References**

- .1        CSA International
  - .1        CAN/CSA-C22.2 No.18 Latest enforceable Edition, Outlet Boxes, Conduit Boxes and Fittings.
  - .2        CAN/CSA-C22.2 No.65 Latest enforceable Edition, Wire Connectors
- .2        Electrical and Electronic Manufacturers' Association of Canada (EEMAC)
  - .1        EEMAC 1Y-2-1961, Bushing Stud Connectors and Aluminum Adapters (1200 Ampere Maximum Rating).
- .3        National Electrical Manufacturers Association (NEMA)

**1.3            Action And Informational Submittals**

- .1        Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2        Product Data:
  - .1        Submit manufacturer's instructions, printed product literature and data sheets for wire and box connectors and include product characteristics, performance criteria, physical size, finish and limitations.

**1.4            Closeout Submittals**

- .1        Submit in accordance with Section 01 78 00 - Closeout Submittals.
- .2        Operation and Maintenance Data: submit operation and maintenance data for wire and box connectors for incorporation into manual.

**1.5            Delivery, Storage And Handling**

- .1        Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements and with manufacturer's written instructions.
- .2        Delivery and Acceptance Requirements: deliver materials to site in original factory packaging, labelled with manufacturer's name and address.
- .3        Storage and Handling Requirements:
  - .1        Store materials off ground, indoors, in dry location and in accordance with manufacturer's recommendations in clean, dry, well-ventilated area.
  - .2        Store and protect wire and box connectors from nicks, scratches, and blemishes.
  - .3        Replace defective or damaged materials with new.

## **Part 2 Products**

### **2.1 Materials**

- .1 Pressure type wire connectors to: CAN/CSA-C22.2 No.65, with current carrying parts of copper sized to fit copper conductors as required.
- .2 Fixture type splicing connectors to: CAN/CSA-C22.2 No.65, with current carrying parts of copper sized to fit copper conductors 10 AWG or less.
- .3 Bushing stud connectors: to NEMA to consist of:
  - .1 Connector body and stud clamp for stranded copper conductors.
  - .2 Clamp for stranded copper conductors.
  - .3 Stud clamp bolts.
- .4 Clamps or connectors for armoured cable, TECK cable as required to: CAN/CSA-C22.2 No.18.

## **Part 3 Execution**

### **3.1 Examination**

- .1 Verification of Conditions: verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for wire and box connectors installation in accordance with manufacturer's written instructions.
  - .1 Visually inspect substrate in presence of Departmental Representative.
  - .2 Inform Departmental Representative of unacceptable conditions immediately upon discovery.
  - .3 Proceed with installation only after unacceptable conditions have been remedied and after receipt of written approval to proceed from Departmental Representative.

### **3.2 Installation**

- .1 Remove insulation carefully from ends of conductors cables and:
  - .1 Apply coat of zinc joint compound on aluminum conductors prior to installation of connectors.
  - .2 Install mechanical pressure type connectors and tighten screws with appropriate compression tool recommended by manufacturer. Installation shall meet secureness tests in accordance with CAN/CSA-C22.2 No.65.
  - .3 Install fixture type connectors and tighten to CAN/CSA-C22.2 No.65. Replace insulating cap.
  - .4 Install bushing stud connectors in accordance with NEMA.

### **3.3 Cleaning**

- .1 Progress Cleaning: clean in accordance with Section 01 74 11 - Cleaning.
  - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 11 - Cleaning.

**END OF SECTION**

**Part 1 General**

**1.1 Related Requirements**

- .1 This Section covers items common to Sections of Divisions 26 and 28. These Sections supplement requirements of Division 1.

**1.2 References**

- .1 Not used.

**1.3 Product Data**

- .1 Provide product data in accordance with Section 01 33 00 - Submittal Procedures.

**1.4 Delivery, Storage And Handling**

- .1 Packaging Waste Management: remove for reuse and return of pallets, crates, padding and packaging materials in accordance with Section 01 74 21 - Construction/Demolition Waste Management and Disposal.

**Part 2 Products**

**2.1 Building Wires**

- .1 Conductors: stranded for 10 AWG and larger. Minimum size: 12 AWG.
- .2 Copper conductors: size as indicated, with 600V insulation of cross-linked thermosetting polyethylene material rated RW90 XLPE Jacketted.
- .3 Neutral supported cable: 1 phase insulated conductors of Copper and one neutral conductor of Copper steel reinforced, size as indicated. Type: NS90 Insulation: Type NS-1 rated 300 V.

**2.2 Teck 90 Cable**

- .1 Cable: in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Conductors:
  - .1 Grounding conductor: copper.
  - .2 Circuit conductors: copper, size as indicated.
- .3 Insulation:
  - .1 Ethylene propylene rubber EP.
  - .2 Cross-linked polyethylene XLPE.
  - .3 Rating: 600 V.
- .4 Inner jacket: polyvinyl chloride material.
- .5 Armour: interlocking galvanized steel.
- .6 Overall covering: thermoplastic polyvinyl chloride, compliant to applicable Building Code classification for this project.

- .7 Fastenings:
  - .1 One hole steel straps to secure surface cables 50 mm and smaller. Two hole steel straps for cables larger than 50 mm.
  - .2 Channel type supports for two or more cables at 1500 mm centers.
  - .3 Threaded rods: 6 mm diameter to support suspended channels.
- .8 Connectors:
  - .1 Watertight, approved for TECK cable.

### **2.3 Armoured Cables**

- .1 Conductors: insulated, copper, size as indicated.
- .2 Type: AC90.
- .3 Armour: interlocking type fabricated from galvanized steel strip.
- .4 Connectors: anti short connectors.

## **Part 3 Execution**

### **3.1 Field Quality Control**

- .1 Perform tests in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Perform tests using method appropriate to site conditions and to approval of Departmental Representative and local authority having jurisdiction over installation.
- .3 Perform tests before energizing electrical system.

### **3.2 General Cable Installation**

- .1 Terminate cables in accordance with Section 26 05 20 - Wire and Box Connectors - (0-1000 V).
- .2 Cable Colour Coding: to Section 26 05 00 - Common Work Results for Electrical.
- .3 Conductor length for parallel feeders to be identical.
- .4 Lace or clip groups of feeder cables at distribution centres, pull boxes, and termination points.
- .5 Wiring in walls: typically drop or loop vertically from above to better facilitate future renovations. Generally wiring from below and horizontal wiring in walls to be avoided unless indicated.
- .6 Provide numbered wire collars for control wiring. Numbers to correspond to control shop drawing legend. Obtain wiring diagram for control wiring.

### **3.3 Installation Of Building Wires**

- .1 Install wiring as follows:
  - .1 In conduit systems in accordance with Section 26 05 34 - Conduits, Conduit Fastenings and Conduit Fittings.
  - .2 In surface and lighting fixture raceways in accordance with Section 26 05 00.

**3.4 Installation Of Teck90 Cable (0 -1000 V)**

- .1 Group cables wherever possible on channels.
- .2 Install cable concealed, securely supported by straps.

**3.5 Installation Of Armoured Cables**

- .1 Group cables wherever possible on channels.

**END OF SECTION**

**Part 1            General**

**1.1            Related Requirements**

- .1        This Section covers items common to Sections of Divisions 26 and 28. These Sections supplement requirements of Division 1.

**1.2            References**

- .1        CSA Group
  - .1        CSA C22.1-15, Canadian Electrical Code, Part 1 (23rd Edition), Safety Standard for Electrical Installations.
  - .2        CSA C22.2 No.41-13, Grounding and Bonding Equipment (Tri-National Standard, with NMX-J-590ANCE and UL 467).
  - .3        CSA C22.2 No.65 Latest enforceable Edition, Wire connectors (Tri-National Standard, with UL 486A-486B NMX-J-543-ANCE).

**1.3            Action And Informational Submittals**

- .1        Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2        Product Data:
  - .1        Submit manufacturer's instructions, printed product literature and data sheets for connectors and terminations and include product characteristics, performance criteria, physical size, finish and limitations.
- .3        Certificates: obtain inspection certificate of compliance covering high voltage stress from inspection authority and include it with maintenance manuals.

**1.4            Closeout Submittals**

- .1        Submit in accordance with Section 01 78 00 - Closeout Submittals.
- .2        Operation and Maintenance Data: submit operation and maintenance data for connectors and terminations for incorporation into manual.

**1.5            Delivery, Storage And Handling**

- .1        Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements and with manufacturer's written instructions.
- .2        Delivery and Acceptance Requirements: deliver materials to site in original factory packaging, labelled with manufacturer's name and address.
- .3        Storage and Handling Requirements:
  - .1        Store materials off ground, indoors, in dry location and in accordance with manufacturer's recommendations in clean, dry, well-ventilated area.
  - .2        Store and protect connectors and terminations from nicks, scratches, and blemishes.
  - .3        Replace defective or damaged materials with new.

**Part 2 Products**

**2.1 Connectors And Terminations**

- .1 Copper long barrel compression connectors to CSA C22.2 No.65 as required sized for conductors.
- .2 Contact aid for aluminum cables where applicable.
- .3 2 way joint boxes dry location type in accordance with Section 26 05 33 - Raceway and Boxes for Electrical Systems.

**Part 3 Execution**

**3.1 Examination**

- .1 Verification of Conditions: verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for connectors and terminations installation in accordance with manufacturer's written instructions.
  - .1 Visually inspect substrate in presence of Departmental Representative.
  - .2 Inform Departmental Representative of unacceptable conditions immediately upon discovery.
  - .3 Proceed with installation only after unacceptable conditions have been remedied and after receipt of written approval to proceed from Departmental Representative.

**3.2 Installation**

- .1 Install stress cones, terminations, and splices in accordance with manufacturer's instructions.
- .2 Bond and ground as required to CSA C22.2 No.41.

**3.3 Cleaning**

- .1 Progress Cleaning: clean in accordance with Section 01 74 11 - Cleaning.
  - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 11 - Cleaning.

**END OF SECTION**

**Part 1            General**

**1.1            Related Requirements**

- .1        This Section covers items common to Sections of Divisions 26 and 28. These Sections supplement requirements of Division 1.

**1.2            References**

- .1        American National Standards Institute /Institute of Electrical and Electronics Engineers (ANSI/IEEE)
  - .1        ANSI/IEEE 837-02, IEEE Standard for Qualifying Permanent Connections Used in Substation Grounding.

**1.3            Action And Informational Submittals**

- .1        Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2        Product Data:
  - .1        Submit manufacturer's instructions, printed product literature and data sheets for grounding equipment and include product characteristics, performance criteria, physical size, finish and limitations.

**1.4            Closeout Submittals**

- .1        Submit in accordance with Section 01 78 00 - Closeout Submittals.
- .2        Operation and Maintenance Data: submit operation and maintenance data for grounding equipment for incorporation into manual.

**1.5            Delivery, Storage And Handling**

- .1        Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements and with manufacturer's written instructions.
- .2        Delivery and Acceptance Requirements: deliver materials to site in original factory packaging, labelled with manufacturer's name and address.
- .3        Storage and Handling Requirements:
  - .1        Store materials off ground, indoors, in dry location and in accordance with manufacturer's recommendations in clean, dry, well-ventilated area.
  - .2        Store and protect grounding equipment from nicks, scratches, and blemishes.
  - .3        Replace defective or damaged materials with new.

**Part 2           Products**

**2.1            Equipment**

- .1        Clamps for grounding of conductor: size as required to electrically conductive underground water pipe.

- .2 Grounding conductors: bare stranded copper, soft annealed, size as indicated.
- .3 Insulated grounding conductors: green, copper conductors, size as indicated.
- .4 Ground bus: copper, size as indicated, complete with insulated supports, fastenings, connectors.
- .5 Non-corroding accessories necessary for grounding system, type, size, material as indicated, including but not necessarily limited to:
  - .1 Grounding and bonding bushings.
  - .2 Protective type clamps.
  - .3 Bolted type conductor connectors.
  - .4 Bonding jumpers, straps.
  - .5 Pressure wire connectors.

### **Part 3 Execution**

#### **3.1 Examination**

- .1 Verification of Conditions: verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for grounding equipment installation in accordance with manufacturer's written instructions.
  - .1 Visually inspect substrate in presence of Departmental Representative.
  - .2 Inform Departmental Representative of unacceptable conditions immediately upon discovery.
  - .3 Proceed with installation only after unacceptable conditions have been remedied and after receipt of written approval to proceed from Departmental Representative.

#### **3.2 Installation General**

- .1 Install complete permanent, continuous grounding system including, conductors, connectors, accessories. Where EMT is used, run ground wire in conduit.
- .2 Install connectors in accordance with manufacturer's instructions.
- .3 Protect exposed grounding conductors from mechanical injury.
- .4 Use mechanical connectors for grounding connections to equipment provided with lugs.
- .5 Soldered joints not permitted.
- .6 Install bonding wire for flexible conduit, connected at both ends to grounding bushing, solderless lug, clamp or cup washer and screw. Neatly cleat bonding wire to exterior of flexible conduit.
- .7 Install flexible ground straps for bus duct enclosure joints, where such bonding is not inherently provided with equipment.
- .8 Install separate ground conductor to outdoor lighting standards.
- .9 Bond single conductor, metallic armoured cables to cabinet at supply end, and provide non-metallic entry plate at load end.

- .10 Ground secondary service pedestals.

### **3.3 Equipment Grounding**

- .1 Install grounding connections to typical equipment included in, but not necessarily limited to following list. Service equipment, frames of motors, starters, control panels, cable trays.

### **3.4 Field Quality Control**

- .1 Perform tests in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Perform ground continuity and resistance tests using method appropriate to site conditions and to approval of Departmental Representative and local authority having jurisdiction over installation.
- .3 Perform tests before energizing electrical system.
- .4 Disconnect ground fault indicator during tests.

### **3.5 Cleaning**

- .1 Progress Cleaning: clean in accordance with Section 01 74 11 - Cleaning.
  - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 11 - Cleaning.

**END OF SECTION**

**Part 1            General**

**1.1            Related Requirements**

- .1        This Section covers items common to Sections of Divisions 26 and 28. These Sections supplement requirements of Division 1.

**1.2            References**

**1.3            Action And Informational Submittals**

- .1        Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2        Product Data:
  - .1        Submit manufacturer's instructions, printed product literature and data sheets for hangers and supports and include product characteristics, performance criteria, physical size, finish and limitations.

**1.4            Delivery, Storage And Handling**

- .1        Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements and with manufacturer's written instructions.
- .2        Delivery and Acceptance Requirements: deliver materials to site in original factory packaging, labelled with manufacturer's name and address.
- .3        Storage and Handling Requirements:
  - .1        Store materials off ground, indoors, in dry location and in accordance with manufacturer's recommendations in clean, dry, well-ventilated area.
  - .2        Store and protect hangers and supports from nicks, scratches, and blemishes.
  - .3        Replace defective or damaged materials with new.

**Part 2           Products**

**2.1           Support Channels**

- .1        U shape, size 41 x 41 mm, 2.5 mm thick, suspended.

**Part 3           Execution**

**3.1           Examination**

- .1        Verification of Conditions: verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for hangers and supports installation in accordance with manufacturer's written instructions.
  - .1        Visually inspect substrate in presence of Departmental Representative.
  - .2        Inform Departmental Representative of unacceptable conditions immediately upon discovery.

- .3 Proceed with installation only after unacceptable conditions have been remedied and after receipt of written approval to proceed from Departmental Representative.

### **3.2 Installation**

- .1 Secure equipment to solid masonry, tile and plaster surfaces with lead anchors.
- .2 Secure equipment to poured concrete with expandable inserts.
- .3 Secure equipment to hollow masonry walls or suspended ceilings with toggle bolts.
- .4 Secure surface mounted equipment with twist clip fasteners to inverted T bar ceilings. Ensure that T bars are adequately supported to carry weight of equipment specified before installation.
- .5 Support equipment, conduit or cables using clips, spring loaded bolts, cable clamps designed as accessories to basic channel members.
- .6 Fasten exposed conduit or cables to building construction or support system using straps.
  - .1 One-hole steel straps to secure surface conduits and cables 50 mm and smaller.
  - .2 Two-hole steel straps for conduits and cables larger than 50 mm.
  - .3 Beam clamps to secure conduit to exposed steel work.
- .7 Suspended support systems.
  - .1 Support individual cable or conduit runs with 6 mm diameter threaded rods and spring clips.
  - .2 Support 2 or more cables or conduits on channels supported by 6 mm diameter threaded rod hangers where direct fastening to building construction is impractical.
- .8 For surface mounting of two or more conduits use channels at 1.5 m on centre spacing.
- .9 Provide metal brackets, frames, hangers, clamps and related types of support structures where indicated or as required to support conduit and cable runs.
- .10 Ensure adequate support for raceways and cables dropped vertically to equipment where there is no wall support.
- .11 Do not use wire lashing or perforated strap to support or secure raceways or cables.
- .12 Do not use supports or equipment installed for other trades for conduit or cable support except with permission of other trade and approval of Departmental Representative.
- .13 Install fastenings and supports as required for each type of equipment cables and conduits, and in accordance with manufacturer's installation recommendations.

### **3.3 Cleaning**

- .1 Progress Cleaning: clean in accordance with Section 01 74 11 - Cleaning.
  - .1 Leave Work area clean at end of each day.

- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 11 - Cleaning.

**END OF SECTION**

**Part 1 General**

**1.1 Related Requirements**

- .1 This Section covers items common to Sections of Divisions 26 and 28. These Sections supplement requirements of Division 1.

**1.2 References**

- .1 Canadian Standards Association (CSA International)
  - .1 CSA C22.1-15, Canadian Electrical Code, Part 1, 23rd Edition.

**1.3 Action And Informational Submittals**

- .1 Provide submittals in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Submit samples for floor box in accordance with Section 01 33 00 - Submittal Procedures.

**1.4 Delivery, Storage And Handling**

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements.

**Part 2 Products**

**2.1 Outlet And Conduit Boxes General**

- .1 Size boxes in accordance with CSA C22.1.
- .2 102 mm square or larger outlet boxes as required.
- .3 Gang boxes where wiring devices are grouped.
- .4 Blank cover plates for boxes without wiring devices.
- .5 Combination boxes with barriers where outlets for more than one system are grouped.

**2.2 Galvanized Steel Outlet Boxes**

- .1 One-piece electro-galvanized construction.
- .2 Single gang flush device boxes for flush installation, minimum size 76 x 50 x 38 mm or as indicated. 102 mm square outlet boxes when more than one conduit enters one side with extension and plaster rings as required.
- .3 Utility boxes for outlets connected to surface-mounted EMT conduit, minimum size 102 x 54 x 48 mm.
- .4 102 mm square or octagonal outlet boxes for lighting fixture outlets.

**2.3 Conduit Boxes**

- .1 Cast FS boxes with factory-threaded hubs and mounting feet for surface wiring of devices.

**2.4 Fittings - General**

- .1 Bushing and connectors with nylon insulated throats.
- .2 Knock-out fillers to prevent entry of debris.
- .3 Conduit outlet bodies for conduit up to 35mm and pull boxes for larger conduits.
- .4 Double locknuts and insulated bushings on sheet metal boxes.

**Part 3 Execution**

**3.1 Installation**

- .1 Support boxes independently of connecting conduits.
- .2 Fill boxes with paper, sponges or foam or similar approved material to prevent entry of debris during construction. Remove upon completion of work.
- .3 For flush installations mount outlets flush with finished wall using plaster rings to permit wall finish to come within 6 mm of opening.
- .4 Provide correct size of openings in boxes for conduit, mineral insulated and armoured cable connections. Do not install reducing washers.
- .5 Vacuum clean interior of outlet boxes before installation of wiring devices.
- .6 Identify systems for outlet boxes as required.

**END OF SECTION**

**Part 1 General**

**1.1 Related Requirements**

- .1 This Section covers items common to Sections of Divisions 26 and 28. These Sections supplement requirements of Division 1.

**1.2 References**

- .1 Canadian Standards Association (CSA International)
  - .1 CAN/CSA C22.2 No. 18 latest enforceable edition, Outlet Boxes, Conduit Boxes, Fittings and Associated Hardware, A National Standard of Canada.
  - .2 CSA C22.2 No. 45 latest enforceable edition, Rigid Metal Conduit.
  - .3 CSA C22.2 No. 56-04, Flexible Metal Conduit and Liquid-Tight Flexible Metal Conduit.
  - .4 CSA C22.2 No. 83- latest enforceable edition, Electrical Metallic Tubing.
  - .5 CSA C22.2 No. 211.2- latest enforceable edition, Rigid PVC (Unplasticized) Conduit.
  - .6 CAN/CSA C22.2 No. 227.3- latest enforceable edition, Nonmetallic Mechanical Protection Tubing (NMPT), A National Standard of Canada.

**1.3 Action And Informational Submittals**

- .1 Provide submittals in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product data: submit manufacturer's printed product literature, specifications and datasheets.
  - .1 Submit cable manufacturing data.
- .3 Quality assurance submittals:
  - .1 Test reports: submit certified test reports.
  - .2 Certificates: submit certificates signed by manufacturer certifying that materials comply with specified performance characteristics and physical properties.
  - .3 Instructions: submit manufacturer's installation instructions.

**1.4 Waste Management And Disposal**

- .1 Separate waste materials for reuse in accordance with Section 01 74 21 - Construction/Demolition Waste Management and Disposal.
- .2 Place materials defined as hazardous or toxic waste in designated containers.
- .3 Ensure emptied containers are sealed and stored safely for disposal away from children.

**Part 2 Products**

**2.1 Cables**

- .1 Identify cables for exclusively dc applications.

**2.2 Conduits**

- .1 Rigid metal conduit: to CSA C22.2 No. 45, hot dipped galvanized steel threaded.
- .2 Epoxy coated conduit: to CSA C22.2 No. 45, with zinc coating and corrosion resistant epoxy finish inside and outside.
- .3 Electrical metallic tubing (EMT): to CSA C22.2 No. 83, with couplings.
- .4 Rigid pvc conduit: to CSA C22.2 No. 211.2.

**2.3 Conduit Fastenings**

- .1 One hole steel straps to secure surface conduits 50 mm and smaller.
  - .1 Two hole steel straps for conduits larger than 50 mm.
- .2 Beam clamps to secure conduits to exposed steel work.
- .3 Channel type supports for two or more conduits at 1.5 m on centre.
- .4 Threaded rods, 6 mm diameter, to support suspended channels.
- .5 Stand-offs with gaskets if surface installation.

**2.4 Conduit Fittings**

- .1 Fittings: to CAN/CSA C22.2 No. 18, manufactured for use with conduit specified.  
Coating: same as conduit.
- .2 Ensure factory "ells" where 90 degrees bends for 25 mm and larger conduits.
- .3 Watertight connectors and couplings for EMT.
  - .1 Set-screws are not acceptable.

**2.5 Fish Cord**

- .1 Polypropylene.

**Part 3 Execution**

**3.1 Manufacturer's Instructions**

- .1 Compliance: comply with manufacturer's written recommendations or specifications, including product technical bulletins, handling, storage and installation instructions, and datasheets.

**3.2 Installation**

- .1 Install conduits to conserve headroom in exposed locations and cause minimum interference in spaces through which they pass.

- .2 Conceal conduits except in mechanical and electrical service rooms and in unfinished areas.
- .3 Use rigid hot dipped galvanized steel threaded conduit except where specified otherwise.
- .4 Use electrical metallic tubing (EMT) except in cast concrete.
- .5 Minimum conduit size for lighting and power circuits: 19 mm.
- .6 Bend conduit cold:
  - .1 Replace conduit if kinked or flattened more than 1/10th of its original diameter.
- .7 Mechanically bend steel conduit over 19 mm diameter.
- .8 Field threads on rigid conduit must be of sufficient length to draw conduits up tight.
- .9 Install fish cord in empty conduits.
- .10 Remove and replace blocked conduit sections.
  - .1 Do not use liquids to clean out conduits.
- .11 Dry conduits out before installing wire.

### **3.3 Surface Conduits**

- .1 Run parallel or perpendicular to building lines.
- .2 Locate conduits behind infrared or gas fired heaters with 1.5 m clearance.
- .3 Run conduits in flanged portion of structural steel.
- .4 Group conduits wherever possible on suspended and surface channels.
- .5 Do not pass conduits through structural members except as indicated.
- .6 Do not locate conduits less than 75 mm parallel to steam or hot water lines with minimum of 25 mm at crossovers.

### **3.4 Concealed Conduits**

- .1 Run parallel or perpendicular to building lines.
- .2 Do not install horizontal runs in masonry walls.
- .3 Do not install conduits in terrazzo or concrete toppings.

### **3.5 Conduits In Cast-In-Place Concrete**

- .1 Locate to suit reinforcing steel.
  - .1 Install in centre one third of slab.
- .2 Protect conduits from damage where they stub out of concrete.
- .3 Install sleeves where conduits pass through slab or wall.
- .4 Provide oversized sleeve for conduits passing through waterproof membrane, before membrane is installed.
  - .1 Use cold mastic between sleeve and conduit.

- .5 Conduits in slabs: minimum slab thickness 4 times conduit diameter.
- .6 Encase conduits completely in concrete with minimum 25 mm concrete cover.
- .7 Organize conduits in slab to minimize cross-overs.

### **3.6 Cleaning**

- .1 Proceed in accordance with Section 01 74 11 - Cleaning.
- .2 On completion and verification of performance of installation, remove surplus materials, excess materials, rubbish, tools and equipment.

**END OF SECTION**

**Part 1 General**

**1.1 Related Requirements**

- .1 This Section covers items common to Sections of Divisions 26 and 28. These Sections supplement requirements of Division 1.

**1.2 References**

- .1 CSA International
  - .1 CSA C22.2 No.42-10, General Use Receptacles, Attachment Plugs and Similar Devices.
  - .2 CAN/CSA C22.2 No.42.1-00, Cover Plates for Flush-Mounted Wiring Devices (Bi-national standard, with UL 514D).
  - .3 CSA C22.2 No.55, Special Use Switches.
  - .4 CSA C22.2 No.111-10, General-Use Snap Switches (Bi-national standard, with UL 20).

**1.3 Action And Informational Submittals**

- .1 Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
  - .1 Submit manufacturer's instructions, printed product literature and data sheets for wiring devices and include product characteristics, performance criteria, physical size, finish and limitations.

**1.4 Closeout Submittals**

- .1 Submit in accordance with Section 01 78 00 - Closeout Submittals.
- .2 Operation and Maintenance Data: submit operation and maintenance data for wiring devices for incorporation into manual.

**1.5 Delivery, Storage And Handling**

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements and with manufacturer's written instructions.
- .2 Delivery and Acceptance Requirements: deliver materials to site in original factory packaging, labelled with manufacturer's name and address.
- .3 Storage and Handling Requirements:
  - .1 Store materials off ground, indoors, in dry location and in accordance with manufacturer's recommendations in clean, dry, well-ventilated area.
  - .2 Store and protect wiring devices from nicks, scratches, and blemishes.
  - .3 Replace defective or damaged materials with new.

**Part 2 Products**

**2.1 Cover Plates**

- .1 Weatherproof Cover plates with gasket stamped aluminum.
- .2 Die cast utility box cover for wiring devices installed in recessed-mounted boxes.
- .3 Cast cover plates for wiring devices mounted in surface-mounted FS or FD type conduit boxes.

**2.2 Source Quality Control**

- .1 Cover plates from one manufacturer throughout project.

**Part 3 Execution**

**3.1 Examination**

- .1 Verification of Conditions: verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for wiring devices installation in accordance with manufacturer's written instructions.
  - .1 Visually inspect substrate in presence of Departmental Representative.
  - .2 Inform Departmental Representative of unacceptable conditions immediately upon discovery.
  - .3 Proceed with installation only after unacceptable conditions have been remedied and after receipt of written approval to proceed from Departmental Representative.

**3.2 Installation**

- .1 Switches:
  - .1 Install single throw gasketted waterproof switches with handle in "UP" position when switch closed.
  - .2 Mount waterproof gasketted switches at height in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Cover plates:
  - .1 Install suitable waterproof gasketted cover plates.
  - .2 Do not use cover plates meant for flush outlet boxes on surface-mounted boxes.

**3.3 Cleaning**

- .1 Progress Cleaning: clean in accordance with Section 01 74 11 - Cleaning.
  - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 11 - Cleaning.

**3.4 Protection**

- .1 Protect installed products and components from damage during construction.
- .2 Protect stainless steel cover plate finish with paper or plastic film until painting and other work is finished.
- .3 Repair damage to adjacent materials caused by wiring device installation.

**END OF SECTION**

.1 General

**1.2 Related Requirements**

- .1 This Section covers items common to Sections of Divisions 26 and 28. These Sections supplement requirements of Division 1.

**1.3 References**

- .1 American National Standards Institute (ANSI)
- .1 ANSI C82.1-04, Lamp Ballasts-Line Frequency Fluorescent Lamp Ballast.
- .2 American National Standards Institute/Institute of Electrical and Electronics Engineers (ANSI/IEEE)
- .1 ANSI/IEEE C62.41-latest enforceable edition, Recommended Practice for Surge Voltages in Low-Voltage AC Power Circuits.
- .3 ASTM International Inc.
- .1 ASTM F1137-00 latest enforceable edition, Standard Specification for Phosphate/Oil and Phosphate/Organic Corrosion Protective Coatings for Fasteners.
- .4 Canadian Standards Association (CSA International)
- .5 ICES-005-latest enforceable edition Radio Frequency Lighting Devices.
- .6 Underwriters' Laboratories of Canada (ULC)

**1.4 Action And Informational Submittals**

- .1 Provide submittals in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
- .1 Provide manufacturer's printed product literature, specifications and datasheet and include product characteristics, performance criteria, physical size, finish and limitations.
- .2 Provide complete photometric data prepared by independent testing laboratory for luminaires where specified, for approval by Departmental Representative.
- .3 Photometric data to include: spacing criterion.
- .3 Quality assurance submittals: provide following in accordance with Section 01 45 00 - Quality Control.
- .1 Manufacturer's instructions: provide manufacturer's written installation instructions and special handling criteria, installation sequence, cleaning procedures.

**1.5 Quality Assurance**

- .1 Provide mock-ups in accordance with Section 01 45 00 - Quality Control.

**1.6 Delivery, Storage And Handling**

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements.
- .2 Deliver materials to site in original factory packaging, labelled with manufacturer's name, address.

**Part 2 Products**

**2.1 Drivers**

- .1 LED Drivers
- .2 Reliable and consistent operation
- .3 High efficiency >90%
- .4 Greater than 0.9 PF and Less than 20% THD
- .5 Greater than 50,000 hrs life time
- .6 5-year limited warranty
- .7 ROHS compliance
- .8 Safety approbations (UL, CSA, CE, ENEC, PSE, SELV or CQC)
- .9 Dimmable and Programmable.
- .10 Designed to meet the needs of LED lighting
- .11 Available in either dedicated input voltage or Intellivolt options
- .12 The Adjustable Output Current (AOC) feature
- .13 Specific dimmable versions to enable use of lighting controls to help increase energy saving through a wide variety of protocols, such as 0-10V

**2.2 Finishes**

- .1 Light fixture finish and construction to meet ULC listings and CSA certifications related to intended installation.

**2.3 Optical Control Devices**

- .1 As indicated in luminaire schedule.

**2.4 Luminaires**

- .1 As indicated in luminaire schedule.

**Part 3 Execution**

**3.1 Installation**

- .1 Locate and install luminaires as indicated.
- .2 Provide adequate support to suit ceiling system.

**3.2 Wiring**

- .1 Connect luminaires to lighting circuits:
  - .1 Install flexible or rigid conduit for luminaires as indicated.

**3.3 Luminaire Supports**

- .1 For suspended ceiling installations support luminaires independently of ceiling, support luminaires from ceiling grid in accordance with local inspection requirements.

**3.4 Luminaire Alignment**

- .1 Align luminaires mounted in continuous rows to form straight uninterrupted line.
- .2 Align luminaires mounted individually parallel or perpendicular to building grid lines.

**3.5 Cleaning**

- .1 Clean in accordance with Section 01 74 11 - Cleaning.
  - .1 Remove surplus materials, excess materials, rubbish, tools and equipment.

**END OF SECTION**

**Part 1            General**

**1.1            Related Requirements**

- .1       This Section covers items common to Sections of Divisions 26 and 28. These Sections supplement requirements of Division 1.

**1.2            References**

- .1       CSA International
  - .1       CSA C22.2 No. 5-09 latest enforceable edition, Molded-Case Circuit Breakers, Molded-Case Switches and Circuit-Breaker Enclosures (Tri-national standard with UL 489, and NMX-J-266-ANCE-2010).

**1.3            Action And Informational Submittals**

- .1       Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2       Product Data:
  - .1       Submit manufacturer's instructions, printed product literature and data sheets for circuit breakers and include product characteristics, performance criteria, physical size, finish and limitations.
- .3       Include time-current characteristic curves for breakers with interrupting capacity of 22,000 A symmetrical (rms) and over at system voltage.
- .4       Certificates:
  - .1       Prior to installation of circuit breakers in either new or existing installation, Contractor must submit 3 copies of a production certificate of origin from the manufacturer. Production certificate of origin must be duly signed by factory and local manufacturer's representative certifying that circuit breakers come from this manufacturer and are new and meet standards and regulations.
    - .1       Production certificate of origin must be submitted to Departmental Representative for approval.
  - .2       Delay in submitting production of certificate of origin will not justify any extension of contract and additional compensation.
  - .3       Any work of manufacturing, assembly or installation to begin only after acceptance of production certificate of origin by Departmental Representative. Unless complying with this requirement, Departmental Representative reserves the right to mandate manufacturer listed on circuit breakers to authenticate new circuit breakers under the contract, and to Contractor's expense.
  - .4       Production certificate of origin must contain:
    - .1       Manufacturer's name and address and person responsible for authentication. Person responsible must sign and date certificate.
    - .2       Licensed dealer's name and address and person of distributor responsible for Contractor's account.
    - .3       Contractor's name and address and person responsible for project.

- .4 Local manufacturer's representative name and address. Local manufacturer's representative must sign and date certificate.
- .5 Name and address of building where circuit breakers will be installed:
  - .1 Project title: Bariatric Shower Renovations.

#### **1.4 Delivery, Storage And Handling**

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements and with manufacturer's written instructions.
- .2 Delivery and Acceptance Requirements: deliver materials to site in original factory packaging, labelled with manufacturer's name and address.
- .3 Storage and Handling Requirements:
  - .1 Store circuit breakers off ground, indoors, in dry location and in accordance with manufacturer's recommendations in clean, dry, well-ventilated area.
  - .2 Store and protect circuit breakers from nicks, scratches, and blemishes.
  - .3 Replace defective or damaged materials with new.

### **Part 2 Products**

#### **2.1 Breakers General**

- .1 Moulded-case circuit breakers: to CSA C22.2 No. 5
- .2 Bolt-on moulded case circuit breaker: quick- make, quick-break type, for manual and automatic operation with temperature compensation for 40 degrees C ambient.
- .3 Common-trip breakers: with single handle for multi-pole applications.
- .4 Magnetic instantaneous trip elements in circuit breakers to operate only when value of current reaches setting.
  - .1 Trip settings on breakers with adjustable trips to range from 3-8 times current rating.
- .5 Circuit breakers with interchangeable trips as indicated.
- .6 Circuit breakers to have minimum 22kA symmetrical rms interrupting capacity rating.

#### **2.2 Thermal Magnetic Breakers**

- .1 Moulded case circuit breaker to operate automatically by means of thermal and magnetic tripping devices to provide inverse time current tripping and instantaneous tripping for short circuit protection.

### **Part 3 Execution**

#### **3.1 Examination**

- .1 Verification of Conditions: verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for installation in accordance with manufacturer's written instructions.

- .1 Visually inspect substrate in presence of Departmental Representative.
- .2 Inform Departmental Representative of unacceptable conditions immediately upon discovery.
- .3 Proceed with installation only after unacceptable conditions have been remedied and after receipt of written approval to proceed from Departmental Representative.

### **3.2 Installation**

- .1 Install circuit breakers as indicated.

### **3.3 Cleaning**

- .1 Progress Cleaning: clean in accordance with Section 01 74 11 - Cleaning.
  - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 11 - Cleaning.

**END OF SECTION**