

PART 1 - GENERAL

1.1 RELATED REQUIREMENTS

- .1 Section 26 05 00 – Common Works Results - Electrical

1.2 REFERENCE STANDARDS

- .1 CSA International
 - .1 CAN/CSA-C22.2 No.18 (Latest Edition), Outlet Boxes, Conduit Boxes and Fittings.
 - .2 CAN/CSA-C22.2 No.65 (Latest Edition), Wire Connectors (Tri-National Standard with UL 486A-486B and NMX-J-543-ANCE-03).
- .2 Electrical and Electronic Manufacturers' Association of Canada (EEMAC)
 - .1 EEMAC 1Y-2 (Latest Edition), Bushing Stud Connectors and Aluminum Adapters (1200 Ampere Maximum Rating).
- .3 National Electrical Manufacturers Association (NEMA)

PART 2 - PRODUCTS

2.1 MATERIALS

- .1 Pressure type wire connectors to: CAN/CSA-C22.2 No.65, with current carrying parts of copper sized to fit copper conductors as required.
- .2 Fixture type splicing connectors to: CAN/CSA-C22.2 No.65, with current carrying parts of copper sized to fit copper conductors 10 AWG or less.
- .3 Bushing stud connectors: to EEMAC 1Y-2 to consist of:
 - .1 Connector body and stud clamp for stranded copper conductors.
 - .2 Clamp for copper bar.
 - .3 Stud clamp bolts.
 - .4 Bolts for copper bar.
 - .5 Sized for conductors and bars as indicated.
- .4 Clamps or connectors for armoured cable, aluminum sheathed cable, flexible conduit, non-metallic sheathed cable as required to: CAN/CSA-C22.2 No.18.

PART 3 - EXECUTION

3.1 INSTALLATION

- .1 Remove insulation carefully from ends of conductors and:
 - .1 Install mechanical pressure type connectors and tighten screws with appropriate compression tool recommended by manufacturer. Installation shall meet secureness tests in accordance with CAN/CSA-C22.2 No.65.
 - .2 Install fixture type connectors and tighten. Replace insulating cap.
 - .3 Install bushing stud connectors in accordance with EEMAC 1Y-2.

END OF SECTION