


Part 1 General

1.1 THIS SECTION COVERS ITEMS COMMON TO SECTIONS OF DIVISION 26. THIS SECTION SUPPLEMENTS REQUIREMENTS OF DIVISION 01.

1.2 DESCRIPTION OF WORK



Work to be completed under this Contract includes the following:

- .1 Remove old service and all electrical equipment off the wharf 401 and 402 and right side approach to Wharf 401.
- .2 Extend existing underground services from utility pole P2 to new service entrance and Panel 'A' enclosure that is raised up 1.0 meter.
- .3 Reinstall and re-arrange existing feeder from Panel 'A' to Panel 'B'.
- .4 Provide under wharf 401 and in new concrete deck 402 conduit and wire & cabletray c/w brackets. Also reroute and reconnect conduits and wires from Wharfs 403 and 404 to Panel 'B'. Complete minor work on wharfs 403 and 404 as indicated on drawings.
- .5 Provide four (4) power centers c/w electrical equipment and power to three (3) Derrick's and conduit in new deck to future power centers and Derrick.
- .6 Provide three (3) new poles, lights, wire and conduit and lighting controls.
- .7 Provide underground and above ground wire and conduit, receptacles and power to oil building on right approach to wharf and wood wharf.
- .8 Provide electrical testing, commissioning, as-built drawings and O&M manuals.

1.3 CODES AND STANDARDS

- .1 Do complete installation in accordance with CSA C22.1 except where specified otherwise.
- .2 Comply with CSA Certification Standards and Electrical Bulletins in force at time of tender submission.
- .3 Do overhead and underground systems in accordance with CSA C22.3 No. 1M except where specified otherwise.
- .4 Abbreviations for electrical terms: to CSA Z85.

1.4 CARE, OPERATION AND START-UP

- .1 Instruct Departmental Representative and operating personnel in the operation, care and maintenance of equipment.
- .2 Arrange and pay for services of manufacturer's factory service Departmental Representative to supervise start-up of installation, check, adjust, balance and calibrate components.
- .3 Provide these services for such period, and for as many visits as necessary to put equipment in operation, and ensure that operating personnel are conversant with all aspects of its care and operation.

1.5 VOLTAGE RATINGS

- .1 Operating voltages: to CAN3-C235-83.
- .2 Motors, electric heating, control and distribution devices and equipment to operate satisfactorily at 60 Hz within normal operating limits established by above standards. Equipment to operate in extreme operating conditions established in above standard without damage to equipment.

1.6 PERMITS, FEES AND INSPECTIONS

- .1 Submit to Electrical Inspection Department and Supply Authority necessary number of drawings and specifications for examination and approval prior to commencement of work.
- .2 Pay associated fees.
- .3 Departmental Representative will provide drawings and specifications required by Electrical Inspection - Department and Supply Authority at no cost.
- .4 Notify Departmental Representative of changes required by Electrical Inspection Department prior to making changes.

1.7 MATERIALS AND EQUIPMENT

- .1 Provide materials and equipment in accordance with Division 01.
- .2 Equipment and material to be CSA certified. Where there is no alternative to supplying equipment which is not CSA certified, obtain special approval from Electrical Inspection Department.
- .3 Factory assembly control panels and component assemblies.

1.8 ELECTRIC MOTORS EQUIPMENT AND CONTROLS

- .1 Supplier, installer & wiring responsibility is indicated on electrical drawings.
- .2 Coordinate final connection to all equipment and controls.

1.9 FINISHES

- .1 Shop finish metal enclosure surfaces by application of rust resistant primer inside and outside, and at least two coats of finish enamel.
 - .1 Paint outdoor electrical equipment "equipment green" finish to EEMAC Y1-1.
 - .2 Paint indoor switchgear and distribution enclosures light grey to EEMAC 2Y-1.
- .2 Clean and touch up surfaces on shop-painted electrical equipment scratched or marred during shipment or installation, to match original paint.
- .3 Clean, prime and paint exposed painted non-galvanized hangers, racks and fastenings to prevent rusting.

1.10 EQUIPMENT IDENTIFICATION

- .1 Identify electrical equipment with nameplates as follows:
 - .2 Nameplates:
 - .1 Lamacoid 3mm thick plastic engraving sheet, white face, black core, mechanically attached. Laser etched lamacoids may also be used.
- NAMEPLATE SIZES**
-
- | | | | |
|--------|-------------|---------|--------------------|
| Size 1 | 10 x 50 mm | 1 line | 3 mm high letters |
| Size 2 | 12 x 70 mm | 1 line | 5 mm high letters |
| Size 3 | 12 x 70 mm | 2 lines | 3 mm high letters |
| Size 4 | 20 x 90 mm | 1 line | 8 mm high letters |
| Size 5 | 20 x 90 mm | 2 lines | 5 mm high letters |
| Size 6 | 25 x 100 mm | 1 line | 12 mm high letters |
| Size 7 | 25 x 100 mm | 2 lines | 6 mm high letters |
- .3 Wording on nameplates to be approved by Departmental Representative prior to manufacture.
 - .4 Allow for average of twenty-five (25) letter per nameplate/language.
 - .5 Identification to be English and French.
 - .6 All switchboards, panels, disconnect switches, transformers, control panels, magnetic starters, time clocks, shrouds, light poles, derricks, junction boxes, and receptacles are to be provided with 'lamacoid' nameplates. Nameplates are to be affixed to all metal surfaces with metal type "pop-rivets".

- .7 Nameplates are to be affixed to other surfaces with contact type cement. Contact type cement is to be applied to complete backside of plate, as opposed to several points or locations on same.
- .8 Lamacoids on shrouds to indicate shroud number – SH2. Lamacoid on light pole to indicate pole number and circuit P6 (ccts B-5, B-7). Lamacoids on derricks to indicate derrick number and circuit DK4 (ccts B-25, 27). Lamacoid on junction boxes to indicate circuit numbers in box (ccts B-5, B-7). Lamacoids on receptacle boxes to indicate receptacle number and circuit number – R22 (cct B-32).
- .9 Lamacoid nameplates installed on distribution panelboards, motor control centres, splitter troughs, transformers, shall indicate the following:
 - .1 Designated name of equipment;
 - .2 Overcurrent protection device rating;
 - .3 Voltages, number of phases and wires;
 - .4 Designation of power source.

Example:

PANEL N - 150A
120/208V - 3PH - 4W
FED FROM MAIN SWITCHBOARD #CDP-A

- .10 Install an additional 'Lamacoid' nameplate on all, or any piece of electrical equipment, or apparatus, ie. Main Switchboard, CDP panels, panelboards, motor control centres, and fusible switches, etc. that may contain overcurrent devices, i.e. circuit breakers and/or fuses, that have been designed for, and incorporate an interrupting capacity sized "larger" than 10kAIC.

Examples:

Minimum interrupting capacity of breakers installed in this panel is to be not less than 22 kAIC.

Minimum interrupting capacity of fuses installed in this MCC is to be not less than 100 kAIC.

1.11 WIRING IDENTIFICATION

- .1 Identify feeder and branch circuit wiring including neutral conductors at both ends, including in all junction and outlet boxes located in between, with permanent indelible identifying markings, indicating panel and circuit number. (i.e. A1-25).
- .2 Maintain phase sequence and colour coding throughout. (Red, black, blue, white). No colour taping of wires is allowed.

- .3 Colour code: to CSA C22.1.
- .4 Use colour coded wires in communication cables, matched throughout system.

1.12 CONDUIT AND CABLE IDENTIFICATION

- .1 Colour code conduits and metallic sheathed cables.
- .2 Code with plastic tape or paint at points where conduit or cable enters wall or floor, and at 15m intervals.
- .3 Colours to be 25mm wide prime colour and 20mm wide auxiliary colour.

<u>Prime</u>	<u>Auxiliary</u>
up to 250V	yellow
up to 600V	yellow green
Telephone	white

1.13 DEVICE IDENTIFICATION

- .1 All receptacles, light poles, welder/winch and shore power outlets are to have its panel and circuit identified with a lamaroid nameplate. White letters on white background, 6mm high x 25mm long (i.e. A-3 or A-2,4,6). Nameplates to be properly secured to outlet box with screws. Receptacle number, light pole number, shore power and welder/winch number to also be identified (i.e. Recept. #1, Light #1, Shore Power #1, Welder/Winch #1).

1.14 WIRING TERMINATIONS

- .1 Lugs, terminals, screws used for termination of wiring to be suitable for copper conductors.

1.15 MANUFACTURERS AND CSA LABELS

- .1 Visible and legible after equipment is installed.

1.16 WARNING SIGNS

- .1 As specified and to meet requirements of Inspection Department and Departmental Representative.
- .2 Use decal signs, minimum 175 x 250mm size.
- .3 “DANGER HIGH VOLTAGE” signs to be installed on each of the new ES-1 and ES-2 enclosures.

1.17 LOCATION OF OUTLETS

- .1 Change location of outlets at no extra cost or credit, providing distance does not exceed 3.0m, and information is given before installation.
- .2 Locate light switches on latch side of doors.

1.18 MOUNTING HEIGHTS

- .1 Mounting height of equipment is from finished floor to centreline of equipment unless specified or indicated otherwise.
- .2 If mounting height of equipment is not indicated, verify before proceeding with installation.
- .3 Install electrical equipment at the following heights unless indicated otherwise.
 - .1 Receptacles:
 - .1 General: in shrouds.
 - .2 Panelboards: 1500mm or as required by Code.
 - .3 Local Switches: 1250mm
 - .4 Telephone Outlets: 300mm
 - .5 Thermostats: 1250mm
- .4 Generally, masonry outlet boxes are to be installed in bottom of concrete blocks to approximate heights indicated.
- .5 Refer to all detail drawings and confirm mounting of outlet boxes prior to roughing-in.

1.19 LOAD BALANCE

- .1 Measure phase current to panelboards with normal loads (lighting) operating at time of acceptance. Adjust branch circuit connections as required to obtain best balance of current between phases and record changes.
- .2 Measure phase voltages at loads and adjust transformer taps to within 2% of rated voltage of equipment.
- .3 Submit, at completion of work a report listing all phase and neutral currents on panelboards operating under normal load. State hour and date on which each load was measured, and voltage at time of test.

1.20 CONDUIT AND CABLE INSTALLATION

- .1 Install conduit, and sleeves, prior to pouring of concrete. Sleeves through concrete: sheet metal, sized for free passage of conduit, and protruding 50mm.

- .2 Install cables, conduits and fittings to be embedded or plastered over neatly and close to structure so furring can be kept to a minimum.

1.21 FIELD QUALITY CONTROL

- .1 All electrical work to be carried out by qualified, licensed electricians or apprentices as per the conditions of the Provincial Act respecting manpower vocational training and qualification. Employees registered in a provincial apprentices program shall be permitted, under the direct supervision of a qualified licensed electrician, to perform specified tasks – the activities permitted shall be determined based on the level of training attained and the demonstration of ability to perform specified duties. The work of this division to be carried out by a contractor who holds a valid Electrical contractor license as issued by the Province of Nova Scotia.
- .2 Conduct and pay for tests of the following:
 - .1 Power distribution system, including phasing, voltage, grounding and load balancing;
 - .2 Circuits originating from branch distribution panels;
 - .3 Lighting and its control;
 - .4 Motors, heaters and associated control equipment including sequenced operation of systems where applicable;
 - .5 Systems: communications, etc.
- .3 Furnish manufacturer's certificate or letter confirming that entire installation as it pertains to each system has been installed to manufacturer's instructions.
- .4 Insulation resistance testing:
 - .1 Megger circuits, feeders and equipment up to 350V with a 500V instrument.
 - .2 Megger circuits, feeders and equipment between 350V and 600V with a 1000V instrument.
 - .3 Check resistance to ground before energizing.
- .5 Notify Departmental Representative three days in advance, of equipment and system testing and verification. Carry out tests in presence of Departmental Representative.
- .6 Provide instruments, meters, equipment and personnel required to conduct tests during and at conclusion of project.
- .7 Submit test results for Departmental Representative's review.

1.22 COORDINATION OF PROTECTIVE DEVICES

- .1 Ensure circuit protective devices such as overcurrent relays, and fuses, are installed to values and settings as indicated.

1.23 AS-BUILTS DOCUMENTS

- .1 At completion of project and prior to final inspection, the electrical contractor, at his own expense, shall mark all changes in red on blueprint record drawings and submit the as-built sets to Departmental Representative.

1.24 SHOP DRAWINGS, PRODUCT DATA & SAMPLES

- .1 Submit shop drawings, product data and samples in accordance with Division 01 30 00.
- .2 Indicate details of construction, dimensions, capacities, weights and electrical performance characteristics of equipment or material.
- .3 Where applicable, include wiring, single line and schematic diagrams.
- .4 Include wiring drawings or diagrams showing interconnection with work of other Sections.

1.25 OPERATION AND MAINTENANCE DATA

- .1 Provide operation and maintenance data for electrical work for incorporation into maintenance manual.
- .2 Include in operations and maintenance data:
 - .1 Details with respect to design elements, construction features, component function and maintenance requirements, to permit effective start-up, operation, maintenance, repair, modification, extension and expansion of any portion or feature of installation.
 - .2 Technical data, product data, supplemented by bulletins, component illustrations, exploded views, technical descriptions of items and parts lists. Advertising or sales literature not acceptable.
 - .3 Wiring and schematic diagrams and performance curves.
 - .4 Names and addresses of local suppliers for all items included in maintenance manual.

1.26 MAINTENANCE MATERIALS

- .1 Provide maintenance materials in accordance with Division 01.

1.27 PROTECTION

- .1 Protect exposed live equipment during construction for personnel safety.
- .2 Shield and mark all live parts "LIVE 120 VOLTS" or with appropriate voltage in English & French.

1.28 CLEANING

- .1 At time of final cleaning, clean lighting reflectors, lenses and other lighting surfaces that have been exposed to construction dust, dirt and fingerprints.

1.29 COORDINATION WITH OTHER TRADES

- .1 The Electrical Contractor shall totally review all architectural, structural and mechanical drawings and specifications to coordinate and determine work associated with electrical work prior to submitting tender price. Also, review all Addendums associated with all trades.
- .2 After review of all documents associated with other trades, forward any questions and obtain answers by Addendum, prior to tender submission.
- .3 Submission of tender by Electrical Contractor acknowledges coordination with other trades as part of these contract documents

1.30 PROJECT WASTE MANAGEMENT

- .1 Contractor must adhere to project waste management guidelines.

1.31 PROJECT RECORD DOCUMENTS

- .1 Provide Project Record Documents to Division 01.

1.32 SCHEDULE

- .1 Overtime work and work outside normal work hours as deemed necessary to accomplish scheduling are the responsibility of the contractor and must meet the requirements of the Department of Labour. All costs resulting from such overtime must be included in the contractor's estimated total tender price.

1.33 COORDINATION OF EXISTING AND NEW

- .1 In order to install new services while maintaining existing, coordination between old and new must be provided. This may restrict installation of new services and how the work is carried out.
- .2 All costs for this coordination must be included in the total tendered price.

1.34 MEASUREMENT FOR PAYMENT

- .1 Measurement for payment for Division 26 is lump sum.

1.35 SINGLE LINE ELECTRICAL DIAGRAMS

- .1 Provide single line electrical diagrams in metal frames with clear polycarbonate glazing as follows:
 - .1 Electrical distribution systems: locate in main electrical room.
- .2 Drawings: 600 x 600mm minimum size.

1.36 SITE EXAMINATION

- .1 Electrical Contractor to refer and conform to General Instruction Section 01 10 10.15.

END OF SECTION

Part 1 General

1.1 DESCRIPTION OF SYSTEM

- .1 In general, work of this Section consists of the complete removal of all existing electrical equipment and materials on the wharf to be renovated.

1.2 RELATED WORK

- .1 Electrical General Provisions: Section 26 05 00.
- .2 Wharf Removals.

1.4 REFERENCE STANDARDS

- .1 All removal or modification work of electrical construction to be done in accordance with the safety standards outlined in the Canadian Electrical Code.

1.5 PROTECTION

- .1 Be responsible for any damages to existing structure as a result of the work.

1.6 SALVAGE MATERIAL

- .1 Materials and equipment identified on the drawing as being reused are to be taken down, stored, reinstalled, etc. as required to allow for new construction.
- .2 Contractor must identify any damaged equipment or materials intended for reuse prior to demolition and point out deficiencies to the Departmental Representative at that time.

1.7 DISPOSAL

- .1 Prior to demolition Departmental Representative will identify any items of electrical equipment which are to be set aside as directed for future use by Owner.
- .2 All other materials and equipment removed under work of this Section becomes the property of the Contractor for disposal off of property.
- .3 Comply with all municipal, provincial and federal bylaws and standards when disposing of waste.

1.8 SCHEDULE

- .1 The Contractor is to note that the Departmental Representative intends to carry on business as usual and work activities must be coordinated to maintain electrical services in occupied areas. Provide any required temporary work.
- .2 Overtime work and work outside normal work hours as deemed necessary to accomplish this scheduling are the responsibility of the Contractor and must meet the requirements of the Department of Labour. All costs resulting from such overtime must be included in the Contractor's Estimated Total Tender Price.
- .3 Coordinate with NSPI to remove all equipment, poles, lines, services, etc. from the site.

Part 2 Products

Not applicable.

Part 3 Execution

3.1 GENERAL REMOVALS

- .1 Remove all existing electrical services including exposed wire and conduit, except those designated for reuse.
- .2 Remove electrical services associated with existing systems.
- .3 Coordinate work of this Section with other trades.
- .4 Schedule all removal work with the Departmental Representative. Do not disrupt operations except as permitted by the Schedule.

3.2 CUTTING

- .1 Cutting required for removals and alterations to be to the approval of the Departmental Representative and performed with appropriate power tools.

3.3 CLEANING

- .1 Reused existing equipment to be cleaned in accordance with 26 05 00.

END OF SECTION

Part 1 General

Not applicable.

Part 2 Products**2.1 MATERIALS**

- .1 Pressure-type wire connectors: with current-carrying parts of copper sized to fit copper conductors as required. Use twist-on connectors for #14 and smaller.
- .2 In-line insulated compression connectors for #12 conductors and larger.
- .3 Bushing stud connectors: to EEMAC 1Y-2 to consist of:
 - .1 Connector body and stud clamp for stranded round copper conductors;
 - .2 Clamp for stranded round copper conductors;
 - .3 Stud clamp bolts;
 - .4 Bolts for copper conductors;
 - .5 Sized for conductors as indicated.
- .4 Steel clamps or connectors for flexible conduit, as required.
- .5 Crimp style wire connectors, nylon insulated, with current carrying parts of copper alloy, for conductors #16 and smaller.
- .6 Fork tongue, nylon insulated, crimp style terminals for connecting conductors #16 and smaller to screw down terminals.
- .7 Crimp style wire connectors, nylon insulated with current carrying parts of copper alloy, for connecting solid to stranded conductors.
- .8 Heavy wall shrinkable tubing with 600V insulation: 3M "Cold Shrink Splice" or approved equal.
- .9 Use in-line insulated compression connectors for splices in panelboards to reduce from oversize conductors (due to voltage drop) to smaller conductors that will fit on circuit breakers.

Part 3 Execution**3.1 INSTALLATION**

- .1 Remove insulation carefully from ends of conductors and:
 - .1 Install mechanical pressure type connectors and tighten. Installation shall meet secureness tests in accordance with CSA C22.2 No. 65.
 - .2 Install fixture type connectors and tighten.
 - .3 Install bushing stud connectors in accordance with EEMAC 1Y-2.

3.2 RESTRICTION

- .1 No splices are allowed in underground cables or panelboards (distribution, lighting and power) or in equipment enclosures, unless indicated otherwise.

END OF SECTION

Part 1 General**1.1 PRODUCT DATA**

- .1 Submit product data in accordance with Section 26 05 00.

Part 2 Products**2.1 BUILDING WIRES**

- .1 Conductors: minimum size 12 AWG (solid) for power and lighting; stranded for size 8 AWG and larger except as noted.
- .2 Copper conductors sized as indicated with 600V insulation of chemically cross-linked thermosetting polyethylene material rated RW90 for all work.

2.2 TECK CABLE

- .1 Conductors:
 - .1 Grounding conductor: copper
 - .2 Circuit conductors: copper size as indicated.
- .2 Insulation:
 - .1 Chemically cross-linked thermosetting polyethylene rated type RW90 1000V.
- .3 Inner jacket: polyvinyl chloride material.
- .4 Armour: flat interlocking aluminium.
- .5 Overall covering: thermoplastic polyvinyl chloride material, FT4 rated.
- .6 Fastenings:
 - .1 One-hole steel straps to secure surface cables 50mm and smaller. Two-hole steel straps for cables larger than 50mm.
- .7 Connectors:
 - .1 Watertight, approved for TECK cable.
- .8 Splices:
 - .1 Where feeders and branch circuits are required to be lengthened, butt compression splices are to be used utilizing cold shrink quick splice low voltage kits and shear bolt crimp connectors.
 - .2 Splice kits to be 3M Cat. #QSLV-M Series and shear bolt crimp connector to be 3M Cat. #QCI Series or other approved manufacturer or approved equal.

2.3 FIXTURE WIRING

- .1 Temperature rating of fixture wiring entering ballast compartment of fixtures to meet manufacturer's recommendations.
 - .1 For 90°C, use R90
 - .2 For 105°C, use TEW
 - .3 For 125°C, use GTF

2.4 COLOUR CODING

- .1 All conductors to be colour coded in accordance with Section 26 05 00.1.11.

Part 3 Execution**3.1 INSTALLATION OF BUILDING WIRES**

- .1 Install wiring as follows:
 - .1 In conduit systems in accordance with Section 26 05 34.
 - .2 In underground ducts in accordance with Section 26 05 44.
 - .3 In trenches in accordance with Section 26 05 41.
 - .4 In surface and lighting fixture raceways in accordance with Section 26 50 00.
 - .5 In wireways and auxiliary gutters in accordance with Section 26 50 00.

3.2 INSTALLATION OF TECK CABLE 0 – 1000V

- .1 Install cables as indicated.
- .2 Group cables wherever possible on channels.
- .3 Install cables in trenches in accordance with Section 26 05 41.
- .4 Terminate cables in accordance with Section 26 05 20.

3.3 WIRE & CONDUIT METHODS

- .1 Use standard building wire and PVC conduits or TECK cables for all branch circuits.
- .2 All wire shall be #12 minimum from panel.

3.4 SITE LIGHTING

- .1 Install conductors on light poles in PVC conduit from wharf deck to junction box at base and then TECK cable to top of pole junction box.

- .2 Fasten on pole using S/S clamps every 300mm.
- .3 Install conductors from junction box to luminaire as indicated. Use appropriate connectors and secure in place.

3.5 INSTALLATION OF FIXTURE WIRE

- .1 Fixture wire to be installed to ballast compartment unless indicated otherwise where required for temperature rating.

END OF SECTION

Part 1 General

1.1 STANDARDS

- .1 All grounding and bonding requirements shall be in accordance with the Canadian Electrical Code, Part 1.

Part 2 Products

2.1 EQUIPMENT

- .1 Rod electrodes, copper clad steel 19 mm dia. by 3.0m long.
- .2 Plate electrodes for grounding locations on harbour bottom.
- .3 System and circuit, equipment, grounding conductors, bare stranded copper, untinned, soft annealed, size as indicated.
- .4 Insulated grounding conductors: green, to Section 26 05 21.
- .5 Non-corroding accessories necessary for grounding system, type, size, material as indicated, including but not necessarily limited to:
 - .1 Grounding and bonding bushings
 - .2 Protective type clamps
 - .3 Bolted type conductor connectors
 - .4 Thermit welded type conductor connectors
 - .5 Bonding jumpers, straps
 - .6 Pressure wire connectors
- .6 Clamps for grounding of conductor, size as required to electrically conductive underground water pipe.

Part 3 Execution

3.1 INSTALLATION GENERAL

- .1 Install complete permanent, continuous, system and circuit, equipment, grounding systems including electrodes, conductors, connectors, accessories, as indicated, to conform to requirements of Departmental Representative and local authority having jurisdiction over installation.
- .2 Install connectors to manufacturer's instructions.
- .3 Protect exposed grounding conductors from mechanical injury.

- .4 Make buried connections, and connections to conductive water main, electrodes, using copper welding by thermit process.
- .5 Use mechanical connectors for grounding connections to equipment provided with lugs.
- .6 Soldered joints not permitted.
- .7 Install an integral bonding wire in all flexible conduit connected at both ends to grounding bushing, solderless lug, clamp or cup washer and screw.
- .8 Install separate ground conductor, to outdoor lighting standards.
- .9 Connect building structural steel to ground by welding copper to steel.
- .10 Make grounding connections in radial configuration only, with connections terminating at single grounding point. Avoid loop connections.
- .11 Bond single conductor, metallic armoured cables to cabinet at supply end and load end.

3.2 ELECTRODES

- .1 Install ground plate electrodes and make grounding connections as indicated.
- .2 Bond separate, multiple electrodes together.
- .3 Use size #6 AWG copper conductors for connections to electrodes.

3.3 SYSTEM & CIRCUIT GROUNDING

- .1 Install system and circuit grounding connections to neutral of secondary 208V and 600V system.

3.4 EQUIPMENT GROUNDING

- .1 Install grounding connections to typical equipment included in, but not necessarily limited to, the following list: Service equipment, duct systems, control panels, steel work, distribution panels, outdoor lighting.

3.5 FIELD QUALITY CONTROL

- .1 Perform tests in accordance with Section 26 05 00.
- .2 Perform ground continuity and resistance tests using method appropriate to site conditions and to approval of Departmental Representative and local authority having jurisdiction over installation.

- .3 Perform tests before energizing electrical system.

END OF SECTION

Part 1 General

Not applicable.

Part 2 Products**2.1 SUPPORT CHANNELS**

- .1 U shape, size 41 x 41mm, 2.5mm thick, stainless steel, surface mounted, suspended as required.

2.2 CHANNEL FINISH

- .1 All support and fastening devices to be 316 grade stainless steel.

2.3 SPECIFIED PURPOSE SUPPORTS

- .1 Specified purpose stainless, spring steel fasteners, as manufactured by Caddy, B-line or approved equal, for interior support of boxes, conduit and cable from main structures and channels.

Part 3 Execution**3.1 INSTALLATION**

- .1 Secure equipment to poured concrete with expandable inserts.
- .2 Support equipment, conduit or cables using clips, spring loaded bolts, cable clamps designed as accessories to basic channel members.
- .3 Fasten exposed conduit or cables to building construction or support system using straps.
 - .1 One-hole stainless steel straps to secure surface conduits and cables 53mm and smaller.
 - .2 Two-hole stainless steel straps for conduits and cables larger than 53mm.
- .4 Provide stainless steel metal brackets, frames, hangers, clamps and related types of support structures where indicated or as required to support conduit and cable runs.
- .5 Do not use wire lashing or perforated strap to support or secure raceways or cables.
- .6 Do not use supports or equipment installed for other trades for conduit or cable support except with permission of other trades and approval of Departmental Representative.

- .7 Install fastenings and supports as required for each type of equipment cables and conduits, and in accordance with manufacturer's installation recommendation.
- .8 For surface mounting of two or more conduits, use channels at 1.5m oc spacing.
- .9 Ensure adequate support for raceways and cables dropped vertically to equipment where there is no wall support.

END OF SECTION

Part 1 General**1.1 SHOP DRAWINGS & PRODUCT DATA**

- .1 Submit shop drawings and product data for cabinets in accordance with Section 26 05 00.

Part 2 Products**2.1 JUNCTION & PULL BOXES**

- .1 PVC waterproof construction with screw-on overlapping covers, complete with gasket, for surface mounting. Type JB or equivalent. Use stainless steel screws/bolts for mounting.
- .2 Stainless steel type 316 junction box as indicated complete with stainless screws/bolts for mounting.

2.2 ELECTRICAL SHROUDS

- .1 Aluminium shroud 9mm thick with dimensions as detailed on drawing, made from ASTM 6061 salt water rated aluminium with all seams welded on both sides. A 13mm rubber mat (type SBR-60) is to be installed between concrete deck and shroud. Provide 16mm dia. stainless steel adhesive anchors embedded 200mm into drilled holes in the concrete.

2.3 PANEL 'A' & PANEL 'B' ALUMINUM ENCLOSURE

- .1 NEMA Type 4X, 9mm thick ASTM 6061 salt water rated aluminum enclosure with all seams welded on both sides, hinged door and return flange overlapping sides, handle and catch, painted white steel inner panel for surface mounting, complete with heavy-duty padlock and two (2) keys.
- .2 Cabinet to be 2215mm (H) x 1000mm (W) x 305mm (D).

Part 3 Execution**3.1 JUNCTION, PULL BOXES AND CABINETS INSTALLATION**

- .1 Install pull boxes in inconspicuous but accessible locations. Location must be coordinated with other trades.
- .2 Mount cabinets, with top not higher than 610mm above finished floor.
- .3 Size and install cabinets to CEC requirements.

- .4 Only main junction and pull boxes are indicated. Provide pull boxes so as not to exceed 30.0 m of conduit run between pull boxes.

3.2 IDENTIFICATION

- .1 Provide equipment identification in accordance with Section 26 05 00.
- .2 Install size 2 identification labels indicating system name, voltage and phase.

END OF SECTION

Part 1 General**1.1 PRODUCT DATA**

- .1 Submit product data in accordance with Section 26 05 00.

Part 2 Products**2.1 OUTLET & CONDUIT BOXES - GENERAL**

- .1 Size boxes in accordance with CSA C22.1.
- .2 PVC (150 x 150 x 100)mm and (200 x 200 x 100)mm and (300 x 300 x 200)mm outlet boxes, or sized as required, for special devices and requirements.
- .3 Gang boxes where wiring devices are grouped.
- .4 Blank cover plates for boxes without wiring devices.
- .5 Combination boxes with barriers where outlets for more than one system are grouped.

2.2 CONDUIT BOXES

- .1 Cast FS or FD feraloy boxes with factory-threaded hubs and mounting feet for surface wiring of switches and receptacles.
- .2 For 20A TL receptacle, 30A 2P TL receptacle and telephone outlet, use HUBBELL Cat. #HBL60CM83 conduit box. To match existing boxes in Phase 1 work.

2.3 FITTINGS - GENERAL

- .1 PVC bushing and connectors (watertight).
- .2 Knockout fillers to prevent entry of foreign materials or water.
- .3 Conduit outlet bodies for conduit up to 32mm and pull boxes for larger conduits.
- .4 Double locknuts and insulated bushings on sheet metal boxes.
- .5 Set-screw type steel bushings and connectors for EMT fittings unless indicated otherwise. Nylon insulated throats for 25mm conduits and larger.

Part 3 Execution

3.1 INSTALLATION

- .1 Support boxes independently of connecting conduits.
- .2 Fill boxes with paper, sponges or foam or similar approved material to prevent entry of debris during construction. Remove upon completion of work.
- .3 Provide correct size of openings in boxes for conduit and armoured cable connections. Reducing washers not allowed.

END OF SECTION

Part 1 General**1.1 LOCATION OF CONDUIT**

- .1 Drawings do not show all conduits. Those shown are in diagrammatic form only.

Part 2 Products**2.1 CONDUITS**

- .1 Rigid PVC conduit: size as indicated.
- .2 Rigid steel conduit, hot dipped galvanized after fabrication.
- .3 Flexible metal conduit and liquid-tight flexible metal conduit.

2.2 CONDUIT FASTENINGS

- .1 One-hole PVC straps to secure surface conduits 50mm and smaller. Two-hole PVC straps for conduits larger than 50mm. Use stainless steel screws/bolts for mounting hardware.
- .2 Channel type supports for two or more conduits at 1.5 oc.
- .3 6mm diameter threaded rods to support suspended channels.

2.3 CONDUIT FITTINGS

- .1 Fittings manufactured for use with conduit specified. Coating: same as conduit. “O” ring expansion joints and watertight junction box adapters/couplings. Provide PVC expansion joints at all structural expansion joints and at all locations where PVC conduit exits underground.
- .2 Factory “ells” where 90 degree bends are required for conduits larger than 40mm.
- .3 Steel set screw connectors and couplings for EMT unless indicated otherwise.
- .4 Steel watertight connectors and couplings for EMT where indicated.
- .5 Terminate all spare conduits with PVC conduit caps where not terminated in a junction box, cabinet or panel.

2.4 FISH CORD

- .1 Polypropylene in all spare conduits.

Part 3 Execution**3.1 INSTALLATION**

- .1 Install conduits to conserve space in exposed locations and cause minimum interference in spaces through which they pass.
- .2 Use rigid PVC conduit under ground floor slab and in poured concrete unless indicated otherwise. Install an integral ground wire in all PVC conduit.
- .3 Use liquid tight flexible metal conduit for connections to exterior light fixtures unless indicated otherwise and to equipment in damp or wet locations.
- .4 Install fish cord in empty conduits.
- .5 Where conduits become blocked, remove and replace blocked section.
- .6 Dry conduits out before installing wire.
- .7 Conduit sizing, where indicated, is based on copper conductors and PVC conduit. NUAL is not to be used.
- .8 Use rigid steel conduit for exterior exposed above grade work.
- .9 Use EMT for interior feeders and branch circuit work except in poured concrete, underground and where subject to mechanical damage, unless indicated otherwise. When used for panel feeders, install a separate integral ground wire sized in accordance with the CEC.
- .10 Use flexible metal conduit for connection to motors in dry areas and interior light fixtures.
- .11 Bend conduit cold. Replace conduit if kinked or flattened more than 1/10th of its original diameter.
- .12 Mechanically bend steel conduit over 19mm diameter.
- .13 Field threads on rigid conduit must be of sufficient length to draw conduits up tight.

3.2 SURFACE CONDUITS

- .1 Run parallel or perpendicular to construction lines.
- .2 Run conduits in center portion of concrete wharf deck.
- .3 Group conduits wherever possible.
- .4 Do not pass conduits through structural members.

3.3 CONDUITS IN CAST-IN-PLACE CONCRETE

- .1 Locate to suit reinforcing steel. Install in centre one-half of slab.
- .2 Protect conduits from damage where they stub out of concrete.
- .3 Install sleeves where conduits pass through slab or wall.
- .4 Where conduits pass through waterproof membrane, provide oversized sleeve before membrane is installed. Use cold mastic between sleeve and conduit.
- .5 Encase conduits completely in concrete.

3.4 CONDUITS IN CAST-IN-PLACE SLABS ON GRADE

- .1 Run conduits 25mm and larger below slab. Provide 50mm of sand over conduits below floor slab.

3.5 CONDUITS UNDERGROUND

- .1 Slope conduits to provide drainage.
- .2 Conduits rising up from below grade to penetrate the floor/wharf at 90° angles. Slanted conduits not permitted.

3.6 CONDUIT SEALANT

- .1 All conduit terminations entering buildings or enclosures, to be sealed to prevent entrance of water and condensation.
- .2 Sealant to be a two-part polyurethane conduit, sealing compound installed as per manufacturer's instructions.
- .3 Standard of acceptance:
 - .1 Multi-urethanes Multi-Paste.

END OF SECTION

Part 1 General**1.1 CABLE TRAY STANDARDS**

- .1 Cable trays shall be non-ventilated type to CAN/CSA-C22.2 No. 126.

Part 2 Products**2.1 CABLETROUGH**

- .1 Cabletroughs and fittings: to CAN/CSA-C22.2 No. 126.
- .2 Non-ventilated style.
- .3 Stainless steel 316 grade finish; 150mm high, 900mm wide c/w 316 grade S/S cover c/w cover clamps.
- .4 Fittings and ground clamps: all required manufactured accessories for the cabletrough supplied. To be 316 grade finish.

2.2 SUPPORTS

- .1 Provide 316 grade S/S supports as indicated and/or as required, with end cut so as to not project more than 25mm from edge of hanger.

Part 3 Execution**3.1 INSTALLATION**

- .1 Install cabletrough support systems as indicated or as required.
- .2 Support cabletrough with hanger brackets attached to underside of concrete deck with 75mm S/S anchor bolts and threaded 13mm 316 grade S/S rod or anchors in concrete.
- .3 Remove sharp burrs or projections to prevent damage to cables or injury to personnel.
- .4 All fittings shall be field formed as needed.
- .5 Grounding to Code requirements.

3.2 CABLES IN CABLETROUGH

- .1 Install cables individually.
- .2 Secure cables in cabletrough with nylon ties.
- .3 Identify cables in accordance with Section 26 05 00.

END OF SECTION

Part 1 General**1.1 DESCRIPTION OF WORK**

- .1 Work included in this section consists of the excavating, backfilling and trenching required to install cables and ducts by general contractor and supply and installation of ducts, spacers and marker tape by Division 26.

1.2 RELATED WORK

- .1 Concrete-encased underground cable duct: Section 26 05 41.

1.3 PROTECTION

- .1 Protect excavated earth to be reused from freezing by approved method.
- .2 Grade around excavations to prevent surface water runoff into excavated area.

1.4 INSPECTION & TESTING

- .1 Testing of materials and compaction will be carried out by testing laboratory designated by Departmental Representative.
- .2 Departmental Representative will pay costs for inspection and testing.

1.5 UTILITY LINES

- .1 Before commencing work, establish location and extent of underground utility lines in area of excavation. Notify Departmental Representative of findings.
- .2 Make good damage to existing utility lines resulting from work.

1.6 PERMITS, FEES & INSPECTIONS

- .1 Obtain prior approval from the Municipality/Departmental Representative for street cuts. Pay any fees required.
- .2 Repairs to meet Municipality/Departmental Representative standards and approval.

Part 2 Products

2.1 BACKFILL MATERIALS

- .1 Bedding sand: clean, washed, coarse bank sand free from clay, shale and organic matter.
- .2 Common backfill materials: excavated soil selected from trench bottom or from other source, free from roots, rocks larger than 75mm and building debris and approved by Departmental Representative before used as fill.
- .3 Granular backfill:
 - .1 Clean, hard, durable, uncoated particles free from clay lumps, cementation, organic or other objectionable material, meeting following gradation limits:

<u>ASTM Sieve Designation</u>	<u>% Passing</u>
50.0 mm	100
31.5 mm	60 -100
16.0 mm	40 - 75
4.75 mm	25 - 60
2.0 mm	20 - 45
425 micrometers	10 - 25
75 micrometers	0 – 10

2.2 CABLE MARKER SHEET

- .1 Polyethylene marker sheet: to be 150mm wide for burial 300mm below grade directly over buried cable.
- .2 Marker sheet to be orange in colour with the following words printed in large black block letters: "CAUTION CAUTION CAUTION - BURIED ELECTRIC LINE BELOW".

The above-described message is to be printed every 914mm minimum of marker sheet.

Part 3 Execution

3.1 EXCAVATIONS

- .1 Excavate to lines, grades, elevations and dimensions as indicated on drawings or as directed.
- .2 Cut edges of asphalt pavement with suitable cutting wheel or jack hammer and saw cut reinforced concrete deck prior to excavation. Cut only to width required to install services.

- .3 Remove unsuitable material from trench bottom to extent and depth directed by Departmental Representative.
- .4 Stockpile suitable excavated materials required for trench backfill in approved location.
- .5 Dispose of surplus and unsuitable excavation material off site.
- .6 Where required due to removal of unsuitable material or unauthorized over excavation, bring bottom of excavation to design grade with common backfill material.
- .7 Compact trench bottom to density at least equal to density of adjacent surrounding soil.
- .8 Excavations require inspection and approval prior to commencement of installation operations.

3.2 BEDDING INSTALLATION

- .1 Place sand bed in trenches where cable ducts are direct buried.
- .2 Ensure that trench has been excavated to the proper required depth.
- .3 Cover bottom of trench with 75mm of sand.
- .4 Lay cable ducts in trench in accordance with Section 26 05 41.

3.3 BACKFILLING & COMPACTION

- .1 Do not proceed with final trench backfilling operations until installation of cable ducts is complete and that Departmental Representative has inspected installations.
- .2 Use approved common backfill material as indicated or directed.
- .3 Backfill around installation as shown.
- .4 Place backfill material in uniform layers not exceeding 150mm in thickness up to sub-grade elevation or top of trench. Compact each layer before placing succeeding layer.
- .5 Compact common backfill materials as follows:
 - .1 In non-pavement areas to a density at least equal to density of adjacent, undisturbed soil.
 - .2 In pavement areas and sod areas to a minimum of 95% density for ASTM D698-78 maximum density.

- .6 Dispose of surplus backfill material off property after backfilling operations are complete.

3.4 CABLE MARKER TAPE

- .1 Install polyethylene marker tape in trenches where cables are installed in cable ducts.
- .2 Place marker tape 300mm below final grade; continuous over full length of cable run.

3.5 RESTORATION OF EXISTING SURFACES AFFECTED

- .1 The following paragraphs are intended for complete reinstatement of all the existing surfaces disturbed by the excavations of this section.
- .2 Where existing grassed areas are encountered during excavations, stock pile reusable materials for replacement after cable or duct installation and backfilling are completed.
- .3 Where existing asphalt pavement is encountered during excavations, remove all asphalt debris from site and after cable duct installation and backfilling are completed, provide new base coarse and asphalt pavement to match existing.

END OF SECTION

Part 1 General**1.1 RELATED WORK**

- .1 Trenching: Section 26 05 40.
- .2 Concrete Formwork: Section 03 10 00.
- .3 Concrete Reinforcement: Section 03 20 00.
- .4 Cast-in-place Concrete: Section 03 30 00.

Part 2 Products**2.1 MATERIALS**

- .1 PVC underground telecommunications cable ducting: to CSA B196.3.
- .2 Plastic underground power cable ducting: to CSA B196.1.

2.2 PVC DUCTS

- .1 PVC ducts, type DB2, encased in reinforced concrete, size as indicated for power and telephone.

2.3 PVC DUCT FITTINGS

- .1 Rigid PVC opaque solvent welded type couplings, balloon-end fittings, plugs, caps, adapters as required to make complete installation.
- .2 Expansion joints as indicated.
- .3 Rigid PVC 5° angle couplings as indicated.
- .4 Base and intermediate plastic spacers as required.
- .5 Rigid PVC 90° & 45° bends as required.

2.4 RIGID STEEL CONDUITS

- .1 To Section 26 05 34.
- .2 Couplings, reducers, plugs, caps, adapter and supports as required to make a complete installation.
- .3 Use long sweep bends only.

2.5 CABLE PULLING EQUIPMENT

- .1 6mm stranded polypropylene bare pull rope tensile strength 5kn continuous throughout each duct run with 3m spare rope at each end.

2.6 MARKERS

- .1 Over all underground duct and pipe runs, install continuously, at 300mm below grade, 75mm wide electrical underground polyethylene marking tape with warning "CAUTION CAUTION CAUTION, UNDERGROUND LINES BELOW".

Part 3 Execution**3.1 INSTALLATION - GENERAL**

- .1 Install reinforced concrete encased underground duct banks, including form work.
- .2 Build duct bank on undisturbed soil or on well-compacted granular fill not less than 150mm thick, compacted to 95% of maximum proctor dry density.
- .3 Open trench completely before ducts are laid and ensure that no obstructions will necessitate change in grade of ducts.
- .4 Install ducts at elevations and with slope as indicated and minimum slope of 1 to 400.
- .5 Install base spacers at maximum intervals of 1.5m levelled to grades indicated for bottom layer of ducts.
- .6 Lay PVC ducts with configuration and reinforcing as indicated with preformed interlocking, rigid plastic intermediate spacers to maintain spacing between ducts at not less than 75mm

horizontally and vertically. Stagger joints in adjacent layers at least 150mm and make joints watertight. Encase duct bank with 75mm thick concrete cover. Use galvanized steel conduit for sections extending above finished grade level.

- .7 Make transpositions, offsets and changes in direction using 5 degree bends sections, do not exceed a total of 20 degrees with duct offset.
- .8 Terminate duct runs with a duct coupling set flush with the end of the concrete envelope when dead ending duct bank for future extension.
- .9 Cut, ream and taper end of ducts infield to manufacturer's recommendations, so that duct ends are fully equal to factory-made ends.
- .10 Allow concrete to attain 50% of its specified strength before backfilling.
- .11 Use conduit to duct adapters when connecting to conduits
- .12 Use anchors, ties and trench jacks as required to secure ducts and prevent moving during pouring of concrete. Tie ducts to spacers with twine or other non-metallic material. Remove weights or wood braces before concrete has set and fill voids.
- .13 Clean ducts before laying. Cap ends of ducts during construction and after installation to prevent entrance of foreign materials.
- .14 Immediately after pouring of concrete, pull through each duct a mandrel followed by a stiff bristle brush to remove sand, earth and other foreign matter. Avoid disturbing or damaging ducts where concrete has not set completely. Pull stiff bristle brush through each duct immediately before pulling in cables.
- .15 Install four 3m lengths of 15M reinforcing rods, one in each corner of duct bank when connecting duct to buildings.

3.2 INSPECTIONS

- .1 Advise Departmental Representative so that he may inspect ducts prior to pouring and be present during pour of concrete and clean-out.

END OF SECTION

Part 1 General

Not applicable.

Part 2 Products

Not applicable.

Part 3 Execution**3.1 CABLE INSTALLATION IN DUCTS**

- .1 Install cables as indicated in ducts.
- .2 Do not pull spliced cables inside ducts.
- .3 Install multiple cables in duct simultaneously.
- .4 Use CSA approved lubricants of type compatible with cable jacket to reduce pulling tension.
- .5 To facilitate matching of colour coded multi-conductor control cables; reel off in same direction during installation.
- .6 Before pulling cable into ducts and until cables are properly terminated, seal ends of cables with moisture seal tape.
- .7 After installation of cables, seal duct ends with duct sealing compound.
- .8 Install in each empty conduit a pull rope continuous throughout each duct run with 3m spare at each end.

3.2 FIELD QUALITY CONTROL

- .1 Perform tests in accordance with Section 26 05 00.
- .2 Perform tests using qualified personnel. Provide necessary instruments and equipment.
- .3 Check phase rotation and identify each phase conductor of each feeder.

- .4 Check each feeder for continuity, short circuits and grounds. Ensure resistance to ground of circuits is no less than 50 megohms.
- .5 Tests:
 - .1 After installing cable, but before splicing and terminating, perform insulation resistance test with 1000V megger on each phase conductor.
 - .2 Check insulation resistance after each termination to ensure that cable system is no Less than 50 megohms.
- .6 Provide Departmental Representative with list of test results showing location at which each test was made, circuit tested and result of each test.
- .7 Remove and replace entire length of cable if cable fails to meet any of the test criteria.

END OF SECTION

Part 1 General**1.1 RELATED WORK**

- .1 Excavation and Backfilling: Section 26 05 40.

Part 2 Products**2.1 MATERIALS**

- .1 Plastic underground power cable ducting: to CSA B196.1.

2.2 PVC DUCTS

- .1 PVC ducts, size as indicated for power and telephone.

2.3 PVC DUCT FITTINGS

- .1 Rigid PVC opaque solvent welded type couplings, plugs, caps, adapters as required to make complete installation.
- .2 Expansion joints as indicated.
- .3 Rigid PVC 5° angle couplings as indicated.

2.4 CABLE PULLING EQUIPMENT

- .1 6mm stranded nylon pull rope tensile strength 5kn.

2.5 MARKERS

- .1 150mm wide polyethylene marker tape with wording "CAUTION CAUTION CAUTION – UNDERGROUND CABLES BELOW", installed continuously over all underground ducts, 300mm below finished grade.

Part 3 Execution**3.1 INSTALLATION**

- .1 Install duct as indicated and in accordance with manufacturer's instructions.
- .2 Clean inside of ducts before laying.
- .3 Ensure full and even support every 1.5m throughout duct length.
- .4 Slope ducts as indicated with 1 to 400 minimum slope.
- .5 During construction, cap ends of ducts to prevent entrance of foreign materials.
- .6 Pull through each duct a steel or wooden mandrel not less than 300mm long and of a diameter 6mm less than internal diameter of duct, followed by stiff bristle brush to remove sand, earth and other foreign matter. Pull stiff bristle brush through each duct immediately before pulling in cables.
- .7 In each duct, install pull rope continuous throughout each duct run with 3.0m spare rope at each end.

END OF SECTION

Part 1 General

1.1 RELATED STANDARDS

- .1 NSPI Service Entrance Standard: (Existing completed in 2016 but Contractor will have to get NS Power to disconnect and reconnect service when Panel 'A' enclosure is raised 1 meter from bottom of cabinet to new grade raised one (1) meter above existing grade).

1.2 COORDINATION WITH POWER SUPPLY AUTHORITY

- .1 Coordinate and meet requirements of local power supply authority. Ensure availability of power when required.
- .2 Arrange for primary line extensions, utility installation and energization.

1.3 UTILITY COST

- .1 The installation of the primary and secondary service to be included in the Contract Price.
- .2 Any fees or costs required by the Utility to remove existing and provide new service is to be paid for by the Contractor as part of the Contract Price.

Part 2 Products

2.1 MATERIALS

- .1 PVC conduit, necessary fittings: to Section 26 05 34.
- .2 Electrical contractor to carry lump sum amount of \$2,000.00 in his tendered price to pay for all charges by NSPI based on NSPI invoice amount with no contractor mark-up. Unused amount will be returned to the Departmental Representative.

Part 3 Execution

3.1 INSTALLATION

- .1 Fit-up service pole to NSPI Standard Construction Practice. Terminate communications and power ducts on opposite sides of pole.
- .2 Install primary ducts as indicated.

- .3 Install meter sockets.
- .4 Install secondary ducts, conduit and wire as indicated.
- .5 Allow adequate conductor length for connection to supply by power supply authority.
- .6 Make grounding connections in accordance with Section 26 05 28.
- .7 Install secondary conduits as indicated.
- .8 Install cables in underground ducts and conduit as indicated.

END OF SECTION

Part 1 General

1.1 RELATED STANDARDS

- .1 Complete service entrance to conform to NSPI Service Entrance Standards and as detailed on drawings. (Completed in 2016)

1.2 SHOP DRAWINGS AND PRODUCT DATA

- .1 Submit shop drawings and product data in accordance with Section 26 05 00.

Part 2 Products

2.1 SUPPLY DATA

- .1 Service equipment suitable for incoming power supply:
 - .1 400A, 120/240V, 1Ø, 3W, 60Hz grounded neutral as indicated on drawings.

Part 3 Execution

3.1 INSTALLATION

- .1 Install service equipment as indicated.
- .2 Connect to incoming service as indicated.
- .3 Connect to outgoing load circuits as indicated.
- .4 Make grounding connections in accordance with Section 26 05 28 and Utility Service Entrance Standards.
- .5 Make provision for power supply authority's metering to meet their requirements.

END OF SECTION

Part 1 General

1.1 SHOP DRAWINGS & PRODUCT DATA

- .1 Submit shop drawings and product data in accordance with Section 26 05 00.

Part 2 Products

2.1 SWITCHES

- .1 15A, 120V, single pole, as indicated.
- .2 Manually operated general purpose ac switches as indicated and with the following features:
 - .1 Terminal holes approved for No. 10 AWG wire.
 - .2 Silver alloy contacts.
 - .3 Urea or melamine moulding for parts subject to carbon tracking.
 - .4 Suitable for back and side wiring.
 - .5 Black toggle.
 - .6 Marine grade.
- .3 Toggle operated fully rated for tungsten filament and fluorescent lamp, and up to 80% of rated capacity of motor loads.
- .4 Switches of one manufacturer throughout project.
- .5 Standard of acceptance:
 - .1 For 15A, 120V almond switches:
 - .1 Arrow Hart
 - .2 Bryant
 - .3 Hubbell #CS115BK c/w HBL17 CM50 coverplate
 - .4 Leviton
 - .5 Pass & Seymour

2.2 RECEPTACLES

- .1 Marine grade duplex receptacles as indicated, CSA Type 5-20 R, 125V, 20A, U ground, with the following features:
 - .1 Yellow urea moulded housing, nylon front.
 - .2 Suitable for No. 10 AWG for back and side wiring.
 - .3 Break-off links for use as split receptacle.
 - .4 Eight back wired entrances, four side wiring contacts.
 - .5 Double wipe contacts and riveted grounding contacts.
- .2 Acceptable manufacturers or approved equal:
 - .1 Hubbell #HBL53CM62/HBL52CM21
 - .2 Leviton

.3 Pass & Seymour

.3 Single marine grade 20A, 120V receptacle twist lock c/w in-use coverplate and backbox:
.1 Hubbell #HBL23CM10/MX5280SNC/HBL60CM83

.4 Single Marine Grade 30A 120V receptacle twist-lock c/w in-use coverplate and backbox:
.1 Hubbell # HBL26CM10/MX5280SNC/HBL60CM83

2.3 COVERPLATES

.1 Coverplates for wiring devices.

.2 Coverplate from one manufacturer throughout project.

.3 One-gang weather proof coverplate for wiring devices mounted on a surface mounted outlet box, Hubbell No. HBL52CM21 or HBL74CM25WOA.

2.4 PLYWOOD, WOOD POSTS AND POLES

.1 Plywood to be 27mm thick marine grade.

.2 Wood posts to be 200 x 200 x 3600mm pressure treated.

.3 Wood poles to be Class 3 Jack Pine, 15 meters long, pressure treated.

.4 All bolts, washers, lock washers and nuts for wood connections to be hot dipped galvanized steel.

2.5 EXPANSION JOINTS (53mm WABBLE JOINT)

.1 Expansion joints to be IPEX Cat. #SE-I-35 (flex hose part #072047 and 4 S/S clamps part #075020) or equal.

Part 3 Execution

3.1 INSTALLATION

.1 Switches:

.1 Install single throw switches with handles in "UP" position when switch closed.

.2 Install switches in gang type outlet box when more than one switch is required in one location.

.3 Mount toggle switches at height specified in Section 26 05 00 or as indicated.

- .2 Receptacles:
 - .1 Install receptacles in gang type outlet box when more than one receptacle is required in one location.
 - .2 Mount receptacles at height specified in Section 26 05 00 or as indicated.
- .3 Cover plates:
 - .1 Protect cover plate finish with paper or plastic film until painting and other work is finished.
 - .2 Do not use cover plates meant for flush outlet boxes on surface mounted boxes.
 - .3 Install suitable common cover plates where wiring devices are grouped.
- .4 Use only screw down terminals for connecting wiring devices to circuits.
- .5 Install pin and sleeve receptacles and convenience receptacles as indicated.

3.2 IDENTIFICATION

- .1 Identify all outlets with size 5 nameplate indicating source, circuit number, voltage, ampacity and phasing.
- .2 Provide separate nameplate to identify outlets for use by “Fisherman” or “Buyer”.

END OF SECTION

Part 1 General

1.1 SHOP DRAWINGS & PRODUCT DATA

- .1 Submit shop drawings and product data in accordance with Section 26 05 00.

1.2 MAINTENANCE MATERIALS

- .1 Provide maintenance materials in accordance with Section 26 05 00.
- .2 Three spare fuses of each type and size installed up to and including 600A.

1.3 DELIVERY & STORAGE

- .1 Ship fuses in original containers.
- .2 Do not ship fuses installed.
- .3 Store fuses in original containers in storage cabinet.

Part 2 Products

2.1 FUSES - GENERAL

- .1 HRC fuses: to have interrupting capability of 200,000 A symmetrical.
- .2 Fuses: product of one manufacturer.

2.2 FUSE TYPES

- .1 HRC-1 fuses (formerly Class L):
 - .1 Type L2, fast acting, plus two spares.
- .2 100% rates fuses where indicated (Type J).
- .3 Fuses in junction box at bottom of wood pole to be GEC #CRS30H fuse fitted with 6 Amp Type C fuse for camera disconnect; and GEC #CRS30H fuse fitted with 8 Amp Type C fuse for 2-350W LED light fixtures.

2.3 MANUFACTURERS

- .1 Acceptable manufacturers or approved equal:

- .1 English Electric
- .2 GEC Canada Ltd.
- .3 Gould-Shawmut Company
- .4 Littelfuse

Part 3 Execution

3.1 INSTALLATION

- .1 Install fuses in mounting devices immediately before energizing circuit.
- .2 Ensure correct fuses fitted to physically matched mounting devices.
- .3 Ensure correct fuses fitted to assigned electrical circuit.

END OF SECTION

Part 1 General**1.1 RELATED SECTIONS**

- .1 Read and be governed by Section 26 05 00.

1.2 RELATED WORK

- .1 Comply with relevant Sections of this and other Divisions of this Specification.

1.3 ACCEPTABLE MATERIALS

- .1 Where materials are specified by the trade name within this section, refer to Section 00 21 14 for procedure to be followed in applying for approval of alternatives.

Part 2 Products**2.1 MATERIALS**

- .1 Ground fault circuit interrupters Class 'A' shall be manufactured to CSA and Electrical Bulletin No. 752.
- .2 Components forming the ground fault protective system, to be of same manufacturer.

2.2 SYSTEM NO. 1 – BREAKER TYPE

- .1 Ground fault interrupter breakers shall be suitable for 20A, 30A, 120V, 1P circuits and shall be complete with:
 - .1 Automatic shunt trip circuit breaker.
 - .2 Zero sequence transformer.
 - .3 Overcurrent, short circuit and GFI protection.
 - .4 Facilities for testing and reset.
 - .5 Maximum 5mA trip.

Part 3 Execution**3.1 INSTALLATION**

- .1 Neutral must not be grounded on load side of ground fault relay.

- .2 Phase conductors and neutral must pass through zero sequence transformers.
- .3 Connect supply and load wiring to equipment in accordance with manufacturer's recommendations.

3.2 FIELD QUALITY CONTROL

- .1 Perform tests in accordance with Section 26 05 00 – Electrical General Requirements.
- .2 Demonstrate simulated ground fault tests.

END OF SECTION

Part 1 General**1.1 PRODUCT DATA**

- .1 Submit product data in accordance with Section 26 05 00.
- .2 Include time current characteristic curves for breakers with ampacity of 400A and over.

Part 2 Products**2.1 BREAKERS GENERAL**

- .1 Bolt-on moulded case circuit breaker: quick-make, quick-break type, for manual and automatic operation with temperature compensation for 40°C ambient.
- .2 Common-trip breakers with single handle for multi-pole applications.
- .3 Magnetic instantaneous trip elements in circuit breakers, to operate only when the value of current reaches setting. Trip settings on breakers with adjustable trips to range from 3 - 10 times current rating.
- .4 Circuit breakers with interchangeable trips as indicated.
- .5 100% rated circuit breakers where indicated on drawings.

2.2 THERMAL MAGNETIC BREAKERS

- .1 Moulded case circuit breaker to operate automatically by means of thermal and magnetic tripping devices to provide inverse time current tripping.

2.3 OPTIONAL FEATURES

- .1 Include ground fault interrupting capability (5ma maximum) where indicated.

2.4 MANUFACTURERS

- .1 Acceptable manufacturer or approved equal:
 - .2 Cutler-Hammer – to match equipment in Phase 1 work.

Part 3 Execution

3.1 INSTALLATION

- .1 Install circuit breakers as indicated.

END OF SECTION

Part 1 General**1.1 PRODUCT DATA**

- .1 Submit product data in accordance with Section 26 05 00.

Part 2 Products**2.1 DISCONNECT SWITCHES**

- .1 Enclosed manual air break switches in non-hazardous locations: to DSA C22.2 No. 4.
- .2 Fuseholder assemblies to CSA C22.2 No. 39.
- .3 Heavy-duty fusible disconnect switch in CSA type 4X 316 grade stainless steel enclosure.
- .4 Provision for padlocking in ON-OFF switch position complete with heavy-duty padlock.
- .5 Mechanically interlocked door to prevent opening when handle in ON position.
- .6 Quick-make, quick-break action.
- .7 Fuseholders in each fused switch suitable without adapters, for type of fuse as indicated.
- .8 ON-OFF switch position indication on switch enclosure cover.

2.2 EQUIPMENT IDENTIFICATION

- .1 Provide equipment identification in accordance with Section 26 05 00.
- .2 Indicate name of load controlled on size 4 nameplate.

2.3 MANUFACTURERS

- .1 Acceptable manufacturers or approved equal:
 - .1 Cutler-Hammer – to match equipment in Phase 1 work.

Part 3 Execution**3.1 INSTALLATION**

- .1 Install disconnect switches complete with fuses as indicated.

END OF SECTION

Part 1 General

1.1 SHOP DRAWINGS

- .1 Submit shop drawings in accordance with Section 26 05 00.
- .2 Submit complete photometric data prepared by independent testing laboratory for luminaires specified, for review by Departmental Representative.

1.2 EQUIVALENT MANUFACTURERS

- .1 The manufacturer and catalogue numbers used herein are to establish an acceptable standard of quality. Equivalent products by the listed luminaire manufacturers may be used as alternatives subject to verification of photometric data and construction material at the shop drawing stage.
- .2 Standard of acceptance:
 - .1 Holophane – to match equipment in Phase 1 work.

Part 2 Products

2.1 LED LIGHT ENGINE

- .1 Light engine to have 353W of high powered LED's with nine (9) modules.
- .2 CRI to be 70 with colour temperature of 4000K.
- .3 LED driver to be rated for 100,000 hours.
- .4 Delivered lumens to be 29,456 with current of 1050ma @ 120V.
- .5 BUG rating of B3-U3-G3.
- .6 Acceptable manufacturer:
 - .1 Holophane Cat. #PLLED-9-4K-10A – to match equipment in Phase 1 work.

2.2 FINISHES

- .1 Baked enamel finish:
 - .1 Conditioning for metal before painting:
 - .1 For corrosion resistance conversion coating to CGSB 31-GP-103M.
 - .2 For paint base, conversion coating to CGSB 31-GP-105M, CGSB 31-GP-106A.
 - .2 Metal surfaces of luminaire housing and reflectors finished with high gloss baked enamel to give smooth, uniform appearance, free from pinholes or defects.

- .3 Inside surfaces finished as follows:
 - .1 White, minimum reflection factor 85%.
 - .2 Colour fastness: yellowness factor not above 0.02 and after 250 hr. exposure in Atlas fadeometer not to exceed 0.05.
 - .3 Film thickness, not less than 0.3mm average, and in no areas less than 0.025mm.
 - .4 Gloss not less than 80 units as measured with Gardner 60 deg. glossmeter.
 - .5 Flexibility: withstand bending over 12mm mandrel without showing signs of cracking or flaking under 10 times magnification.
 - .6 Adhesion: 24mm square lattice made of 3mm squares cut through film to metal with sharp razor blade. Adhesive cellulose tape applied over lattice and bulled. Adhesion satisfactory if no coating removed.
- .2 Alzak finish:
 - .1 Aluminium sheet fabricated from special aluminium alloys and chemically brightened, subsequently anodically treated to specifications established by Alcoa, to produce:
 - .1 Finish for mild commercial service, minimum density of coating 0.8 mg/sq.cm., minimum reflectivity 83% for specular and 75% for diffuse.
 - .2 Finish for regular industrial service, minimum density of coating 1.2 mg/sq.cm., minimum reflectivity 82% for specular and 73% for diffuse.
 - .3 Finish for heavy duty service, minimum density of coating 1.5 mg/sq.cm. minimum reflectivity 78% for specular 65% for diffuse.

2.4 LUMINAIRE – TYPE A

<u>ITEM</u>	<u>DESCRIPTION</u>	<u>LED</u>	<u>MOUNTING</u>
1.	FLOOD LIGHT WITH 353 WATTS OF LED'S	HOLOPHANE 9-4K-10A – TO MATCH EQUIPMENT IN PHASE 1 WORK	1. MOUNTED ON 316 GRADE STAINLESS STEEL YOKE AND 08657- GP SLIP FITTER – 53mm ADAPTER FOR WOOD POLE
2.	SEALED OPTICAL SYSTEM IP65 RATED		
3.	EPA RATED AT 0.125 SQ. METERS		
4.	WEIGHT 19.1 KG		
5.	REDUCED GLARE WITH REFLECTOR AND INTERNAL PRISM REFRACTORS		

(Cont'd)

<u>ITEM</u>	<u>DESCRIPTION</u>	<u>LED</u>	<u>MOUNTING</u>
6.	LED's TO HAVE INDIVIDUAL PRE-ORIENTED LENS TO PROVIDE TYPE 3 ASYMETRICAL DISTRIBUTION		
7.	LUMINAIRE TO BE CUSTOM PAINTED WITH CLEAR COAT		
8.	ACCEPTABLE MANUFACTURER HOLOPHANE CAT. #PLLED-9-4K-10A-AS-45-5-L-GP-05-23-08657-GP		

Part 3 Execution

3.1 INSTALLATION

- .1 Locate and install luminaires as indicated.
- .2 Supply and install all material required for proper mounting of all luminaires.

3.2 WIRING

- .1 Connect luminaires to lighting circuits.

3.3 LUMINAIRE ALIGNMENT

- .1 Align luminaires mounted individually parallel or perpendicular to building grid lines.
- .2 Align luminaires at night-time under direction of Departmental Representative. Allow for four hours time with three men and bucket truck so that alignment can be made to satisfaction of client.

END OF SECTION