

Part 1 General

1.1 REFERENCE STANDARDS

- .1 CSA Group
 - .1 CSA C22.1-18 Canadian Electrical Code, Part 1 (24th Edition), Safety Standard for Electrical Installations.
 - .2 CSA C22.2 No. 0-10 (R2015) – General Requirements – Canadian electrical code, part II.
 - .3 CAN/CSA-C22.3 No.1-10, Overhead Systems.
 - .4 CAN3-C235-83(R2010), Preferred Voltage Levels for AC Systems, 0 to 50,000 V.
- .2 Institute of Electrical and Electronics (IEEE)/National Electrical Safety Code Product Line (NESC)
 - .1 IEEE SP1122-2000, The Authoritative Dictionary of IEEE Standards Terms, 7th Edition.

1.2 DEFINITIONS

- .1 Electrical and electronic terms: unless otherwise specified or indicated, terms used in these specifications, and on drawings, are those defined by IEEE SP1122.

1.3 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Shop drawings:
 - .1 Submit drawings stamped and signed by professional engineer registered or licensed in Province of Manitoba, Canada.
 - .2 Submit wiring diagrams and installation details of equipment indicating proposed location, layout and arrangement, control panels, accessories, piping, ductwork, and other items that must be shown to ensure co-ordinated installation.
 - .3 Identify on wiring diagrams circuit terminals and indicate internal wiring for each item of equipment and interconnection between each item of equipment.
 - .4 Indicate of drawings clearances for operation, maintenance, and replacement of operating equipment devices.
 - .5 Submit two (2) number of copies of 600 x 900 mm minimum size drawings to authority having jurisdiction.
 - .6 If changes are required, notify Departmental Representative of these changes before they are made.
- .3 Certificates:
 - .1 Provide CSA certified equipment.
 - .2 Where CSA certified equipment is not available, submit such equipment to inspection authorities for approval before delivery to site.
 - .3 Submit test results of installed electrical systems and instrumentation.

- .4 Permits and fees: in accordance with General Conditions of contract.
- .5 Submit, upon completion of Work, load balance report as described in PART 3 - LOAD BALANCE.
- .6 Submit certificate of acceptance from authority having jurisdiction upon completion of Work to Departmental Representative.

1.4 CLOSEOUT SUBMITTALS

- .1 Submit in accordance with Section 01 78 00 - Closeout Submittals.
- .2 Operation and Maintenance Data: submit operation and maintenance data for lighting, lighting controls, fire alarm, access control, and intrusion alarm for incorporation into manual.
 - .1 Provide for each system and principal item of equipment as specified in technical sections for use by operation and maintenance personnel.
 - .2 Operating instructions to include following:
 - .1 Wiring diagrams, control diagrams, and control sequence for each principal system and item of equipment.
 - .2 Start up, proper adjustment, operating, lubrication, and shutdown procedures.
 - .3 Safety precautions.
 - .4 Procedures to be followed in event of equipment failure.
 - .5 Other items of instruction as recommended by manufacturer of each system or item of equipment.
 - .3 Print or engrave operating instructions and frame under glass or in approved laminated plastic.
 - .4 Post instructions where directed.
 - .5 For operating instructions exposed to weather, provide weather-resistant materials or weatherproof enclosures.
 - .6 Ensure operating instructions will not fade when exposed to sunlight and are secured to prevent easy removal or peeling.

1.5 DELIVERY, STORAGE AND HANDLING

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements.
- .2 Delivery and Acceptance Requirements: deliver materials to site in original factory packaging, labelled with manufacturer's name and address.
- .3 Storage and Handling Requirements:
 - .1 Store materials indoors and in accordance with manufacturer's recommendations in clean, dry, well-ventilated area.
 - .2 Store and protect from nicks, scratches, and blemishes.
 - .3 Replace defective or damaged materials with new.

Part 2 Products

2.1 DESIGN REQUIREMENTS

- .1 Operating voltages: to CAN3-C235.
- .2 Motors, electric heating, control and distribution devices and equipment to operate satisfactorily at 60 Hz within normal operating limits established by above standard.
 - .1 Equipment to operate in extreme operating conditions established in above standard without damage to equipment.
- .3 Language operating requirements: provide identification nameplates for control items in English.

2.2 MATERIALS AND EQUIPMENT

- .1 Provide material and equipment in accordance with Section 01 61 00 - Common Product Requirements.
- .2 Material and equipment to be CSA certified. Where CSA certified material and equipment are not available, obtain special approval from inspection authorities before delivery to site and submit such approval as described in PART 1 - ACTION AND INFORMATIONAL SUBMITTALS.
- .3 Factory assemble control panels and component assemblies.

2.3 ELECTRIC MOTORS, EQUIPMENT AND CONTROLS

- .1 Verify installation and co-ordination responsibilities related to motors, equipment and controls, as indicated.
- .2 Control wiring and conduit: in accordance with mechanical specifications and drawings.

2.4 WARNING SIGNS

- .1 Warning Signs: in accordance with requirements of authority having jurisdiction.
- .2 Decal signs, minimum size 175 x 250 mm.

2.5 WIRING TERMINATIONS

- .1 Ensure lugs, terminals, screws used for termination of wiring are suitable for either copper or aluminum conductors.

2.6 EQUIPMENT IDENTIFICATION

- .1 Identify electrical equipment with nameplates and labels as follows:
 - .1 Nameplates: lamacoid 3 mm black face, white core, lettering accurately aligned and engraved into core, mechanically attached with self-tapping screws.
 - .2 Sizes as follows:

NAMEPLATE SIZES			
Size 1	10 x 50 mm	1 line	3 mm high letters
Size 2	12 x 70 mm	1 line	5 mm high letters
Size 3	12 x 70 mm	2 lines	3 mm high letters
Size 4	20 x 90 mm	1 line	8 mm high letters

Size 5	20 x 90 mm	2 lines	5 mm high letters
Size 6	25 x 100 mm	1 line	12 mm high letters
Size 7	25 x 100 mm	2 lines	6 mm high letters

- .2 Labels: embossed plastic labels with 6 mm high letters unless specified otherwise.
- .3 Wording on nameplates to be approved by Departmental Representative prior to manufacture.
- .4 Allow for minimum of twenty-five (25) letters per nameplate.
- .5 Nameplates for terminal cabinets and junction boxes to indicate system and/or voltage characteristics.
- .6 Disconnects, starters and contactors: indicate equipment being controlled and voltage.
- .7 Terminal cabinets and pull boxes: indicate system and voltage.
- .8 Transformers: indicate capacity, primary and secondary voltages.

2.7 WIRING IDENTIFICATION

- .1 Identify wiring with permanent indelible identifying markings, numbered, on both ends of phase conductors of feeders and branch circuit wiring.
- .2 Maintain phase sequence and colour coding throughout.
- .3 Colour coding: to CSA C22.1.
- .4 Use colour coded wires in communication cables, matched throughout system.

2.8 CONDUIT AND CABLE IDENTIFICATION

- .1 Colour code conduits, boxes and metallic sheathed cables.
- .2 Code with plastic tape or paint at points where conduit or cable enters wall, ceiling, or floor, and at 15 m intervals.
- .3 Colours: 25 mm wide prime colour and 20 mm wide auxiliary colour.

Type	Prime	Auxiliary
up to 250 V	Yellow	
up to 600 V	Yellow	Green
up to 5 kV	Yellow	Blue
up to 15 kV	Yellow	Red
Fire Alarm	Red	
Emergency Voice	Red	Blue
Other Security Systems	Red	Yellow

Part 3 Execution

3.1 EXAMINATION

- .1 Verification of Conditions: verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for installation in accordance with manufacturer's written instructions.
 - .1 Visually inspect substrate in presence of Departmental Representative.

- .2 Inform Departmental Representative of unacceptable conditions immediately upon discovery.
- .3 Proceed with installation only after unacceptable conditions have been remedied.

3.2 INSTALLATION

- .1 Do complete installation in accordance with CSA C22.1 except where specified otherwise.
- .2 Ensure manufacturer's nameplates, CSA labels and identification nameplates are visible and legible after equipment is installed.

3.3 CONDUIT AND CABLE INSTALLATION

- .1 Install cables, conduits and fittings embedded or plastered over, close to building structure so furring can be kept to minimum.

3.4 LOCATION OF OUTLETS

- .1 Locate outlets in accordance with Section 26 05 32 - Outlet Boxes, Conduit Boxes and Fittings.
- .2 Do not install outlets back-to-back in wall; allow minimum 150 mm horizontal clearance between boxes.
- .3 Change location of outlets at no extra cost or credit, providing distance does not exceed 3000 mm, and information is given before installation.
- .4 Locate light switches on latch side of doors.
 - .1 Locate disconnect devices in mechanical and elevator machine rooms on latch side of floor.

3.5 MOUNTING HEIGHTS

- .1 Mounting height of equipment is from finished floor to centreline of equipment unless specified or indicated otherwise.
- .2 If mounting height of equipment is not specified or indicated, verify before proceeding with installation.
- .3 Install electrical equipment at following heights unless indicated otherwise.
 - .1 Local switches: 1400 mm.
 - .2 Wall receptacles:
 - .1 General: 300 mm.
 - .2 Above top of continuous baseboard heater: 200 mm.
 - .3 Above top of counters or counter splash backs: 175 mm.
 - .4 In mechanical rooms: 1400 mm.
 - .3 Panelboards: as required by Code or as indicated.
 - .4 Telephone and interphone outlets: 300 mm.
 - .5 Fire alarm stations: 1500 mm.
 - .6 Fire alarm bells: 2100 mm.

- .7 Television outlets: Coordinate behind television location. 300mm.

3.6 CO-ORDINATION OF PROTECTIVE DEVICES

- .1 Ensure circuit protective devices such as overcurrent trips, relays and fuses are installed to required values and settings.

3.7 FIELD QUALITY CONTROL

- .1 Load Balance:
 - .1 Measure phase current to panelboards with normal loads (lighting) operating at time of acceptance; adjust branch circuit connections as required to obtain best balance of current between phases and record changes.
 - .2 Measure phase voltages at loads and adjust transformer taps to within 2% of rated voltage of equipment.
 - .3 Provide upon completion of work, load balance report as directed in PART 1 - ACTION AND INFORMATIONAL SUBMITTALS, phase and neutral currents on panelboards, dry-core transformers and motor control centres, operating under normal load, as well as hour and date on which each load was measured, and voltage at time of test.
- .2 Conduct following tests in accordance with Section 01 45 00 - Quality Control.
 - .1 Power distribution system including phasing, voltage, grounding and load balancing.
 - .2 Circuits originating from branch distribution panels.
 - .3 Lighting and its control.
 - .4 Motors, heaters and associated control equipment including sequenced operation of systems where applicable.
 - .5 Systems: fire alarm.
 - .6 Insulation resistance testing:
 - .1 Megger circuits, feeders and equipment up to 350 V with a 500 V instrument.
 - .2 Megger 350-600 V circuits, feeders and equipment with a 1000 V instrument.
 - .3 Check resistance to ground before energizing.
- .3 Carry out tests in presence of Departmental Representative.
- .4 Provide instruments, meters, equipment and personnel required to conduct tests during and at conclusion of project.

3.8 SYSTEM STARTUP

- .1 Instruct operating personnel in operation, care and maintenance of systems, system equipment and components.

3.9 CLEANING

- .1 Progress Cleaning: clean in accordance with Section 01 74 00 - Cleaning.
 - .1 Leave Work area clean at end of each day.

- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 00 - Cleaning.

END OF SECTION

Part 1 General

1.1 REFERENCES

- .1 CSA Group (CSA)
 - .1 CAN/CSA-C22.2 No.18-98(R2003), Outlet Boxes, Conduit Boxes and Fittings.
 - .2 CAN/CSA-C22.2 No.65-03(R2008), Wire Connectors (Tri-National Standard with UL 486A-486B and NMX-J-543-ANCE-03).
- .2 Electrical and Electronic Manufacturers' Association of Canada (EEMAC)
 - .1 EEMAC 1Y-2-1961, Bushing Stud Connectors and Aluminum Adapters (1200 Ampere Maximum Rating).
- .3 National Electrical Manufacturers Association (NEMA)

1.2 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
 - .1 Submit manufacturer's instructions, printed product literature and data sheets for wire and box connectors and include product characteristics, performance criteria, physical size, finish and limitations.

1.3 CLOSEOUT SUBMITTALS

- .1 Submit in accordance with Section 01 78 00 - Closeout Submittals.
- .2 Operation and Maintenance Data: submit operation and maintenance data for wire and box connectors for incorporation into manual.

1.4 DELIVERY, STORAGE AND HANDLING

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements.
- .2 Delivery and Acceptance Requirements: deliver materials to site in original factory packaging, labelled with manufacturer's name and address.
- .3 Storage and Handling Requirements:
 - .1 Store materials indoors and in accordance with manufacturer's recommendations in clean, dry, well-ventilated area.
 - .2 Store and protect wire and box connectors from nicks, scratches, and blemishes.
 - .3 Replace defective or damaged materials with new.

Part 2 Products

2.1 MATERIALS

- .1 Pressure type wire connectors to: CAN/CSA-C22.2 No.65, with current carrying parts of copper sized to fit copper conductors as required.
- .2 Fixture type splicing connectors to: CAN/CSA-C22.2 No.65, with current carrying parts of copper sized to fit copper conductors 10 AWG or less.

- .3 Clamps or connectors for aluminum sheathed cable and flexible conduit as required to:
CAN/CSA-C22.2 No.18.

Part 3 Execution

3.1 EXAMINATION

- .1 Verification of Conditions: verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for wire and box connectors installation in accordance with manufacturer's written instructions.
 - .1 Visually inspect substrate in presence of Departmental Representative.
 - .2 Inform Departmental Representative of unacceptable conditions immediately upon discovery.
 - .3 Proceed with installation only after unacceptable conditions have been remedied.

3.2 INSTALLATION

- .1 Remove insulation carefully from ends of conductors and cables:
 - .1 Apply coat of zinc joint compound on aluminum conductors prior to installation of connectors.
 - .2 Install mechanical pressure type connectors and tighten screws with appropriate compression tool recommended by manufacturer. Installation shall meet secureness tests in accordance with CAN/CSA-C22.2 No.65.
 - .3 Install fixture type connectors and tighten to CAN/CSA-C22.2 No.65. Replace insulating cap.

3.3 CLEANING

- .1 Progress Cleaning: clean in accordance with Section 01 74 00 - Cleaning.
 - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 00 - Cleaning.

END OF SECTION

Part 1 General

1.1 NOT USED.

Part 2 Products

2.1 BUILDING WIRES

- .1 Conductors: stranded for 10 AWG and larger. Minimum size: 12 AWG.
- .2 Copper conductors: size as indicated, with 600V insulation of cross-linked thermosetting polyethylene material rated RW90 XLPE, Jacketted.

2.2 ARMOURED CABLES

- .1 Conductors: insulated, copper, size as indicated.
- .2 Type: AC90.
- .3 Armour: interlocking type fabricated from galvanized steel strip.
- .4 Type: ACWU90 PVC jacket over thermoplastic armour and compliant to applicable Building Code classification for this project.
- .5 Connectors: anti short connectors.

2.3 CONTROL CABLES

- .1 Type: LVT: 2 soft annealed copper conductors, sized as indicated:
 - .1 Insulation: Thermoplastic.
 - .2 Sheath: Thermoplastic jacket and armour of closely wound aluminum wire.

Part 3 Execution

3.1 FIELD QUALITY CONTROL

- .1 Perform tests in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Perform tests using method appropriate to site conditions and to approval of Departmental Representative and local authority having jurisdiction over installation.
- .3 Perform tests before energizing electrical system.

3.2 GENERAL CABLE INSTALLATION

- .1 Terminate cables in accordance with Section 26 05 20 - Wire and Box Connectors - (0-1000 V).
- .2 Cable Colour Coding: to Section 26 05 00 - Common Work Results for Electrical.
- .3 Conductor length for parallel feeders to be identical.
- .4 Lace or clip groups of feeder cables at distribution centres, pull boxes, and termination points.

- .5 Wiring in walls: typically drop or loop vertically from above to better facilitate future renovations. Generally wiring from below and horizontal wiring in walls to be avoided unless indicated.
- .6 Branch circuit wiring for surge suppression receptacles and permanently wired computer and electronic equipment to be 2-wire circuits only, i.e. common neutrals not permitted.
- .7 Provide numbered wire collars for control wiring. Numbers to correspond to control shop drawing legend. Obtain wiring diagram for control wiring.

3.3 INSTALLATION OF BUILDING WIRES

- .1 Install wiring as follows:
 - .1 In conduit systems in accordance with Section 26 05 34 - Conduits, Conduit Fastenings and Conduit Fittings.

3.4 INSTALLATION OF ARMoured CABLES

- .1 Group cables wherever possible on channels.

3.5 INSTALLATION OF ALUMINUM SHEATHED CABLE

- .1 Group cables wherever possible on channels.

3.6 INSTALLATION OF CONTROL CABLES

- .1 Install control cables in conduit.
- .2 Ground control cable shield.

END OF SECTION

Part 1 General

1.1 REFERENCE STANDARDS

- .1 CSA-C22.1-18, Canadian Electrical Code, Part I (24th Edition), Safety Standard for Electrical Installations

Part 2 Products

2.1 EQUIPMENT

- .1 Grounding conductors: bare stranded copper, soft annealed, size as indicated.
- .2 Insulated grounding conductors: green, copper conductors, size as indicated.
- .3 Ground bus: copper, size as indicated, complete with insulated supports, fastenings, connectors.

Part 3 Execution

3.1 EXAMINATION

- .1 Verification of Conditions: verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for grounding equipment installation in accordance with manufacturer's written instructions.
 - .1 Visually inspect substrate in presence of Departmental Representative.
 - .2 Inform Consultant and Departmental Representative of unacceptable conditions immediately upon discovery.
 - .3 Proceed with installation only after unacceptable conditions have been remedied and after receipt of written approval to proceed from Departmental Representative or Consultant.

3.2 INSTALLATION GENERAL

- .1 Install connectors in accordance with manufacturer's instructions.
- .2 Protect exposed grounding conductors from mechanical injury.
- .3 Use mechanical connectors for grounding connections to equipment provided with lugs.
- .4 Soldered joints not permitted.
- .5 Install bonding wire for flexible conduit, connected at both ends to grounding bushing, solderless lug, clamp or cup washer and screw. Neatly cleat bonding wire to exterior of flexible conduit.
- .6 Install flexible ground straps for bus duct enclosure joints, where such bonding is not inherently provided with equipment.
- .7 Connect building structural steel and metal siding to ground by welding copper to steel.
- .8 Make grounding connections in radial configuration only, with connections terminating at single grounding point. Avoid loop connections.
- .9 Bond single conductor, metallic armoured cables to cabinet at supply end, and load end.

- .10 Ground secondary service pedestals.

3.3 EQUIPMENT GROUNDING

- .1 Install grounding connections to typical equipment included in, but not necessarily limited to following list. Service equipment, transformers, switchgear, duct systems, frames of motors, motor control centres, starters, control panels, building steel work, generators, elevators and escalators, distribution panels, outdoor lighting, cable trays.

3.4 COMMUNICATION SYSTEMS

- .1 Install grounding connections for telephone, sound, fire alarm, security systems, intercommunication systems as follows:
 - .1 Telephones: make telephone grounding system in accordance with telephone company's requirements.
 - .2 Sound, fire alarm, security systems, intercommunication systems as indicated.

3.5 FIELD QUALITY CONTROL

- .1 Perform tests in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Perform ground continuity and resistance tests using method appropriate to site conditions and to approval of Departmental Representative and local authority having jurisdiction over installation.
- .3 Perform tests before energizing electrical system.
- .4 Disconnect ground fault indicator during tests.

3.6 CLEANING

- .1 Progress Cleaning: clean in accordance with Section 01 74 00 - Cleaning.
 - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 00 - Cleaning.

END OF SECTION

Part 1 General

1.1 CONSTRUCTION WASTE MANAGEMENT AND DISPOSAL

- .1 Remove from site and dispose of all packaging materials at appropriate recycling facilities.
- .2 Divert unused metal materials from landfill to metal recycling facility as approved by Departmental Representative.
- .3 Fold up metal banding, flatten and place in designated area for recycling.

Part 2 Products

2.1 SUPPORT CHANNELS

- .1 U shape, size 41 x 41 mm, 2.5 mm thick, surface mounted and suspended.

Part 3 Execution

3.1 INSTALLATION

- .1 Secure equipment to solid masonry, tile and plaster surfaces with lead anchors.
- .2 Secure equipment to poured concrete with expandable inserts.
- .3 Secure equipment to hollow masonry walls or suspended ceilings with toggle bolts.
- .4 Secure surface mounted equipment with twist clip fasteners to inverted T bar ceilings. Ensure that T bars are adequately supported to carry weight of equipment specified before installation.
- .5 Support equipment, conduit or cables using clips, spring loaded bolts, cable clamps designed as accessories to basic channel members.
- .6 Fasten exposed conduit or cables to building construction or support system using straps.
 - .1 One-hole steel straps to secure surface conduits and cables 50 mm and smaller.
 - .2 Two-hole steel straps for conduits and cables larger than 50 mm.
 - .3 Beam clamps to secure conduit to exposed steel work.
- .7 Suspended support systems.
 - .1 Support individual cable or conduit runs with 6 mm diameter threaded rods and spring clips.
 - .2 Support 2 or more cables or conduits on channels supported by 6 mm diameter threaded rod hangers where direct fastening to building construction is impractical.
- .8 For surface mounting of two or more conduits use channels at 900mm on centre spacing.

- .9 Provide metal brackets, frames, hangers, clamps and related types of support structures where indicated or as required to support conduit and cable runs.
- .10 Ensure adequate support for raceways and cables dropped vertically to equipment where there is no wall support.
- .11 Do not use wire lashing or perforated strap to support or secure raceways or cables.
- .12 Do not use supports or equipment installed for other trades for conduit or cable support except with permission of other trade and approval of Departmental Representative.
- .13 Install fastenings and supports as required for each type of equipment cables and conduits, and in accordance with manufacturer's installation recommendations.

3.2 CLEANING

- .1 Progress Cleaning: clean in accordance with Section 01 74 00 - Cleaning.
 - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 00 - Cleaning.

END OF SECTION

Part 1 General

1.1 REFERENCE STANDARDS

- .1 CSA Group (CSA)
 - .1 CSA C22.1-18, Canadian Electrical Code, Part 1, 24th Edition.

1.2 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Provide submittals in accordance with Section 01 33 00 - Submittal Procedures.

Part 2 Products

2.1 JUNCTION AND PULL BOXES

- .1 Construction: welded steel enclosure.
- .2 Covers Flush Mounted: 25 mm minimum extension all around.
- .3 Covers Surface Mounted: screw-on flat covers.

Part 3 Execution

3.1 JUNCTION, PULL BOXES AND CABINETS INSTALLATION

- .1 Install pull boxes in inconspicuous but accessible locations.
- .2 Mount cabinets with top not higher than 2 m above finished floor except where indicated otherwise.
- .3 Only main junction and pull boxes are indicated. Install additional pull boxes as required by CSA C22.1.

3.2 IDENTIFICATION

- .1 Equipment Identification: to Section 26 05 00 - Common Work Results for Electrical.
- .2 Identification Labels: size 2 indicating voltage and phase, system name or as indicated.

END OF SECTION

Part 1 General

1.1 REFERENCE STANDARDS

- .1 CSA Group (CSA)
 - .1 CSA C22.1-18, Canadian Electrical Code, Part 1, 24th Edition.

1.2 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Provide submittals in accordance with Section 01 33 00 - Submittal Procedures.

1.3 DELIVERY, STORAGE AND HANDLING

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements.

Part 2 Products

2.1 OUTLET AND CONDUIT BOXES GENERAL

- .1 Size boxes in accordance with CSA C22.1.
- .2 102 mm square or larger outlet boxes as required.
- .3 Gang boxes where wiring devices are grouped.
- .4 Blank cover plates for boxes without wiring devices.
- .5 347 V outlet boxes for 347 V switching devices.
- .6 Combination boxes with barriers where outlets for more than one system are grouped.

2.2 GALVANIZED STEEL OUTLET BOXES

- .1 One-piece electro-galvanized construction.
- .2 Single and multi-gang flush device boxes for flush installation, minimum size 76 x 50 x 38 mm or as indicated. 102 mm square outlet boxes when more than one conduit enters one side with extension and plaster rings as required.
- .3 Utility boxes for outlets connected to surface-mounted EMT conduit, minimum size 102 x 54 x 48 mm. Connectors and fittings for EMT conduit shall be watertight.
- .4 102 mm square or octagonal outlet boxes for lighting fixture outlets.
- .5 Extension and plaster rings for flush mounting devices in finished walls.

2.3 FITTINGS - GENERAL

- .1 Bushing and connectors with nylon insulated throats.
- .2 Knock-out fillers to prevent entry of debris.
- .3 Conduit outlet bodies for conduit up to 35mm and pull boxes for larger conduits.
- .4 Double locknuts and insulated bushings on sheet metal boxes.

Part 3 Execution

3.1 INSTALLATION

- .1 Support boxes independently of connecting conduits.
- .2 Fill boxes with paper, sponges or foam or similar approved material to prevent entry of debris during construction. Remove upon completion of work.
- .3 For flush installations mount outlets flush with finished wall using plaster rings to permit wall finish to come within 6 mm of opening.
- .4 Provide correct size of openings in boxes for conduit, mineral insulated and armoured cable connections. Do not install reducing washers.
- .5 Vacuum clean interior of outlet boxes before installation of wiring devices.
- .6 Identify systems for outlet boxes as required.

END OF SECTION

Part 1 General

1.1 REFERENCE STANDARDS

- .1 CSA Group (CSA)
 - .1 CAN/CSA C22.2 No. 18-98 (R2003). Outlet Boxes, Conduit Boxes, Fittings and Associated Hardware, A National Standard of Canada.
 - .2 CSA C22.2 No. 45-M1981 (R2003), Rigid Metal Conduit.
 - .3 CSA C22.2 No. 56-04, Flexible Metal Conduit and Liquid-Tight Flexible Metal Conduit.
 - .4 CSA C22.2 No. 83-M1985 (R2003), Electrical Metallic Tubing.
 - .5 CSA C22.2 No. 211.2-M1984 (R2003), Rigid PVC (Unplasticized) Conduit.
 - .6 CAN/CSA C22.2 No. 227.3-05, Nonmetallic Mechanical Protection Tubing (NMPT), A National Standard of Canada (February 2006).

1.2 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Provide submittals in accordance with Section 01 33 00 - Submittal Procedures.

Part 2 Products

2.1 CONDUITS

- .1 Electrical metallic tubing (EMT): to CSA C22.2 No. 83, with couplings.
- .2 Flexible metal conduit: to CSA C22.2 No. 56, steel.

2.2 CONDUIT FASTENINGS

- .1 One hole steel straps to secure surface conduits 50 mm and smaller.
 - .1 Two hole steel straps for conduits larger than 50 mm.
- .2 Beam clamps to secure conduits to exposed steel work.
- .3 Channel type supports for two or more conduits at 900mm on centre.
- .4 Threaded rods, 6 mm diameter, to support suspended channels.

2.3 CONDUIT FITTINGS

- .1 Fittings to CAN/CSA C22.2 No. 18, manufactured for use with conduit specified. Coating: same as conduit.
- .2 Ensure factory "ells" where 90 degrees bends for 25 mm and larger conduits.
- .3 Watertight connectors and couplings for EMT.
 - .1 Set-screws are not acceptable.

2.4 FISH CORD

- .1 Polypropylene.

Part 3 Execution

3.1 MANUFACTURER'S INSTRUCTIONS

- .1 Compliance: comply with manufacturer's written recommendations or specifications, including product technical bulletins, handling, storage and installation instructions, and datasheets.

3.2 INSTALLATION

- .1 Install conduits to conserve headroom in exposed locations and cause minimum interference in spaces through which they pass.
- .2 Conceal conduits except in mechanical and electrical service rooms.
- .3 Use rigid galvanized steel threaded conduit except where specified otherwise.
- .4 Use electrical metallic tubing (EMT).
- .5 Use flexible metal conduit for connection to motors in dry areas, connection to recessed incandescent fixtures without prewired outlet box, connection to surface or recessed fluorescent fixtures, and work in movable metal partitions.
- .6 Use liquid tight flexible metal conduit for connection to motors or vibrating equipment in damp, wet or corrosive locations.
- .7 Minimum conduit size for lighting and power circuits: 19 mm.
- .8 Bend conduit cold:
 - .1 Replace conduit if kinked or flattened more than 1/10th of its original diameter.
- .9 Mechanically bend steel conduit over 19 mm diameter.
- .10 Install fish cord in empty conduits.
- .11 Remove and replace blocked conduit sections.
 - .1 Do not use liquids to clean out conduits.
- .12 Dry conduits out before installing wire.

3.3 SURFACE CONDUITS

- .1 Run parallel or perpendicular to building lines.
- .2 Locate conduits behind infrared or gas fired heaters with 1.5 m clearance.
- .3 Run conduits in flanged portion of structural steel.
- .4 Group conduits wherever possible on suspended channels.
- .5 Do not pass conduits through structural members except as indicated.
- .6 Do not locate conduits less than 75 mm parallel to steam or hot water lines with minimum of 25 mm at crossovers.

3.4 CONCEALED CONDUITS

- .1 Run parallel or perpendicular to building lines.
- .2 Do not install horizontal runs in masonry walls.
- .3 Do not install conduits in terrazzo or concrete toppings.

3.5 CLEANING

- .1 Proceed in accordance with Section 01 74 00 - Cleaning.
- .2 On completion and verification of performance of installation, remove surplus materials, excess materials, rubbish, tools and equipment.

END OF SECTION

Part 1 General

1.1 REFERENCE STANDARDS

- .1 CSA Group (CSA)
 - .1 CSA C22.2 No.42-10, General Use Receptacles, Attachment Plugs and Similar Devices.
 - .2 CAN/CSA C22.2 No.42.1-00 (R2009), Cover Plates for Flush-Mounted Wiring Devices (Bi-national standard, with UL 514D).
 - .3 CSA C22.2 No.55-M1986 (R2008), Special Use Switches.
 - .4 CSA C22.2 No.111-10, General-Use Snap Switches (Bi-national standard, with UL 20).

1.2 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
 - .1 Submit manufacturer's instructions, printed product literature and data sheets for wiring devices and include product characteristics, performance criteria, physical size, finish and limitations.

1.3 DELIVERY, STORAGE AND HANDLING

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements.
- .2 Delivery and Acceptance Requirements: deliver materials to site in original factory packaging, labelled with manufacturer's name and address.
- .3 Storage and Handling Requirements:
 - .1 Store materials indoors and in accordance with manufacturer's recommendations in clean, dry, well-ventilated area.
 - .2 Store and protect wiring devices from nicks, scratches, and blemishes.
 - .3 Replace defective or damaged materials with new.

Part 2 Products

2.1 SWITCHES

- .1 Manually-operated general purpose AC switches with following features:
 - .1 Terminal holes approved for No. 10 AWG wire.
 - .2 Silver alloy contacts.
 - .3 Urea or melamine moulding for parts subject to carbon tracking.
 - .4 Suitable for back and side wiring.
 - .5 Ivory toggle.

- .2 Switches of one manufacturer throughout project.

2.2 RECEPTACLES

- .1 Duplex receptacles, CSA type 5-15 R, 125 V, 15 A, U ground, to: CSA C22.2 No.42 with following features:
 - .1 Ivory urea moulded housing.
 - .2 Suitable for No. 10 AWG for back and side wiring.
 - .3 Break-off links for use as split receptacles.
 - .4 Eight back wired entrances, four side wiring screws.
 - .5 Triple wipe contacts and riveted grounding contacts.
- .2 Other receptacles with ampacity and voltage as indicated.
- .3 Receptacles of one manufacturer throughout project.

2.3 COVER PLATES

- .1 Cover plates for wiring devices to: CSA C22.2 No.42.1.
- .2 Sheet steel utility box cover for wiring devices installed in surface-mounted utility boxes.
- .3 Stainless steel, 1 mm thick cover plates for wiring devices mounted in flush-mounted outlet box.

2.4 SOURCE QUALITY CONTROL

- .1 Cover plates from one manufacturer throughout project.

Part 3 Execution

3.1 INSTALLATION

- .1 Switches:
 - .1 Install single throw switches with handle in “UP” position when switch closed.
 - .2 Install switches in gang type outlet box when more than one switch is required in one location.
 - .3 Mount toggle switches at height in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Receptacles:
 - .1 Install receptacles in gang type outlet box when more than one receptacle is required in one location.
 - .2 Mount receptacles at height in accordance with Section 26 05 00 - Common Work Results for Electrical.
 - .3 Install GFCI type receptacles as indicated.
- .3 Cover plates:
 - .1 Install suitable common cover plates where wiring devices are grouped.
 - .2 Do not use cover plates meant for flush outlet boxes on surface-mounted boxes.

3.2 CLEANING

- .1 Progress Cleaning: clean in accordance with Section 01 74 00 - Cleaning.
 - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 00 - Cleaning.

3.3 PROTECTION

- .1 Protect installed products and components from damage during construction.
- .2 Protect stainless steel cover plate finish with paper or plastic film until painting and other work is finished.
- .3 Repair damage to adjacent materials caused by wiring device installation.

END OF SECTION

Part 1 General

1.1 REFERENCE STANDARDS

- .1 American National Standards Institute (ANSI)
 - .1 ANSI C82.1-04, Lamp Ballasts-Line Frequency Fluorescent Lamp Ballast.
- .2 American National Standards Institute/Institute of Electrical and Electronics Engineers (ANSI/IEEE)
 - .1 ANSI/IEEE C62.41-1991, Recommended Practice for Surge Voltages in Low-Voltage AC Power Circuits.
- .3 ASTM International Inc.
 - .1 ASTM F1137-00 (2006), Standard Specification for Phosphate/Oil and Phosphate/Organic Corrosion Protective Coatings for Fasteners.
- .4 CSA Group (CSA)
- .5 Underwriters' Laboratories of Canada (ULC)

1.2 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Provide submittals in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
 - .1 Provide manufacturer's printed product literature, specifications and datasheet and include product characteristics, performance criteria, physical size, finish and limitations.

1.3 DELIVERY, STORAGE AND HANDLING

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements.
- .2 Deliver materials to site in original factory packaging, labelled with manufacturer's name, address.
- .3 Divert unused metal materials from landfill to metal recycling facility.
- .4 Disposal and recycling of fluorescent lamps as per local regulations.

Part 2 Products

2.1 LED Luminaires and Drivers

- .1 All Luminaires
 - .1 Comply with IES LM-79-08 Approved Method for measuring lumen maintenance of LED light sources.
 - .2 Comply with IES LM-80-08 Approved Method for electrical and photometric measurement of SSL product.
 - .3 LEDs shall be Restriction of Hazardous Substances Directive (RoHS) compliant.
 - .4 LED arrays shall be sealed, high performance, long life type; minimum 70% rated output at 50,000 hours.

- .5 LED luminaires shall deliver a minimum of 60 lumens per watt.
 - .1 LEDs shall be "Bin No. 1" quality.
- .6 Drivers shall be solid state and accept 347VAC at 60 Hz input.
- .7 The LED light source shall be fully dimmable with use of compatible dimmers switch designated for low voltage loads.
- .8 LED color temperatures: CRI 85, 4000K as noted +/- 275K.
- .9 Luminaires shall have internal thermal protection.
- .10 Luminaires shall not draw power in the off state. Luminaires with integral occupancy, motion, photo-controls, or individually addressable luminaires with external control and intelligence are exempt from this requirement. The power draw for such luminaires shall not exceed 0.5 watts when in the off state.
- .11 Color spatial uniformity shall be within .004 of CIE 1976 diagram.
- .12 Color maintenance over rated life shall be within .007 of CIE 1976.
- .13 Indoor luminaires shall have a minimum CRI of 85.
- .14 Luminaire manufacturers shall adhere to device manufacturer guidelines, certification programs, and test procedures for thermal management
- .15 LED package(s)/module(s)/array(s) used in qualified luminaires shall deliver a minimum 70% of initial lumens, when installed in-situ, for a minimum of 50,000 hours.
- .16 Luminaires shall be fully accessible from below ceiling plane for changing drivers, power supplies and arrays.
- .17 Minimum acceptable warranty for LED Drivers shall be 50,000 hrs
- .2 Power Supplies and Drivers
 - .1 MB Hydro Powersmart approved.
 - .2 Power Factor: 0.90 or higher
 - .3 Maximum driver case temperature not to exceed driver manufacturer recommended in-situ operation.
 - .4 Output operating frequency: 60Hz.
 - .5 Interference: EMI and RFI compliant with FCC 47 CFR Part 15.
 - .6 Total Harmonic Distortion Rating: 20% Maximum.
 - .7 Meet electrical and thermal conditions as described in LM-80 Section 5.0.
 - .8 Primary Current: Confirm primary current with Drawings.
 - .9 Secondary Current: Confirm secondary current specified by individual luminaire manufacturers.
 - .10 Compatibility: Certified by manufacturer for use with individually specified luminaire and individually specified control components.
 - .11 Solid-state control components to be integral or external per each specified luminaire.
- .3 Controller and Control System
 - .1 System electronics driver / controller to use coordinated communication protocols: 0-10V.
 - .2 The Contractor to ensure that external control equipment is compatible with LED control requirements
 - .3 Provide connector types and wiring as appropriate for un-interrupted communication between devices, considering distance maximums, field

obstructions, and accessibility. Ensure that connection points are optically isolated for system noise reduction.

- .4 Compatibility: Certified by manufacturer for use with individually specified luminaire and individually specified power supplies and/or drivers

2.2 FINISHES

- .1 Light fixture finish and construction to meet ULC listings and CSA certifications related to intended installation.

2.3 LUMINAIRES

- .1 As indicated in luminaire schedule.

Part 3 Execution

3.1 INSTALLATION

- .1 Locate and install luminaires as indicated.
- .2 Provide adequate support to suit ceiling system.

3.2 WIRING

- .1 Connect luminaires to lighting circuits:
 - .1 Install flexible or rigid conduit for luminaires as indicated.

3.3 LUMINAIRE SUPPORTS

- .1 For suspended ceiling installations support luminaires from ceiling grid in accordance with local inspection requirements.

3.4 LUMINAIRE ALIGNMENT

- .1 Align luminaires mounted in continuous rows to form straight uninterrupted line.
- .2 Align luminaires mounted individually parallel or perpendicular to building grid lines.

3.5 CLEANING

- .1 Clean in accordance with Section 01 74 00 - Cleaning.
 - .1 Remove surplus materials, excess materials, rubbish, tools and equipment.

END OF SECTION

Part 1 General

1.1 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
 - .1 Submit manufacturer's instructions, printed product literature and data sheets for communication raceway systems and include product characteristics, performance criteria, physical size, finish and limitations.

Part 2 Products

2.1 SYSTEM DESCRIPTION

- .1 Telecommunications raceways system consists of outlet boxes, cover plates, conduits, pull boxes, sleeves and caps, fish wires, service poles, and service fittings.
- .2 Existing overhead cable tray distribution system.

2.2 MATERIAL

- .1 Conduits: EMT type, in accordance with Section 26 05 34 - Conduits, Conduit Fastenings and Conduit Fittings.
- .2 Cable trays: existing
- .3 Cellular floor raceways: existing
- .4 Fish wire: polypropylene type.

Part 3 Execution

3.1 INSTALLATION

- .1 Modify and extend existing raceway system, including overhead distribution system, fish wire, outlet boxes, floor boxes, pull boxes, cover plates, conduit, sleeves and caps, cable tray, service poles, miscellaneous and positioning material to constitute complete system.

3.2 CLEANING

- .1 Progress Cleaning: clean in accordance with Section 01 74 00 - Cleaning.
 - .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 00 - Cleaning.

3.3 PROTECTION

- .1 Protect installed products and components from damage during construction.

- .2 Repair damage to adjacent materials caused by pathways for communications systems installation.

END OF SECTION

Part 1 General

1.1 REFERENCE STANDARDS

- .1 CSA Group (CSA)
 - .1 CSA-C22.2 No. 214-02, Communications Cables (Bi-National standard with UL 444).
- .2 Telecommunications Industry Association (TIA)/Electronic Industries Alliance (EIA)
 - .1 TIA/EIA-568-B.1-(2001), Commercial Building Telecommunications Cabling Standard, Part 1: General Requirements.
 - .2 TIA/EIA-568-B.2-(2001), Commercial Building Telecommunications Cabling Standard, Part 2: Balanced Twisted-Pair Cabling Components.
 - .3 TIA/EIA-568-B.3-(2000), Optical Fiber Cabling Components Standard.
 - .4 TIA/EIA-606-A-(2002), Administration Standard for the Commercial Telecommunications Infrastructure.
- .3 This scope of work is under Shared Services Canada (SSC).

Part 2 Products

- .1 Not in contract (Shared Services Canada).

Part 3 Execution

3.1 INSTALLATION OF TERMINATION AND CROSS-CONNECT HARDWARE

- .1 Not in contract (Shared Services Canada)

3.2 INSTALLATION OF HORIZONTAL DISTRIBUTION CABLES

- .1 Not in contract (Shared Services Canada)

END OF SECTION