

PART 1 - GENERAL

1.1 RELATED DOCUMENTS .1 Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 REFERENCES .1 CSA C22.1-2012, Canadian Electrical Code, Part 1.

PART 2 - PRODUCTS

2.1 OUTLET AND CONDUIT BOXES GENERAL .1 Size boxes in accordance with CSA C22.1.
.2 102 mm square or larger outlet boxes as required for special devices.
.3 Gang boxes where wiring devices are grouped.
.4 Blank cover plates for boxes without wiring devices.
.5 Combination boxes with barriers where outlets for more than one system are grouped.
.6 See details on drawings for electrical pedestal outlet box types.

2.2 CONDUIT BOXES .1 PVC or fibreglass FS and FD boxes with factory threaded hubs and mounting feet for surface wiring of switches, receptacles and controls. See drawings for details.

2.3 FITTINGS GENERAL .1 Bushing and connectors with nylon insulated throats.
.2 Knock-out fillers to prevent entry of debris.

.3 Conduit outlet bodies for conduit up to 32 mm and pull boxes for larger conduits.

.4 Double locknuts and insulated bushings on sheet metal boxes.

PART 3 - EXECUTION

3.1 INSTALLATION

.1 Support boxes independently of connecting conduits.

.2 Fill boxes with paper, sponges or foam or similar approved material to prevent entry of debris during construction. Remove upon completion of work.

.3 Provide correct size of openings in boxes for conduit, mineral insulated and armoured cable connections. Reducing washers are not allowed.

.4 Provide approved weather tight coverplates for lighting fixture and power pedestal junction boxes.