

Part 1 GENERAL

1.1 REFERENCES

- .1 CSA International
 - .1 CSA C22.2 No.29, Panelboards and Enclosed Panelboards.

1.2 ACTION AND INFORMATIONAL SUBMITTALS

- .1 Submit in accordance with Section 01 33 00 - Submittal Procedures.
- .2 Product Data:
 - .1 Submit manufacturer's instructions, printed product literature and data sheets for panelboards and include product characteristics, performance criteria, physical size, finish and limitations.
- .3 Shop Drawings:
 - .1 Submit drawings stamped and signed by professional engineer registered or licensed in Province of Newfoundland and Labrador, Canada.
 - .2 Include on drawings:
 - .1 Electrical detail of panel, branch breaker type, quantity, ampacity and enclosure dimension.

1.3 CLOSEOUT SUBMITTALS

- .1 Submit in accordance with Section 01 78 00 - Closeout Submittals.
- .2 Operation and Maintenance Data: submit operation and maintenance data for panelboards for incorporation into manual.

1.4 DELIVERY, STORAGE AND HANDLING

- .1 Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements and with manufacturer's written instructions.
- .2 Delivery and Acceptance Requirements: deliver materials to site in original factory packaging, labelled with manufacturer's name and address.
- .3 Storage and Handling Requirements:
 - .1 Store materials indoors in dry location and in accordance with manufacturer's recommendations in clean, dry, well-ventilated area.
 - .2 Store and protect panelboards from nicks, scratches, and blemishes.
 - .3 Replace defective or damaged materials with new.
- .4 Packaging Waste Management: remove for reuse and return of pallets, crates, padding, and packaging materials as specified in Construction Waste Management Plan in

accordance with Section 01 74 21 - Construction/Demolition Waste Management and Disposal.

Part 2 PRODUCTS

2.1 PANELBOARDS

- .1 Panelboards: to CSA C22.2 No.29 and product of one manufacturer.
 - .1 Install circuit breakers in panelboards before shipment.
 - .2 In addition to CSA requirements manufacturer's nameplate must show fault current that panel including breakers has been built to withstand.
- .2 250 V panelboards: bus and breakers rated for 18,000 A (symmetrical) interrupting capacity or as indicated.
- .3 600 V panelboards: bus and breakers rated for 22,000 A (symmetrical) interrupting capacity or as indicated.
- .4 Sequence phase bussing with odd numbered breakers on left and even on right, with each breaker identified by permanent number identification as to circuit number and phase.
- .5 Panelboards: mains, number of circuits, and number and size of branch circuit breakers as indicated.
- .6 Minimum of 2 flush locks for each panel board.
- .7 Two keys for each panelboard and key panelboards alike.
- .8 Copper bus with neutral of same ampere rating of mains.
- .9 Mains: suitable for bolt-on breakers.
- .10 Trim with concealed front bolts and hinges.
- .11 Trim and door finish: baked enamel air dried enamel as per colour schedule.
- .12 All panelboards which serve as main distribution boards (i.e. feed other downstream panels) shall be CDP type or equivalent.

2.2 BREAKERS

- .1 Breakers: to Section 26 28 16.02 - Moulded Case Circuit Breakers.
- .2 Breakers with thermal and magnetic tripping in panelboards except as indicated otherwise.
- .3 Main breaker: separately mounted on top or bottom of panel to suit cable entry. When mounted vertically, down position should open breaker. Rated for 100% duty.

- .4 Lock-on devices for 10% of 15 to 30 A breakers installed as indicated. Turn over unused lock-on devices to Departmental Representative.
- .5 Breakers denoted "LSI" shall be complete with an electronic trip unit – Eaton Type 310+ or equal.

2.3 EQUIPMENT IDENTIFICATION

- .1 Provide equipment identification in accordance with Section 26 05 00 - Common Work Results for Electrical.
- .2 Nameplate for each panelboard size 4 engraved as indicated.
- .3 Complete circuit directory with typewritten legend showing location and load of each circuit, mounted in plastic envelope at inside of panel door.

Part 3 EXECUTION

3.1 EXAMINATION

- .1 Verification of Conditions: verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for panelboards installation in accordance with manufacturer's written instructions.
 - .1 Visually inspect substrate in presence of Departmental Representative.
 - .2 Inform Departmental Representative of unacceptable conditions immediately upon discovery.
 - .3 Proceed with installation only after unacceptable conditions have been remedied and after receipt of written approval to proceed from Departmental Representative.

3.2 INSTALLATION

- .1 Locate panelboards as indicated and mount securely, plumb, true and square, to adjoining surfaces.
- .2 Install surface mounted panelboards on plywood backboards in accordance with Section 06 10 53 - Rough Carpentry. Where practical, group panelboards on common backboard.
- .3 Mount panelboards to height specified in Section 26 05 00 - Common Work Results for Electrical or as indicated.
- .4 Connect loads to circuits.
- .5 Connect neutral conductors to common neutral bus with respective neutral identified.

3.3 CLEANING

- .1 Progress Cleaning: clean in accordance with Section 01 74 11 - Cleaning.

- .1 Leave Work area clean at end of each day.
- .2 Final Cleaning: upon completion remove surplus materials, rubbish, tools and equipment in accordance with Section 01 74 11 - Cleaning.
- .3 Waste Management: separate waste materials for reuse and recycling in accordance with Section 01 74 21 - Construction/Demolition Waste Management and Disposal.
 - .1 Remove recycling containers and bins from site and dispose of materials at appropriate facility.

3.4 PROTECTION

- .1 Protect installed products and components from damage during construction.
- .2 Repair damage to adjacent materials caused by panelboards installation.

END OF SECTION