

PART 1 - GENERAL

- | | | |
|--|----|--|
| <u>1.1 REFERENCES</u> | .1 | Canada Green Building Council (CaGBC)
.1 LEED Canada-NC-2009, LEED (Leadership in Energy and Environmental Design): Green Building Rating System Reference Package For New Construction and Major Renovations. |
| | .2 | CSA Group
.1 CSA C22.2 No.206-13, Lighting Poles. |
| <u>1.2 ACTION AND INFORMATIONAL SUBMITTALS</u> | .1 | Submit in accordance with Section 01 33 00 - Submittal Procedures. |
| | .2 | Product Data:
.1 Submit manufacturer's instructions, printed product literature and data sheets for roadway lighting and include product characteristics, performance criteria, physical size, finish and limitations. |
| | .3 | Sustainable Design Submittals:
.1 LEED Canada submittals: in accordance with Section 01 35 21 - LEED Requirements.
.2 Construction Waste Management:
.1 Submit project Waste Management Plan highlighting recycling and salvage requirements.
.2 Submit calculations on end-of-project recycling rates, salvage rates, and landfill rates demonstrating that 75% of construction wastes were recycled or salvaged. |
| <u>1.3 DELIVERY, STORAGE AND HANDLING</u> | .1 | Deliver, store and handle materials in accordance with Section 01 61 00 - Common Product Requirements and with manufacturer's written instructions. |
| | .2 | Develop Construction Waste Management Plan related to Work of this Section and in accordance with Section 01 35 21 - LEED Requirements. |
-

<u>1.3 DELIVERY, STORAGE AND HANDLING (Cont'd)</u>	.3	Packaging Waste Management: remove for reuse or return of pallets, crates, padding, banding, and packaging materials as specified in Construction Waste Management Plan in accordance with Section 01 74 21 - Construction/Demolition Waste Management and Disposal and Section 01 35 21 - LEED Requirements.
--	----	---

PART 2 - PRODUCTS

<u>2.1 STEEL POLES</u>	.1	Steel poles: to CSA C22.2 No.206 designed for underground wiring and: .1 Mounting on concrete anchor base. .2 Style: as indicated. .3 Straight for 1 luminaire mounting bracket. .4 Access handhole 400 mm above pole base for wiring connections, with welded-on reinforcing frame and bolted-on cover.
------------------------	----	--

<u>2.2 LUMINAIRES</u>	.1	As indicated.
-----------------------	----	---------------

PART 3 - EXECUTION

<u>3.1 EXAMINATION</u>	.1	Verification of Conditions: verify that conditions of substrate previously installed under other Sections or Contracts are acceptable for roadway lighting installation in accordance with manufacturer's written instructions. .1 Visually inspect substrate in presence of Departmental Representative. .2 Inform Departmental Representative of unacceptable conditions immediately upon discovery. .3 Proceed with installation only after unacceptable conditions have been remedied and after receipt of written approval to proceed from Departmental Representative.
------------------------	----	---

- 3.2 INSTALLATION
- .1 Install poles true and plumb, complete with brackets in accordance with manufacturer's instructions.
 - .2 Install luminaires on pole.
 - .3 Check luminaire orientation, level and tilt.
 - .4 Connect luminaire to lighting circuit.
 - .5 Perform tests in accordance with Section 26 05 00 - Common Work Results for Electrical.
- 3.3 CLEANING
- .1 Progress Cleaning: clean in accordance with Section 01 74 11 - Cleaning.
 - .2 Waste Management: separate waste materials for reuse and recycling in accordance with Section 01 74 21 - Construction/Demolition Waste Management and Disposal and Section 01 35 21 - LEED Requirements.
 - .1 Remove recycling containers and bins from site and dispose of materials at appropriate facility.
 - .2 Divert unused concrete materials from landfill to local facility approved by Departmental Representative.